

Mitsubishi Electric
Energy-saving Data Collection Server
EcoWebServer III

Simple - Convenient - Compact
Realizing Energy
Visualization and Demand Management





EcoWebServer III

System Configuration Example

Mitsubishi Electric Energy Management System


Mitsubishi Electric Energy-saving Data Collection Server EcoWebServer III

Support factory, building and school energy-saving activities.
 Build visualized environments and manage energy effectively.
 Support to energy conditions at all times and quickly resolve energy loss problems.
 Finally reduce energy loss, increase productivity and cut production costs.



Support energy-saving activities using "Visible Management"

1. Monitor/Manage energy by department
2. Specific consumption-based management of energy-saving activities
3. Monthly/Annual target-based management
4. Monitor equipment operating status
5. Manage/Record energy data





CONTENTS

- System Configuration Example ... P.2
- Energy-saving Points P.4
- Lineup P.6
- Features P.7
- Example screen P.12
- Application Examples P.14
- Main Unit Specifications..... P.16
- Connection diagram P.17
- Function Comparison/System Environment..... P.18
- External Diagram/Bundled Products List P.19
- Support terminal P.20
- Related Products..... P.21
- Safety Precautions P.22

E-mail notification
(abnormal upper/lower limits, operating status, target value over specific consumption, over planned energy value, error information)

Transfers files in CSV format
(zoom (1 or 5 min), daily, monthly, annual, facility (daily), specific consumption, demand (daily, monthly, annual), demand alarm, control, operation history, system log file)

Acquire time information
Adjust
EcoWebServer III clock




ME96SS

Ethernet (MELSEC communication protocol)

Collects production data

Up to 32 units



MELSEC-Q Series
Energy measuring module /
Insulation monitoring module



MITSUBISHI
GOT

Check demand information
and alarm records onsite

Collects production data


Up to 32 units



Network
monitoring
lamp

**Specific
consumption
management**

CC-Link



MDU breaker

Electronic multi-measuring
instrument
(ME96SS)


Analog input
Temperature input
Contact output
(Enables remote control of load at
locations far from EcoWebServer III)

Air circuit breaker
(AE-SW Series)


**Target-based
management**

Production line

For monitor equipment status



For managing objectives



For improvement activities



Importance of visualizing energy

Essentials Issues for Saving Energy

Target Value Management

Managing objectives is a very important issue when practicing energy savings.

“Target value management” is the process of transforming actual conditions into ideal conditions, and thereby requires understanding the actual situation and how much “unseen” waste there is. For this reason, target value management involves performing detailed management of operations, moving from months to days and lines to equipment, and evolving from “seeing” waste to “understanding” it.

Additionally, when using target value management, it is necessary to construct and put into practice an organization that values “people who set objectives (manage),” “people who find things” and “people capable of thinking of improvements and implementing them.”

Target Value Management



Specific consumption management

In lines where there is a large difference in production volume, it is difficult to save energy and improve productivity using energy management alone.

By understanding specific consumption —energy consumed per product— waste in energy and production processes can be clarified, and it becomes easier to implement countermeasures.

Rather than simply not using energy, it’s important to use energy efficiently when, where and how much needed.

Specific consumption management

EM (Energy loss Minimum) activities

Actual

- No-load power is consumed when there is no production.
- Lights are on in areas where there are no people.
- There are no inverters, so an unnecessary amount of energy is being used.

Improvements

Discover waste

This is specific consumption management

Ideal

Energy required for production:

- **Necessary time** (year, month, day, hour, minute, second...)
- **Necessary place** (all, building, department, production line, equipment)
- **Necessary amount** (technical standards, use/operation standards)

Improve productivity (→ Save energy)

The ideal condition is efficient use of the necessary amount of energy, at the necessary place and necessary time.

Importance of Demand Monitoring

Energy Saving by visualizing demand

What is "Demand"?

Demand is average electric power at a specified period. This period for demand differs for each country and the way of management method.

Electric fee is basically determined based on the highest demand in one year(→contract demand).

The higher the contract demand is, the more expensive the electric basic charge is.


There are two types of basic demand management method as below.

(2) Fixed block demand management method

The demand period consists of only an interval.

Fixed block demand management

Ex) Interval: 30min



(2) Rolling block demand management method


The demand period consists of interval and sub interval.

Interval is the period for calculation of average electric.



Sub interval is the period for update the calculation.

Rolling block demand management method

Ex) Interval: 15min, Sub interval 5min



EcoWebServer III with demand monitoring function comply with the Fixed block demand management method. Interval can be selected from 15min or 30min.



Realize visualization of energy and demand management with one EcoWebServer III.



Mitsubishi Electric Energy-saving Data Collection Server EcoWebServer III



Product name	Energy-saving Data Collection Server
Model no.	MES3-255C-EN
Communication	CC-Link



Product name	Energy-saving Data Collection Server (with demand control function)
Model no.	MES3-255C-DM-EN
Communication	CC-Link

Network Specifications (CC-Link)


Item	Specifications														
Transmission speed	156kbps / 625kbps / 2.5Mbps / 5Mbps / 10Mbps														
Maximum total cable length (maximum transmission distance)	<table border="1"> <tr> <th>Transmission speed</th> <th>Cable length between stations</th> <th>Maximum total cable length</th> </tr> <tr> <td>156kbps</td> <td rowspan="5">20cm or more</td> <td>1200m</td> </tr> <tr> <td>625kbps</td> <td>900m</td> </tr> <tr> <td>2.5Mbps</td> <td>400m</td> </tr> <tr> <td>5Mbps</td> <td>160m</td> </tr> <tr> <td>10Mbps</td> <td>100m</td> </tr> </table>	Transmission speed	Cable length between stations	Maximum total cable length	156kbps	20cm or more	1200m	625kbps	900m	2.5Mbps	400m	5Mbps	160m	10Mbps	100m
	Transmission speed	Cable length between stations	Maximum total cable length												
	156kbps	20cm or more	1200m												
	625kbps		900m												
	2.5Mbps		400m												
5Mbps	160m														
10Mbps	100m														
Maximum number of connected units	64 units However, conditions on the right must be met <table border="1"> <tr> <td>1. Total number of stations</td> <td>$a+b \times 2+c \times 3+d \times 4 \leq 64$</td> </tr> <tr> <td></td> <td>a: 1 station occupied, b: 2 stations occupied, c: 3 stations occupied, d: 4 stations occupied</td> </tr> <tr> <td>2. Number of units connected</td> <td>$16 \times (A+D) + 54 \times B + 88 \times C \leq 2304$</td> </tr> <tr> <td></td> <td>A: Number of remote I/O stations ...64 max</td> </tr> <tr> <td></td> <td>B: Number of remote device stations ...42 max</td> </tr> <tr> <td></td> <td>C: Number of local stations, intelligent device stations ...26 max</td> </tr> <tr> <td></td> <td>D: Number of reserve stations *</td> </tr> </table>	1. Total number of stations	$a+b \times 2+c \times 3+d \times 4 \leq 64$		a: 1 station occupied, b: 2 stations occupied, c: 3 stations occupied, d: 4 stations occupied	2. Number of units connected	$16 \times (A+D) + 54 \times B + 88 \times C \leq 2304$		A: Number of remote I/O stations ...64 max		B: Number of remote device stations ...42 max		C: Number of local stations, intelligent device stations ...26 max		D: Number of reserve stations *
1. Total number of stations	$a+b \times 2+c \times 3+d \times 4 \leq 64$														
	a: 1 station occupied, b: 2 stations occupied, c: 3 stations occupied, d: 4 stations occupied														
2. Number of units connected	$16 \times (A+D) + 54 \times B + 88 \times C \leq 2304$														
	A: Number of remote I/O stations ...64 max														
	B: Number of remote device stations ...42 max														
	C: Number of local stations, intelligent device stations ...26 max														
	D: Number of reserve stations *														
Communication method	Broadcast polling method														
Synchronization method	Frame synchronization method														
Encoding method	NRZI method														
Transmission route format	Bus (RS-485)														
Transmission format	HDLC compatible														
Error control method	CRC ($x^{16}+x^{12}+x^{15}$)														
Connecting cable	CC-Link Ver1.10-compatible dedicated cable														

* Unregistered station numbers from station 1 to the maximum number of stations are counted as reserve stations.

Features

1. Measured data can be displayed on a Web browser with graphs without any programming.

- Using the HTTP Server function, the collected data is transmitted via Ethernet across the Internet/Intranet so that all employees can confirm and understand amount of energy used in real-time.



2. Easy setting by using dedicated setting software.

- The minimum required registering configuration on the measuring is “①Measuring terminal registration” → “②Measuring point registration” → “③Writing project” only.


The configuration process is shown in three steps:

- ① Measuring terminal registration:** The software interface shows various settings tabs. A red dashed box highlights the 'Terminal' tab, with a callout 'Select using terminal'. Another red dashed box highlights the 'Measuring point' tab, with a callout 'Select measuring point information'.
- ② Measuring point registration:** The 'Measuring point' registration screen shows a table with columns for 'Measuring point name', 'Terminal name', 'Measuring item', 'Unit', 'Group', 'Starting', 'Lower limit value', and 'Upper limit value'. A red dashed box highlights the 'Measuring item' dropdown menu, with a callout 'Select measuring items'.
- ③ Writing the project:** The 'Writing the project' screen shows a confirmation dialog box asking 'Are you sure you want to save project?'. A red dashed box highlights the 'Yes' button, with a callout 'Save project'.

3. Add new comparison screens according to the scenario. Strong support provided for analyzing activities.


1 Date comparison graph

- The display procedure is select “① Measuring point group/name → ② Graph display date” and select “③ Display” only.
- A comparison of the specified date and items can be displayed.





2 Measuring point comparison graph

- The display procedure is to select “① Measuring point group/name → ② Graph display format → ③ Graph No. → ④ Graph display intervals etc.” and select “⑤ Display” only.
- It's possible to select graphs and display various graphs in the format of your choice. It's also possible to display the same graph, making it easy to understand graph correlations.



Display screen



4. Easily understand productivity by confirming the specific consumption graph

- By integrating the production volumes from the measuring terminal and PLC, the specific consumption graph can be easily displayed and points related to the drop in specific consumption can be easily understood.
- Additionally, by comparing two specific consumption graphs at the same line, it is possible to confirm the benefits at the time the countermeasure was implemented.

Display date selection menu

- Select the date of the data from the pull-down menu.

Specific consumption measuring point selection menu

- Select the specific consumption measuring point from the pull-down menu.

Automatic update fixed display box

- Yearly/monthly graph: 1hr cycle
- Daily/zoom data: 1min cycle

Objective value scale fixed display box

- Use the checkbox to select whether or not to display the vertical scale of the graph with the specific consumption objective value in the center.

Objective value setting window button

- Objective values can be set for each measuring point from the specific consumption screen.
- A password is required to change objective value settings.

* The password is set so that it can only be changed by the administrator.

Specific consumption amount (=a÷b)

Production amount (b)


Specific consumption target value

Cumulative amount of energy used

Energy used (a)

5. Connection with Mitsubishi Electric GOT display device.

- Information collected on the EcoWebServer III can be displayed on the GOT.
- By displaying the alarm state/measuring value for energy information/demand, real-time monitoring at the site and urgent countermeasures are possible.




6. Alarm output/email notification through a variety of monitoring functions.

- Objective values (upper/lower) and error information can be transmitted through email notifications/ alarm output, and changes in status can be recognized immediately. The result of the careful target value management and monitoring the status monitoring ensure that problems occurring at the site are not overlooked.

<Items monitored>

- Energy plan value
- Specific consumption objective value
- Upper/lower irregularity
- Change in operating state
- Error information
- Demand alarm




Features


7. Simultaneously visualize demand trends and energy consumption per building/load

Compatible model: MES3-255C-DM-EN only

- As the breakdown of power demand (load balance) can be easily understood from the power demand trends and stacked bar graphs for each regional substation and operating equipment can be reviewed, and operations can be planned and proposed based on the analysis results, which enable peak shift/peak cut.




● Demand monitor screen



8. Energy-saving air conditioning operation realized by interconnecting with integrated air-conditioning controller.

Compatible model: MES3-255C-DM-EN only

- Demand control possible by interconnecting with Mitsubishi Electric Web-compatible integrated controller—AE-200J, G-150AD, etc.
Additionally, automatic control of load possible through contact point output via main unit of EcoWebServer III and CC-Link.




Example screen

1. Date comparison graph screen

Electric consumption/current display




Voltage/power factor display



2. Measuring point comparison graph screen

Analysis by application



Analysis by department




Correlation analysis (graph overlapping)



3. Specific consumption graph screen


Daily




Monthly



Yearly



4. Demand monitor screen




5. Demand trend graph screen

Daily



Monthly



Yearly



6. Current value/contact point output monitor screen

Current value

Current value Monitor

Display type: Group
View type: Accumulated value
Group: Main

2014/09/03 11:28:55

ID	Name	Current value
1	Main Main_A	19.9 A
2	Main Main_V	6560 V
3	Main Main_W	219 kW
4	Main Main_kWh	809171 kWh

Contact point output

Contact output Monitor

2014/09/31 15:28:47

No.	Name	Item name	Destination	Ch	Output type	State	Control
1	Demand alarm level1	Level 1 alarm	Output unit	0	Interlock	OFF	OFF
2	Demand alarm level2	Level 2 alarm	Output unit	1	Interlock	OFF	OFF
3	Demand fixed alarm	Limit/Fixed alarm	Output unit	2	Interlock	OFF	OFF
4							OFF
5	Measuring error	Measuring error	Output unit	4	Interlock	ON	OFF
6	File transfer error	File transfer error	Output unit	5	One-shot	OFF	OFF
7							OFF
8							OFF
9	Demand control 1	Control output (Load1)	Output unit	8	Interlock	Close	CHG
10	Demand control 2	Control output (Load2)	Output unit	9	Interlock	Open	CHG
11	Demand control 3	Control output (Load3)	Output unit	A	Interlock	Close	CHG
12							OFF
13							OFF
14							OFF
15							OFF
16							OFF
17							OFF
18							OFF
19							OFF
20							OFF


Application Examples

Factories

Support Energy-saving Activities using "Visible Management".

1. Monitor/Manage energy by department
2. Specific consumption-based management of energy-saving activities
3. Monthly/Annual target-based management
4. Monitoring of equipment operating status
5. Manage/Record energy data


In the office...




To monitor equipment status



For target management




Employees




LAN(Ethernet)


At production site...



Office



Factory No. 2




For improvement activities



Buildings


Significantly reduce installation cost by using the existing LAN.

- 1. Manage/Monitor energy by floor/application
- 2. Manage data remotely
- 3. Easy for tenants and other personnel to read meters
- 4. Monitor operating status of building facilities (e.g., elevators, escalators, air conditioners)
- 5. Record/Manage energy data



Stores

- 1. Remote management of energy data for small, spread-out stores
- 2. Compare data of each store
- 3. Record/Monitor equipment operating status (e.g., manage freezer/refrigerator temperatures)
- 4. Easy for tenants and personnel to read meters




* When using a public line, a dial-up router is required.

* For use via the Internet, a separate contract with an Internet service provider is required.

Schools

- 1. Understand power consumption by facility (e.g., gymnasium) and equipment (e.g., transformer)
- 2. Monitor operating status of equipment distributed across a wide area
- 3. Save time and staff needed for meter-reading work
- 4. Record/Manage energy data



Main Unit Specifications

MES3-255C-EN front

7-segment LED display

Displays an error code when an error is detected.
In addition, in IP address display mode, the preset IP address is displayed at start-up.

USB interface

Not used.

LAN interface CH1

Use connected to a computer network.

LAN interface CH2


Use when connected to a programmable controller network.

Power-supply terminal block

Connect power supply. (Note 1)

CC-Link terminal block

Connect CC-Link communication cable.



LED display

Display each status.

CC-Link station number setting switch

Set CC-Link station number.

CC-Link transmission speed setting switch

Set CC-Link transmission speed.

Contact output terminal block

Closed when conditions monitoring function conditions are met.
Connect external equipment such as buzzers and lamps.

LED display

Display each status.

MES3-255C-DM-EN front

7-segment LED display

Displays an error code when an error is detected.
In addition, in IP address display mode, the preset IP address is displayed at start-up.

USB interface

Not used.

LAN interface CH1

Use connected to a computer network.

LAN interface CH2


Use when connected to a programmable controller network.

Power-supply panel

When you open the panel, you will see the power-supply connection terminal. (Note 1)

LED display

Display each status.



LED display

Display each status.

CC-Link station number setting switch

Set CC-Link station number.

CC-Link transmission speed setting switch

Set CC-Link transmission speed.

Demand monitor section connection terminal

Connect cable to pulse input, alarm output and control output for demand monitoring. (Note 2)

Contact output terminal block


Closed when conditions monitoring function conditions are met.
Connect external equipment such as buzzers and lamps.

CC-Link terminal block

Connect CC-Link communication cable.

Front surface (cover of Server section opened)/bottom surface (CC-Link transmission device)

Front surface (cover of Server section opened)



CompactFlash™ memory card EJECT button

Push the button and remove the CompactFlash™ memory card.

MODE/STOP/RUN switch

Normally, used in RUN state.


RESET/SELECT switch

Used when resetting the main unit.

CompactFlash™ memory card

Stores programs for collecting and displaying data. Data collected is also saved to it. (Note 3)

Bottom surface



RS-232 interface

Not used.

Battery storage compartment


Store the battery.
Remove the cover and connect the connector. (Note 4)

- (Note 1) Connect to AC100–240V (+10%, –15%) 50/60Hz (±5%). Do not connect to a power supply other than that specified as this may cause an accident.
- (Note 2) A separate power supply is required for the demand monitor section when using. When using the main device, AC100–240V (+10%, –15%) 50/60Hz power is required for the demand monitor connector terminals V1, V2. It is possible to connect power from the power-supply module.
- (Note 3) CompactFlash™ memory cards are used in a constantly attached state. If they are removed while the power is on or the memory card is being accessed, this product will malfunction.
- When removing the card from the memory card slot, be sure to place the RESET/SELECT switch in the SELECT position and remove it only after turning off the power supply and the CF CARD LED has turned off.
 - Do not use the CompactFlash™ memory card with any other product. This could corrupt the internal data.
 - Do not insert a CompactFlash™ memory card other than the one included in the package in this device. If a different card is inserted, the system will not operate correctly.
- (Note 4) Be sure to exchange the battery within three minutes after turning off the power. If more than three minutes passes after the battery is removed, the final one hour of data may be lost or the clock may initialize. (Data or configuration settings from more than one hour before will not be initialized). If the clock initializes, please set again after backing up the data. Refer to the operating manual (hardware edition) for the battery replacement procedure.

Connection diagram


Model: MES3-255C-EN, MES3-255C-DM-EN

Power-supply section




Server communications section (LAN interface)


■ When displaying graphs




Connecting point output section



■ When setting (CH1)




■ When connecting the PLC (CH2)




Operation of Ethernet/serial converter can be confirmed using the following product. Line Eye SI-65

CC-Link communication section



Demand monitor section

(1) Where the transaction meter of the multi-measuring power demand meter is 10,000pulse/kWh



Function Comparison/System Environment

Functions

Product Name		MES3-255C-EN	MES3-255C-DM-EN	
Demand function		—	Yes	
Connection device	CC-Link terminal device	Number of remote I/O stations≤64, Number of remote device stations≤42, Number of local stations≤26		
	MITSUBISHI PLC, GOT	MC protocol connection (LAN CH2 used) * device read/write CC-Link unit (local) connection * device read		
Number of measuring points	Measuring points	255 points		
	Number of operation measuring points	32 points (includes 255 measuring points)		
	Virtual measuring points	128 points		
	Specific consumption measuring points	64 points		
	Connection point output	32 points		
	Demand monitoring	Receiving demand Receiving electric energy	— —	2 points (fixed) whole day, timeframe 1-10 2 points (fixed) whole day, timeframe 1-10
Data saving function * CSV format	Zoom (every 1min) data	62-day amount		
	Zoom (every 5min) data	14-day amount		
	Daily data (on the hour or every 30min)	186-day amount		
	Monthly data (specified time (00min) once a day)	60-month amount		
	Yearly data (specified time (00min) once a month)	5-year amount		
	Virtual measuring point data (daily)	186-day amount		
	Virtual measuring point data (monthly)	60-month amount		
	Virtual measuring point data (yearly)	5-year amount		
	Specific consumption measuring point data (daily)	186-day amount		
	Specific consumption measuring point data (monthly)	60-month amount		
	Specific consumption measuring point data (yearly)	5-year amount		
	Equipment data (daily)	186-day amount		
	Operating history data	64KB×4 files		
	System log	256KB×8 files		
	Demand data (daily)	—	186-day amount	
	Demand data (monthly(daily maximum))	—	60-month amount	
	Demand data (yearly(monthly maximum))	—	5-year amount	
Demand alarm/Control log	—	128KB×62 files		
Display function	Real-time	Demand monitor	— • Displays current time limit demand load curve • Displays graph of same day demand results	
		Current value monitor	The current value of the specified measuring points are displayed in the units registered for groups and display lists Displays differential display mode function/differential values for specified measuring points (time differential: amount used from previous hour to present time, daily differential/monthly differential: amount used from previous summary time to present)	
		Connection point output monitor	Displays connecting point output status	
	Graph display	Demand trend graph	—	Displays demand trend graph
		Measuring point comparison graph	Displays comparison of multiple measuring point data for specified display intervals/time displayed	
		Daily comparison graph	Displays comparison of specified measuring points for desired date	
		Specific consumption graph	Displays graph after dividing energy volume by number produced	
	Equipment graph	Displays graph of equipment efficiency, number of defects and equipment energy volume		
Data file	Download measuring point data, virtual measuring point data, specific consumption data, equipment data, operating history data, system log, demand data *, alarms/control log * (*only for products with demand monitoring functions)			
Equipment values list	Displays measuring points, connection point output and content of email notifications set for EcoServerIII			
Monitoring functions	Email notification function	Transmits main unit error notifications, periodic notifications, upper/lower limit notifications, operating status notifications, specific consumption objective value notifications, energy plan value notifications and demand notifications * to the specified SMTP Server (*only for products with demand monitoring functions)		
	Connection point output	Outputs connection points for EcoWebServerIII connection point output module or combined CC-Link input/output module		

Recommended system environment


Item	Specification
OS (basic software)	Microsoft Windows XP Professional(32bit)SP3, Microsoft Windows Vista® Business(32bit)SP2 Microsoft Windows 7 Professional(32bit, 64bit)SP1, Microsoft Windows 8.1 Pro(32bit, 64bit)
CPU	Pentium® 1GHz processor or faster, or compatible microprocessor (DOS/V-compatible device)
Memory	1GB or more
Hard-disk	If data accumulated by Eco EcoServer III is saved to a computer, that storage capacity is required.
CD drive	1 group or more (required for installing setup software)
Display resolution	1280×1024 pixels or more
Display colors	65536 colors or more
Input device	Mouse and keyboard
External interface	10BASE-T / 100BASE-TX
Web browser	Internet Explorer® 7, 8(32bit), 9(32bit), 10(32bit), 11(32bit)
Java plug-in	Oracle Java™ 7 JRE 7(32bit), Oracle Java™ 6 JRE 6(32bit)

External Diagram/Bundled Products List


External dimensions

Unit : mm

■MES3-255C-EN




■MES3-255C-DM-EN




Peripheral installation conditions

■MES3-255C-EN



■MES3-255C-DM-EN



Bundled Products List

Product Name	CC-Link communication product	
	MES3-255C-EN	MES3-255C-DM-EN
Energy-saving Data Collection Server (main unit)	1	1
CompactFlash™ memory card (software)	1	1
Setup software (CD-R)/operating manual collection	1	1
Battery (installed in lower surface of main unit battery section) *1	1	1
Frame attachment screw	4 (M4×12)	4 (M4×14)
CC-Link terminal resistance (black: 110Ω/2W) (white: 130Ω/2W)	Black: 2	White: 2
IEC rail attachment adapter	Small 2	Large 2
IEC rail attachment screw (M5 x 10)	2	2
IEC rail attachment corner washer	2	2
IEC rail attachment stop metal clamp	2	2
Operating manual hardware edition	1	1

*1 To purchase a replacement battery (model name: Q6BAT), inquire at the dealership where you purchased the main product.

Support terminal

MES3-255C-EN, MES3-255C-DM-EN(CC-Link)

Product Name	Icon/type name	Station type	Number of occupying stations
Energy measuring unit(1P2W, 1P3W, 3P3W)	EMU4-BD1-MB	Remote device station	1 station occupied
Energy measuring unit(1P2W, 1P3W, 3P3W, 3P4W)	EMU4-HD1-MB	Remote device station	1 station occupied
Energy measuring standard model ^{*1}	EMU4-BM1-MB	Remote device station	1 station occupied
Energy measuring high performance model ^{*1}	EMU4-HM1-MB	Remote device station	1 station occupied
Insulation Monitoring model ^{*1}	EMU4-LG1-MB	Remote device station	1 station occupied
Energy measuring extension model for same voltage system ^{*2}	EMU4-A2	Remote device station	^{*3}
Energy measuring extension model for different voltage system ^{*2}	EMU4-VA2	Remote device station	^{*3}
Energy measuring unit (Power reception and distribution monitoring(standard product 3 circuits))	EMU2-RD3-C	Remote device station	1 station occupied
Energy measuring unit (Power reception and distribution monitoring(standard product 5 circuits))	EMU2-RD5-C	Remote device station	1 station occupied
Energy measuring unit (Power reception and distribution monitoring(standard product 7 circuits))	EMU2-RD7-C	Remote device station	1 station occupied
Energy measuring unit (Power reception and distribution monitoring(3P4W 2 circuits))	EMU2-RD2-C-4W	Remote device station	1 station occupied
Energy measuring unit (Power reception and distribution monitoring(3P4W 4 circuits))	EMU2-RD4-C-4W	Remote device station	1 station occupied
Energy measuring unit	EMU3-DP1-C	Remote device station	1 station occupied
MDU breaker(WS-V)	MDU(WS-V) : NF250-SEV/HEV with MDU	Remote device station	1 station occupied
MDU breaker(WS)	MDU(WS) : NF400-SEP/HEP with MDU	Remote device station	1 station occupied
	NF600-SEP/HEP with MDU		
	NF800-SEP/HEP with MDU		
Low-voltage air circuit breaker(AE-SW with CC-Link interface unit)	AE-SW(BIF-CC)	Remote device station	1 station occupied
Electronic multi-measuring instrument	ME96SSR-MB	Remote device station	1 station occupied
Electronic multi-measuring instrument	ME96SSH-MB	Remote device station	1 station occupied
Electronic multi-measuring instrument	ME96NSR	Remote device station	1 station occupied
Electronic multi-measuring instrument with transmission function	ME110SSR-C(H)	Remote device station	1 station occupied
Electronic multi-measuring instrument with transmission function	ME110NSR-C	Remote device station	1 station occupied
Thermocouple temperature input unit	AJ65BT-68TD	Remote device station	4 station occupied
Platinum resistance temperature sensor Pt 100 temperature input unit	AJ65BT-64RD3	Remote device station	4 station occupied
Analog-digital conversion unit	AJ65BT-64AD	Remote device station	2 station occupied
Terminal block type 24 VDC input unit(8 points)	AJ65SBBT1-8D	Remote I/O station	1 station occupied
Terminal block type 24 VDC input unit(16 points)	AJ65SBBT1-16D	Remote I/O station	1 station occupied
Terminal block type 24 VDC input unit(32 points)	AJ65SBBT1-32D	Remote I/O station	1 station occupied
Terminal block type DC input transistor output combined unit (Input 8 points, Output 8 points)	AJ65SBBT1-16DT	Remote I/O station	1 station occupied
Terminal block type DC input transistor output combined unit (Input 16 points, Output 16 points)	AJ65SBBT1-32DT	Remote I/O station	1 station occupied
CC-Link master/local unit(Local station)	QJ61BT11N	Intelligent device station	1 station occupied
CC-Link master/local unit(Local station)	LCPU/LJ61BT11	Intelligent device station	1 station occupied

*1 EMU4-BM1-MB, EMU4-HM1-MB, EMU4-LG1-MB are main units of EcoMonitorPlus.

*2 EMU4-A2, EMU4-VA2 are extension units EcoMonitorPlus.

*3 Combination of main unit and extension unit occupied 1 station.

Related Products

EcoMeasure III daily/monthly report specific consumption analysis software

This software supports the specific consumption analysis graph and ledger preparation of daily reports, monthly reports and annual reports from CSV files collected and output by the Mitsubishi Electric EcoWebServer III Energy-saving Data Collection Server.

* The supporting product version, EcoWebServer III with demand monitoring function, for EcoMeasure III, will be released soon.

Features

- (1) Easily create daily, monthly and annual reports.
 - Ledger prepared ledger is saved as an Excel file in user-designated place.
- (2) Easily perform specific consumption management as the index of energy-saving activities.
 - Possible to manually input production volume and perform specific consumption management of energy information from EcoWebServer III and E-Energy.
 - Possible to prepare each specific consumption graph (zoom, daily, weekly and monthly).
- (3) Easily collect data.
 - CSV files stored in EcoWebServer III and E-Energy can be downloaded with simple operations.

Product Appearance



Specifications

Item	Specifications		
Model name	MES3-SW1-DR-FR		
Connection devices	Number of units	2 units maximum (combination of following target devices)	
	Target devices	EcoWebServer III (MES3-255C-EN)	
Number of virtual measurement points	Maximum 95 points (Total of 95 points including virtual measurement points for calculating measurement management points and virtual measurement points for input.) * Four arithmetic operations of up to 64 measurement management points (including constants) can be registered in the virtual measurement points for calculation.		
Number of virtual measurement point groups	Maximum five groups *Addition/Subtraction calculations for up to 32 virtual measurement points can be registered in the virtual measurement point groups.		
Ledger creation function	Ledger creation	Daily report creation, monthly report creation, annual report creation	
	Maximum number of items	The daily, monthly and annual reports can have up to 2,250 output items.	
	Calculation items	Analog (including specific consumption)	Maximum, minimum, average
		Pulse	Total, maximum, minimum, average
Demand		Maximum	
Specific consumption management function	Specific consumption display	Daily specific consumption, weekly specific consumption, monthly specific consumption and zoom specific consumption *1	
	Number of specific consumption	Maximum 100 points	
	Specific consumption target value	Can set by each specific consumption	
	Graph display	Specific consumption, target value, production volume, power used (kWh), accumulated power volume (kWh) * The specific consumption/target value/production volume units can be set freely.	
		Auto-scale function	
	List display	Daily/weekly/ monthly specific consumption	Power volume (kWh), production volume, specific consumption, accumulated power volume (kWh), accumulated production amount, specific consumption target value
		Zoom specific consumption	Power volume (kWh), production volume, specific consumption, power use/hour
Automatic updating	Daily/weekly/ zoom specific consumption	Contents of display newly updated at designated time once per hour each hour	
	Monthly specific consumption	Contents of display newly updated at designated time once per day each day	
Operation environment	OS (basic software)	Microsoft Windows XP(32bit) (SP3) Home Edition/Professional Microsoft Windows Vista® (32bit) (SP2) Home Basic / Home Premium / Business / Enterprise / Ultimate Microsoft Windows Server 2003(32bit) (SP2) Standard Microsoft Windows 7(32bit/64bit) (SP1) Professional	
	Required software	Microsoft Excel 2003(SP3) / 2007(SP3) / 2010(32bit/64bit) (SP1)	
	CPU	If using Windows XP : Pentium processor of 400MHz or higher or a compatible microprocessor (DOS/V- compatible) If using Windows Vista® or Windows 7 : As recommended for the operating system	
	Memory *2	As recommended for the operating system	
	Hard-disk *2	Software: Approx. 100MB or more Data: 8GB or more *3	
	CD-ROM drive	1 drive (for installing software)	
	LAN	10/100/1000BASE-T ×1	
	USB connector (Type A)	1 connector (for connecting hardware key)	
	Display resolution	800×600 pixels or more	
	Display color	256 colors or more	
Number of licenses (number of computers installed in)	• 1 license per 1 client • Hardware key attached (UBS) (1 unit)		

*1 If virtual measurement points for input or measurement points for E-Energy are included, no zoom specific consumption is displayed.

*2 Note that the required memory and available hard-disk space may vary depending on the system environment.

*3 Shows the capacity required when used with maximum eight subsystems connected.

[Daily Report]

[Monthly Report]

[Annual Report]

Safety Precautions

1. Safety Precautions to be Followed at all Times

Operating Environment/Conditions

Using this product in any of the following environments may cause a malfunction or shorten service life. Do not use in environments where:

- | | |
|---|---|
| <ul style="list-style-type: none"> ● Ambient temperature outside the range of 0 - 55°C ● Daily average temperature exceeds 35°C ● Relative humidity outside the range of 5 - 95% or where condensation occurs ● Altitude is higher than 2,000m above sea level ● Presence of excessive dust, corrosive gas, salt-saturated air or oily smoke | <ul style="list-style-type: none"> ● Unit is subject to excessive vibration or physical shock ● Unit is exposed to rain or drops of water ● Unit is exposed to direct sunlight ● Pieces of metal or inductive substances nearby ● Presence of strong electromagnetic field or excessive external electrical noise interference |
|---|---|

Installation/Mounting

Be sure to read the user's manual before installing/mounting the product.

CAUTION

- For safety, unit installation and all wiring connections should be performed by a qualified electrician.
- Be careful of sharp, metal edges; they may cause injury.
- When tightening screws or connecting wiring, be sure that small particles or cut pieces of electrical wiring do not get inside the unit.
- Check the wiring diagram carefully before making connections. Incorrect connections may cause a malfunction, fire or electrical shock.
- Do not perform wiring work using live circuits. Doing so may cause a malfunction, fire or electrical shock.
- Use electrical wires of appropriate size. Not doing so may cause a fire due to the possible generation of heat.
- Use a solderless terminal that matches the size of the electrical wire. Not doing so may result in disconnected wires or improper electrical contact, thereby causing a malfunction, failure, burnout or fire.

Location	Wire size	Compatible solderless terminal
Power-supply terminal block	0.75 - 2 mm ²	RAV1.25-3.5 RAV2-3.5
CC-Link communication terminal block	CC-Link Ver.1.10-compatible dedicated cable	R1.25-3
Contact output terminal block	0.3 - 0.75 mm ²	R1.25-3 (cannot use solderless terminal with sleeve)
Demand monitor block	0.5 - 1.3 mm ²	TGV TC-1.25-11T equivalent (Nichifu Co., Ltd.)

- Be sure to check that all screws have been tightened. Not doing so may cause a malfunction, failure, burnout or fire.
- Tighten screws to the specified torque. Excessive tightening may cause damage to the terminal and/or screws. Failure to tighten properly may cause a malfunction, fire or electrical shock.
- When using lines from demand monitor terminal block, twist the heads of the fine lines together so they do not spread before attachment.

Location	Tightening torque	Location	Tightening torque
Terminal screws for power-supply terminal block (M3.5 screw)	0.8 - 1.0·Nm	Terminal screws for contact output terminal block (M3 screw)	0.42 - 0.58N·m
Terminal screws for CC-Link communication terminal block (M3 screw)	0.42 - 0.58N·m	Mounting screws for contact output terminal block (M3.5 screw)	0.66 - 0.89N·m
Mounting screws for CC-Link communication terminal block (M3.5 screw)	0.66 - 0.89N·m	Unit attachment screws (M3×12 screws)	0.36 - 0.48N·m

- Be sure to check that the terminal cover has been attached. Not doing so may result in electrical shock.
- To prevent induction noise, control wires and communication cables should be installed as far as possible from power lines (wiring should be separated by a distance of at least 100mm).
- Avoid installation inside a panel where high-voltage equipment is used. Use a surge protector for equipment that tends to generate electrical noise.
- During actual use conditions, use Class-D grounding (dedicated grounding) for "FG".
- Do not connect the FG terminal to a box (ground) when conducting the withstand voltage test or insulation resistance test.

CC-Link


- Connect both ends of the CC-Link communication cable shield line to the SLD terminal of each unit.
Each unit's SLD and FG are connected inside of the modules.
Please make sure to insulate the shield with vinyl tape or similar.

Preparations Before Use

- Be sure that the installation location complies with the operating environment and conditions.
- This product requires setting before use. If setting is not done properly, a malfunction may occur.
- Confirm the power-supply rating of the product.
- Remove the dust-resistant seal after completing installation and wiring construction.
Not doing so may cause a malfunction due to the possible generation of heat.
- This product is equipped with a lithium battery. As the battery is not connected at the time of shipping, please connect it before use.

Regarding Use


- Use only within rating range specified in the product's instruction manual. Not doing so may cause a malfunction, failure, fire or burnout.
- An IP address and other settings are required to connect this product to a network (Ethernet). Before use, use the accompanying setup software to perform network-related settings such as setting the IP address.
- The factory default settings are:
IP address = 192.168.10.1, subnet mask = 255.255.255.0, gateway = none
No setting changes are required for direct connection to a computer.
- This product is equipped with a built-in clock. Before use, use the accompanying setup software to set the current date and time.
- Before use, be sure to check that there are no live circuits or bare wires in the vicinity of the product.
If a live circuit or bare wire is found during use, stop operation immediately and take appropriate measures, such as providing protective insulation.
- Please consult with a Mitsubishi Electric sales representative when considering using this product with machinery or systems designed for specialized use such as nuclear power, electric power, aerospace/outer space, medical, or passenger transportation vehicles. (To contact a sales representative, please refer to the end of this document.)
- If the power supply is turned on immediately after turning it off (within 5sec), incoming current may exceed the stipulated value (less than 2ms). Please wait more than 5sec before turning the power supply on after turning it off.



- Do not disassemble or modify product. Doing so may cause a failure, electrical shock or fire.
- A seal sheet has been placed on the side of this product. If the seal sheet has been removed from the product, the product is out-of-service, such as down for maintenance or malfunction analysis.

Maintenance/Inspection

- Do not disassemble or modify any part of the product. Doing so may cause failure, malfunction, injury or fire.
- Do not touch terminals when current is flowing. Doing so may cause electrical shock, malfunction or failure of product operation.
- When cleaning the product or tightening attachment screws, please make sure to turn off the exterior power supply, cutting off power to the input power supply. Not doing so may cause malfunction or failure of product operation.
- Use a soft, dry cloth to wipe dust and dirt from the surface of the product.
- Do not let chemicals touch the surface for long periods of time. Clean product surface using pre-treated wipes. Do not use benzene, thinner or forms of chemical cleansers.
- Conduct inspections as follows to ensure correct use of the product and a long service life.
 - <Daily inspection or check at least once or twice every six months> Check for: ①Product damage, ②LED display abnormalities, ③Abnormal noises, odors and heat.
 - <Check once a year> ④ Confirm if mounting screws or terminal block wire connections have come loose (be sure to turn off the power before performing inspections).
- The lithium battery in the server block needs to be replaced when the battery charge is depleted (red BAT LED lamp on server block will turn on) or every three years.



- Be sure to turn off the power before checking for loose connectors, mounting screws and terminal block wire connections.
- If a power outage occurs when the battery charge is weak, the clock or data may be initialized. Please reset when required, and then change the battery.


Storage

- When storing this product, turn off the power supply, disconnect the wiring and place it in a plastic bag.
- When turning the power supply off for long periods of time, disconnect the connector for the battery. (The cumulative power outage compensation time of the battery is up to 13,700hr (1.57yr). Using the battery outside of the warranty period may result in losing measurement data.)
- Storing the product in one of the environments described below may cause a malfunction or shorten service life. Do not store the product for long periods of time in environments where:

- | | |
|--|---|
| <ul style="list-style-type: none"> ● Ambient temperature is outside the range of -25 - +75°C ● Average daily temperature exceeds 35°C ● Relative humidity is outside the range of 5 - 95% or where condensation occurs ● Altitude exceeds 2,000m ● Presence of excessive dust, corrosive gas, salt-saturated air or oily smoke. | <ul style="list-style-type: none"> ● Unit is subjected to excessive vibration or physical shock. ● Unit is exposed to rain or drops of water ● Unit is exposed to direct sunlight ● Presence of pieces of metal or inductive substances nearby ● Presence of a strong electromagnetic field or excessive external electrical noise interference. |
|--|---|

Disposal

- Dispose of this product following relevant laws and/or guidelines regarding disposal and cleaning (Waste Management Law).
- This product is equipped with a lithium battery. Please dispose of it according to relevant local laws and/or guidelines.



- The lithium battery may still have an electrical charge after it is removed. Store it separately from other metals, as contact with other metals may cause the generation of heat, rupture or fire.

QR Code displayed on product

- As the QR Code displayed on this product is used for production management, it is not for the customer to use. There is no guarantee that the QR Code can be read by a commercial code reader, etc.

Warranty

- Regarding technical inquiries or questions regarding the product, please contact nearest Mitsubishi Electric dealership or distributor.
- Please consult with a Mitsubishi Electric sales representative when considering using this product with machinery or systems designed for specialized use such as nuclear power, electric power, aerospace/outer space, medical, or passenger transportation vehicles.
- This manual and equipment are shipped under strict quality control and product inspection. In the unlikely in case of any defect resulting from production processes, Mitsubishi Electric will replace the product. Please contact the dealership where the product was purchased. Please note, however, Mitsubishi Electric's warranty doesn't include replacement in the cases of failure and/or damage caused due to natural disasters or improper use.
- Please understand that Mitsubishi Electric will not bear the liability for any system problems caused by a customer or third party, legal issues, failure caused by improper use of or during use of the product, or damage caused by other defects.
- Mitsubishi Electric shall not bear the liability for any damage caused by reasons that are not the fault of the Company, loss of opportunity or loss of income suffered by a customer due to the occurrence of this product's failure, damage or secondary damage resulting from special reasons, regardless of whether or not it was foreseeable, accident compensation or other compensation for any damage caused to products other than those of Mitsubishi Electric, and other services.
- The free warranty period of this product shall be the shorter period, either one (1) year after purchase and delivery to the designated location, or 18 months after shipping from the Company factory (beginning from month and year manufactured). However, even during the warranty period, if repair is required due to one of the following causes, a fee shall be charged:
 - 1) improper use or 2) improper operation.
 Fee-based repairs are available after the end of the free warranty period.
- The free warranty period for repairs shall not be renewed.


Repairs at the time of failure/abnormality

- If any abnormality occurs in one of the products listed in this catalog, please read the section, "Trouble Shooting," in the instruction manual (operation version) to check for possible reasons of the problem. If there is no description matching the problem found, please contact nearest Mitsubishi Electric dealership.

2. Precautions for Use

Precautions Regarding Software Use

- Mitsubishi Electric does not guarantee or provide support for FTP server or SMTP server operations. Additionally, Mitsubishi Electric does not provide technical support for individual servers.
- Please be aware that Mitsubishi Electric does not provide network support. Please contact your network administrator.
- Please be aware that Mitsubishi Electric does not provide support regarding computer hardware, operating systems or operations. Please contact the manufacturer or administrator.
- After using the setup software to modify display settings (e.g., a measuring point name), be sure to close and restart the web browser. Not doing so may cause the changes not to take effect due to the web browser's caching function.



- For monitoring operating status, do not use measures such as inputting alarms that consider human safety or require an emergency response (fire alarm). Doing so may lead to an accident.

3. Trademarks

- Microsoft® Windows®, Windows® XP, Windows Vista®, Windows®7, Windows®8.1, Internet Explorer® are trademarks or registered product trademarks of Microsoft Corporation in the U.S.A. and other countries.
- Java and all Java related trademarks and logos are registered trademarks of the Oracle Corporation and its subsidiaries and affiliates in the U.S.A. and other countries.
- CompactFlash™ and CompactFlash™ and CF are trademarks of SanDisk Corporation.
- Ethernet is a trademark of Xerox Corporation in the U.S.A.
- QR Code is a registered trademark of Denso Wave Incorporated in Japan.
- EcoServer is a registered trademark of Mitsubishi Electric Corporation.
- Other company names and product names are registered trademarks or trademarks of their respective companies.



Service Network

Country / Region	Company	Address	Telephone
Australia	Mitsubishi Electric Australia Pty. Ltd.	348 Victoria Road, Rydalmere, N.S.W. 2116, Australia	+61-2-9684-7777
USA	Mitsubishi Electric Automation Inc.	500 Corporate Woods Parkway Vernon Hills, IL 60061, USA	+1-847-478-2100
Brazil	MELCO-TEC Rep. Com. e Assessoria Tecnica Ltda.	Av. Paulista, 1439-CJ.72, Cerqueira Cesar CEP 01311-200, Sao Paulo, SP, CEP:01311-200, Brazil	+55-11-3146-2200
Chile	Rhona S.A.	Agua Santa 4211 P.O. Box 30-D Vina del Mar, Chile	+56-32-2-320-600
China	Mitsubishi Electric Automation (CHINA) Ltd.	No. 1386 Hongqiao Road, Mitsubishi Electric Automation Center Shanghai China, 200336	+86-21-2322-3030
China	Mitsubishi Electric Automation (HongKong) Ltd.	10/F., Manulife Tower, 169 Electric Road, North Point, Hong Kong	+852-2887-8810
Colombia	Proelectrico Representaciones S.A.	Carrera 53 No 29C-73 - Medellin, Colombia	+57-4-235-30-38
Egypt	Cairo Electrical Group	9, Rostoum St. Garden City P.O. Box 165-11516 Maglis El-Shaab, Cairo - Egypt	+20-2-27961337
Europe	Mitsubishi Electric Europe B.V.	Gothaer Strasse 8, D-40880 Ratingen, Germany	+49-(0)2102-486-0
India	Mitlite Electric Company Pvt Ltd	Plot No-32, Sector-6, IMT Maneser,	+91-124-4695300
Indonesia	P. T. Sahabat Indonesia	P.O.Box 5045 Kawasan Industri Pergudangan, Jakarta, Indonesia	+62-(0)21-6610651-9
Korea	Mitsubishi Electric Automation Korea Co., Ltd	1480-6, Gayang-Dong, Gangseo-Gu, Seoul, Korea	+82-2-3660-9572
Laos	Arounkit Corporation Import-Export Solt Co., Ltd.	Saphanmo Village. Sayaetha District, Vientiane Capital, Laos	+856-20-415899
Lebanon	Comptoir d'Electricite Generale-Liban	Cebaco Center - Block A Autostrade Dora, P.O. Box 11-2597 Beirut - Lebanon	+961-1-240445
Malaysia	Mitric Sdn Bhd	5 Jalan Pemberita U1/49, Temasya Industrial Park, Glenmarie 40150 Shah Alam, Selangor, Malaysia	+603-5569-3748
Myanmar	Peace Myanmar Electric Co., Ltd.	NO137/139 Botataung Pagoda Road, Botataung Town Ship 11161, Yangon, Myanmar	+95-(0)1-202589
Nepal	Watt & Volt House	KHA 2-65, Volt House Dillibazar Post Box: 2108, Kathmandu, Nepal	+977-1-4411330
Middle East Arab Countries & Cyprus	Comptoir d'Electricite Generale-International-S.A.L.	Cebaco Center - Block A Autostrade Dora P.O. Box 11-1314 Beirut - Lebanon	+961-1-240430
Pakistan	Prince Electric Co.	1&16 Brandreth Road, Lahore-54000, Pakistan	+92-(0)42-7654342
Philippines	Edison Electric Integrated, Inc.	24th Fl. Galleria Corporate Center, Edsa Cr. Ortigas Ave., Quezon City Metro Manila, Philippines	+63-(0)2-634-8691
Saudi Arabia	Center of Electrical Goods	Al-Shuwayer St. Side way of Salahuddin Al-Ayoubi St. P.O. Box 15955 Riyadh 11454 - Saudi Arabia	+966-1-4770149
Singapore	Mitsubishi Electric Asia Pte. Ltd.	307, Alexandra Road, #05-01/02 Mitsubishi Electric Building, Singapore 159943	+65-6473-2308
South Africa	CBI-electric: low voltage	Private Bag 2016, Isando, 1600, South Africa	+27-(0)11-9282000
Taiwan	Setsuyo Enterprise Co., Ltd	6th Fl., No.105, Wu Kung 3rd, Wu-Ku Hsiang, Taipei, Taiwan, R.O.C.	+886-(0)2-2298-8889
Thailand	United Trading & Import Co., Ltd.	77/12 Bamrungmuang Road, Klong Mahanak, Pomprab Bangkok Thailand	+66-223-4220-3
Uruguay	Fierro Vignoli S.A.	Avda. Uruguay 1274, Montevideo, Uruguay	+598-2-902-0808
Venezuela	Adesco S.A.	Calle 7 La Urbina Edificio Los Robles Locales C y D Planta Baja, Caracas - Venezuela	+58-212-241-9952
Vietnam	CTY TNHH-TM SA GIANG	10th Floor, Room 1006-1007, 255 Tran Hung Dao St., Co Giang Ward, Dist 1, Ho Chi Minh City, Vietnam	+84-8-8386727/28/29

For Safety : Please read the instruction manual carefully before using the products in this catalog. Wiring and connection must be done by the person who has specialized knowledge of electric construction and wirings.

● Trademarks

- Microsoft, Windows Vista, Windows XP, Windows7, Excel are U.S. registered trademark in the U.S. of U.S. Microsoft Corporation, and other countries.
- MODBUS® is a registered trademark of Schneider Automation Inc.
- Other company names and product names in this document are trademarks or registered trademarks of their respective owners.



for a greener tomorrow

Eco Changes is the Mitsubishi Electric Group's environmental statement, and expresses the Group's stance on environmental management. Through a wide range of businesses, we are helping contribute to the realization of a sustainable society.



MITSUBISHI ELECTRIC CORPORATION

HEAD OFFICE: TOKYO BUILDING, 2-7-3, MARUNOUCHI, CHIYODA-KU, TOKYO 100-8310, JAPAN