

SolarEdge Home Smart Socket B13 QIG B-Type

Safety Information

- For indoor use only
- Keep children away from the socket and the outlet
- DO NOT use with medical or life support equipment
- DO NOT use in wet or damp areas
- Remove the socket from the outlet before cleaning DO NOT clean with liquid
- Test the device locally for safe operation before attempting to control it remotely

System Requirements

- An inverter with a SolarEdge Home Network connection and CPU $\geq 4.18.xx$
- SolarEdge SetApp: Smartphone application for a socket connection to an inverter and firmware upgrade
- mySolarEdge: Smartphone application for socket configuration and status reading
- iOS 10 or later or Android 6.0.1 or later

Getting Started


1. Plug your socket into an outlet. A blinking LED is shown.
2. Log in to your SetApp account.
3. From the Commissioning screen, select **Device Manager**. Newly detected devices are displayed.
4. Select a device to be added and configure device parameters.
5. Select **Finish Setting**.

Configuration and Socket Status

1. Run mySolarEdge and log in. The first login requires registration.
2. From the Dashboard → click the **Smart home** tab → **Devices** → **Smart Energy Socket**.

ON/OFF/Reset Button Operation

- Press for <3 seconds to operate manually
- Hold >10 seconds to reset



LED Indications

Operation	Status
Blinking Blue	Waiting to connect to the home network and the load is OFF
Blinking Green	Waiting to connect to the home network and the load is ON
Blue	Connected and the load is OFF
Green	Connected and the load is ON
Red	Error
Flickering Blue	Standby
Flickering Green 5 times	Reset done

Specifications

AC Voltage (nominal)	90 ~ 250 Vac
AC frequency	50/60 Hz
Maximum Load	13A
Communication Type	SolarEdge Home Network
Poles	1
Relay switching cycles	> 20,000
Operating hours	50,000hr
Installation altitude	2000m
Measurement accuracy	1%

Features

- Wireless operation: Smartphone/web Monitoring
- Manual operation
- Child protection on socket input
- Lifetime energy record
- Grounded Socket



Discard this product according to local regulations or send it back to SolarEdge.
 Entsorgen Sie dieses Produkt entsprechend den örtlichen Vorschriften oder senden Sie es zurück an SolarEdge.
 Verwijder dit product in overeenstemming met de lokale regelgeving of stuur het terug naar SolarEdge.
 Mettre ce produit au rebut conformément à la réglementation en vigueur ou renvoyer celui-ci à SolarEdge.

Useful Links

[Datasheet](#)



[Application Note](#)



Support Contact Information

If you have technical problems concerning SolarEdge products, please contact us: <https://www.solaredge.com/service/support>
 Subject to change without notice. Copyright © SolarEdge Inc. All rights reserved. August 2023 V1.0