

HP Networking Legacy ProCurve Product Family Mini-GBIC and SFP Support Matrix

			Genuine HP ProCurve Mini-GBICs and SFPs				
			Gigabit "B" and "C" versions				
HP Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T ¹ (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400-24G	J9078A	all software versions	all software versions	(not supported)	(not supported)	all software versions
1410	1410-24G Switch	J9561A	all software versions	all software versions	(not supported)	(not supported)	all software versions
1700	Switch 1700-24	J9080A	all software versions	VB.01.09 and later	(not supported)	(not supported)	VB.02.00 and later
1800	Switch 1800-24G	J9028A/B	all software versions	PB.02.09 and later	(not supported)	(not supported)	PB.03.00 and later
1810	1810G-24 Switch	J9450A	all software versions	all software versions	(not supported)	(not supported)	(not supported)
	V1810-48G Switch	J9660A	(Gig-LH in J9450A only)	(Gig-LH in J9450A only)	all software versions	all software versions	
2510	Switch 2510-24	J9019A/B	all software versions	all software versions	(not supported)	(not supported)	Q.11.16 and later
	Switch 2510-48	J9020A			all software versions	all software versions	U.11.10 and later
	Switch 2510G-24 Switch 2510G-48	J9279A J9280A			all software versions	all software versions	(not supported)
2520	2520-8-PoE Switch	J9137A	all software versions	all software versions	(not supported)	(not supported)	all software versions
	2520-24-PoE Switch	J9138A					
	2520G-8-PoE Switch	J9298A					
	2520G-24-PoE Switch	J9299A					
2600	Switch 2626	J4899A/B/C	all software versions	H.08.98 and later	(not supported)	(not supported)	H.10.72 and later
	Switch 2650	J4900A/B/C					
	Switch 2626-PWR	J8164A					
	Switch 2650-PWR	J8165A					
	Switch 2600-8-PWR	J8762A					
2610	Switch 2610-24	J9085A	all software versions	all software versions	all software versions	all software versions	R.11.22 and later
	Switch 2610-48	J9088A					
	Switch 2610-24-PWR	J9087A					
	Switch 2610-48-PWR	J9089A					
	Switch 2610-24/12PWR	J9086A					
2615	2615-8-PoE Switch	J9565A	all software versions	all software versions	(not supported)	(not supported)	all software versions
2620	2620-24 Switch	J9623A	all software versions	all software versions	all software versions	all software versions	all software versions
	2620-48 Switch	J9626A					
	2620-24-PoE+ Switch	J9625A					
	2620-48-PoE+ Switch	J9627A					
	2620-24-PPoE+ Switch	J9624A					

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

Gigabit "B" and "C" versions

HP Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T ¹ (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software	
2800	Switch 2824 Switch 2848	J4903A J4904A	all software versions	i.08.103 and later	(not supported)	(not supported)	i.10.69 and later
2810	Switch 2810-24G Switch 2810-48G	J9021A J9022A	all software versions	all software versions	(not supported)	(not supported)	N.11.14 and later
2900	Switch 2900-24G Switch 2900-48G	J9049A J9050A	all software versions	all software versions	(not supported)	(not supported)	T.13.45 and later
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch	J9145A J9147A J9146A J9148A	all software versions	all software versions	(not supported)	(not supported)	all software versions
2915	2915-8G-PoE Switch	J9562A	all software versions	all software versions	(not supported)	(not supported)	all software versions
3400cl	Switch 3400cl-24G Switch 3400cl-48G	J4905A J4906A	all software versions	all software versions	(not supported)	(not supported)	(not supported)
3500	3500-24 Switch 3500-48 Switch 3500-24-PoE Switch 3500-48-PoE Switch	J9470A J9472A J9471A J9473A	K.14.31 and later	K.14.31 and later	(not supported)	(not supported)	K.14.31 and later
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR	J8692A J8693A	all software versions	all software versions	(not supported)	(not supported)	K.13.45 and later
	3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch	J9310A J9311A	K.14.50 and later	K.14.50 and later			K.14.50 and later
3800	3800-24G-2SFP+ Switch 3800-48G-4SFP+ Switch 3800-24G-PoE+-2SFP+ Switch 3800-48G-PoE+-4SFP+ Switch 3800-24SFP-2SFP+ Switch	J9575A J9576A J9573A J9574A J9584A	all software versions	all software versions	all software versions	all software versions	all software versions
4100gl	Switch gl 6-Port Mini-GBIC Module Switch gl 20-Port 10/100/1000 Module	J4893A J4908A	all software versions	G.07.103 and later	G.07.69 and later	G.07.69 and later	(not supported)
4200vl	Switch vl 4-Port Mini-GBIC Module	J8776A	all software versions	all software versions	all software versions	all software versions	L.11.16 and later
	Switch vl 20-Port Gig-T + 4-Port SFP Module	J9033A					
5300xl	Switch xl 4-Port Mini-GBIC Module	J4878A/B	all software versions	E.10.36 and later	E.09.22 and later	E.09.22 and later	E.11.08 and later
	Switch xl 16-Port 10/100/1000 Module	J4907A			(not supported)	(not supported)	

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

Gigabit "B" and "C" versions

HP Networking Switch Series	Product Name	Product Number	Gigabit-SX, LX, LH (J4858B, J4859B, J4860B) (J4858C, J4859C, J4860C)		1000BASE-T ¹ (J8177B) (J8177C)		Gigabit-BX (J9142B, J9143B)	
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software		
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later	
	Switch zl 24-Port Mini-GBIC Module	J8706A						
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	K.14.34 and later	K.14.34 and later	K.14.34 and later	K.14.34 and later		K.15.02.0004 and later
	24-Port SFP v2 zl Module	J9537A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later		
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A						
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A						
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A							
8-Port 10-GbE SFP+ v2 zl Module	J9538A			(not supported)	(not supported)			
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
6108	Switch 6108	J4902A	all software versions	H.07.88 and later	(not supported)	(not supported)	(not supported)	
6120	6120G/XG Blade Switch	498358-B21	SX, LX: all versions LH: not supported	SX, LX: all versions LH: not supported	all software versions	all software versions	(not supported)	
	6120XG Blade Switch	516733-B21						
6200yl	Switch 6200yl-24G-mGBIC	J8992A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later	
6600	6600-24G Switch	J9263A	K.14.03 and later	K.14.03 and later	(not supported)	(not supported)	K.14.03 and later	
	6600-24G-4XG Switch	J9264A						
	6600-48G Switch	J9451A	K.14.24 and later	K.14.24 and later			K.14.24 and later	
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	all software versions	all software versions	CY.01.02.0050 and later	CY.01.02.0050 and later	(not supported)	
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	all software versions	all software versions	all software versions	all software versions	K.13.45 and later	
	Switch zl 24-Port Mini-GBIC Module	J8706A						
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	K.14.34 and later	K.14.34 and later	K.14.34 and later	K.14.34 and later		K.15.02.0004 and later
	24-Port SFP v2 zl Module	J9537A	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later		
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A						
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A						
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A							
8-Port 10-GbE SFP+ v2 zl Module	J9538A			(not supported)	(not supported)			
	20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A						
	20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A						
9300m	EP 8-Port Mini-GBIC Redundant Management Module	J4885A	all software versions	all software versions	07.8.00a and later ²	(not supported)	(not supported)	
	EP 16-Port Mini-GBIC Module	J4894A						
9408sl	9400sl 40-Port Mini-GBIC Module	J8684A	all software versions	all software versions	02.1.00c and later	(not supported)	(not supported)	

HP Networking Legacy ProCurve Mini-GBIC and SFP Support Information

- HP ProCurve products and accessories offer a lifetime warranty, unsurpassed in the marketplace.
- HP ProCurve Networking stands behind our products because we build them to precise specifications and thoroughly test them.
- HP ProCurve mini-GBICs and SFPs are specified and tested as rigorously as the devices in which they are used.
- Non-ProCurve mini-GBICs and SFPs are of unknown quality and therefore cannot be supported with our lifetime warranty.

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

HP Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs		
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-FX (J9054C)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
1400	Switch 1400-24G	J9078A	all software versions	(not supported)	(not supported)	(not supported)
1410	1410-24G Switch	J9561A	all software versions	all software versions	all software versions	all software versions
1700	Switch 1700-24	J9080A	all software versions	(not supported)	(not supported)	(not supported)
1800	Switch 1800-24G	J9028A/B	all software versions	(not supported)	(not supported)	(not supported)
1810	1810G-24 Switch	J9450A	all software versions	all software versions	all software versions	all software versions
	V1810-48G Switch	J9660A	(not supported)			(not supported)
2510	Switch 2510-24	J9019A/B	(not supported)	Q.10.04 and later	Q.10.04 and later	Q.11.16 and later
	Switch 2510-48	J9020A		all software versions	all software versions	U.11.10 and later
	Switch 2510G-24	J9279A		all software versions	all software versions	Y.11.03 and later
	Switch 2510G-48	J9280A				
2520	2520-8-PoE Switch	J9137A	(not supported)	all software versions	all software versions	all software versions
	2520-24-PoE Switch	J9138A				
	2520G-8-PoE Switch	J9298A			J.14.32 and later	
	2520G-24-PoE Switch	J9299A				
2600	Switch 2626	J4899A/B/C	all software versions	(not supported)	(not supported)	(not supported)
	Switch 2650	J4900A/B/C				
	Switch 2626-PWR	J8164A				
	Switch 2650-PWR	J8165A				
	Switch 2600-8-PWR	J8762A				
2610	Switch 2610-24	J9085A	(not supported)	all software versions	all software versions	R.11.22 and later
	Switch 2610-48	J9088A				
	Switch 2610-24-PWR	J9087A				
	Switch 2610-48-PWR	J9089A				
	Switch 2610-24/12PWR	J9086A				
2615	2615-8-PoE Switch	J9565A	(not supported)	all software versions	A.14.07 and later	all software versions
2620	2620-24 Switch	J9623A	(not supported)	all software versions	all software versions	all software versions
	2620-48 Switch	J9626A				
	2620-24-PoE+ Switch	J9625A				
	2620-48-PoE+ Switch	J9627A				
	2620-24-PPoE+ Switch	J9624A				
2800	Switch 2824	J4903A	all software versions	i.10.30 and later	i.10.30 and later	i.10.69 and later
	Switch 2848	J4904A				
2810	Switch 2810-24G	J9021A	(not supported)	N.10.07 and later	N.10.07 and later	N.11.14 and later
	Switch 2810-48G	J9022A				

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

HP Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs				
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	(J9054C)	100-BX (J9099B, J9100B)		
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software		
2900	Switch 2900-24G Switch 2900-48G	J9049A J9050A	(not supported)	T.12.01 and later	T.12.01 and later	T.13.45 and later		
2910al	2910al-24G Switch 2910al-48G Switch 2910al-24G-PoE+ Switch 2910al-48G-PoE+ Switch	J9145A J9147A J9146A J9148A	(not supported)	all software versions	all software versions	all software versions		
2915	2915-8G-PoE Switch	J9562A	(not supported)	all software versions	A.14.07 and later	all software versions		
3400cl	Switch 3400cl-24G Switch 3400cl-48G	J4905A J4906A	all software versions	(not supported)	(not supported)	(not supported)		
3500	3500-24 Switch 3500-48 Switch 3500-24-PoE Switch 3500-48-PoE Switch	J9470A J9472A J9471A J9473A	(not supported)	K.14.31 and later	K.14.31 and later	K.14.31 and later		
3500yl	Switch 3500yl-24G-PWR Switch 3500yl-48G-PWR	J8692A J8693A	(not supported)	K.12.01 and later	K.12.01 and later	K.13.45 and later		
	3500yl-24G-PoE+ Switch 3500yl-48G-PoE+ Switch	J9310A J9311A		K.14.50 and later	K.14.50 and later	K.14.50 and later		
3800	3800-24G-2SFP+ Switch 3800-48G-4SFP+ Switch 3800-24G-PoE+-2SFP+ Switch 3800-48G-PoE+-4SFP+ Switch	J9575A J9576A J9573A J9574A	(not supported)	(not supported)	(not supported)	(not supported)		
	3800-24SFP-2SFP+ Switch	J9584A					all software versions	all software versions
	4100gl	Switch gl 6-Port Mini-GBIC Module Switch gl 20-Port 10/100/1000 Module		J4893A J4908A	all software versions	(not supported)	(not supported)	(not supported)
	4200vl	Switch vl 4-Port Mini-GBIC Module Switch vl 20-Port Gig-T + 4-Port SFP Module		J8776A J9033A	(not supported)	(not supported)	(not supported)	(not supported)
			L.10.24 and later	L.10.24 and later		L.11.16 and later		
5300xl	Switch xl 4-Port Mini-GBIC Module Switch xl 16-Port 10/100/1000 Module	J4878A/B J4907A	all software versions	(not supported)	(not supported)	(not supported)		

Genuine HP ProCurve Mini-GBICs and SFPs (continued)

HP Networking Switch Series	Product Name	Product Number	Gigabit "A" versions	100-Megabit SFPs		
			Gigabit-SX, LX, LH (J4858A, J4859A, J4860A)	100-FX (J9054B)	100-FX (J9054C)	100-BX (J9099B, J9100B)
			Supported with This Software	Supported with This Software	Supported with This Software	Supported with This Software
5400zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	K.12.01 and later	K.12.01 and later	K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A	(not supported)	K.12.01 and later	K.12.01 and later	K.13.45 and later
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	(not supported)	K.14.34 and later	K.14.34 and later	K.14.34 and later
	24-Port SFP v2 zl Module	J9537A	(not supported)	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A				
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A				
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A					
8-Port 10-GbE SFP+ v2 zl Module	J9538A	(not supported)	(not supported)	(not supported)	(not supported)	
20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A					
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A					
6108	Switch 6108	J4902A	all software versions	(not supported)	(not supported)	(not supported)
6120	6120G/XG Blade Switch	498358-B21	(not supported)	(not supported)	(not supported)	(not supported)
	6120XG Blade Switch	516733-B21	(not supported)	(not supported)	(not supported)	(not supported)
6200yl	Switch 6200yl-24G-mGBIC	J8992A	(not supported)	K.12.01 and later	K.12.01 and later	K.13.45 and later
6600	6600-24G Switch	J9263A	(not supported)	K.14.03 and later	K.14.03 and later	K.14.03 and later
	6600-24G-4XG Switch	J9264A		K.14.24 and later	K.14.24 and later	K.14.24 and later
	6600-48G Switch	J9451A		K.14.24 and later	K.14.24 and later	K.14.24 and later
8100fl	Switch fl 10-Port Mini-GBIC Interface Module	J8735A	(not supported)	(not supported)	(not supported)	(not supported)
8200zl	Switch zl 20-Port 10/100/1000 + 4-Port Mini-GBIC Module	J8705A	(not supported)	all software versions	all software versions	K.13.45 and later
	Switch zl 24-Port Mini-GBIC Module	J8706A	(not supported)	all software versions	all software versions	K.13.45 and later
	20-Port 10/100/1000 PoE+ and 4-Port SFP zl Module	J9308A	(not supported)	K.14.34 and later	K.14.34 and later	K.14.34 and later
	24-Port SFP v2 zl Module	J9537A	(not supported)	K.15.02.0004 and later	K.15.02.0004 and later	K.15.02.0004 and later
	20-Port Gig-T / 4-Port SFP v2 zl Module	J9549A				
	20-Port Gig-T PoE+ / 4-Port SFP v2 zl Module	J9535A				
12-Port Gig-T PoE+ / 12-Port SFP v2 zl Module	J9637A					
8-Port 10-GbE SFP+ v2 zl Module	J9538A	(not supported)	(not supported)	(not supported)	(not supported)	
20-Port Gig-T / 2-Port SFP+ v2 zl Module	J9548A					
20-Port Gig-T PoE+ / 2-Port SFP+ v2 zl Module	J9536A					
9300m	EP 8-Port Mini-GBIC Redundant Management Module	J4885A	all software versions	(not supported)	(not supported)	(not supported)
	EP 16-Port Mini-GBIC Module	J4894A	all software versions	(not supported)	(not supported)	(not supported)
9408sl	9400sl 40-Port Mini-GBIC Module	J8684A	all software versions	(not supported)	(not supported)	(not supported)

Footnotes

¹ The J8177B/C 1000BASE-T mini-GBIC is not supported in dual-personality ports.

² For the 9300m, the J8177B 1000BASE-T mini-GBIC is supported only in EP modules.

³ 3rd party products from non-ProCurve vendors are not supported and will not function.

⁴ Non-genuine ProCurve "B version" and "C version" mini-GBICs are not supported and will not function.

⁵ Supported: Qualified for operation in HP ProCurve switches and warranty support from HP ProCurve Networking.

⁶ Might function: The HP ProCurve switch attempts to enable this non-ProCurve mini-GBIC.

Non-ProCurve Mini-GBIC and SFP Support

HP ProCurve Switch Series	Software Versions	Genuine 3rd Party "A versions" from ProCurve Vendors ³		Non-Genuine ProCurve SX, LX, LH "A versions" ⁴	
		Supported? ⁵	Might Function? ⁶	Supported?	Might Function?
1400-24G (J9078A), 1410-24G (J9561A)	all software versions	no	yes	no	yes
1700-24 (J9080A)	all software versions	no	yes	no	yes
1800-24G (J9028A/B), 1810G-24, 48 (J9450A, J9660A)	all software versions	no	yes	no	yes
2510, 2520	all software versions	no	no	no	no
2600 'A' (J4899A, J4900A)	H.07.02 - H.08.81	no	yes	no	yes
	H.08.82 - H.08.97	no	yes	no	no
	H.08.98 and later	no	yes	no	yes
2600-PWR (J8164A, J8165A)	H.07.41 - H.08.81	no	yes	no	yes
	H.08.82 - H.08.97	no	yes	no	no
	H.08.98 and later	no	yes	no	yes
2600 'B', 2600 'C' (J4899B/C, J4900B/C)	all software versions	no	yes	no	no
2600-8-PWR (J8762A)	all software versions	no	yes	no	no
2610, 2615-8-PoE (J9565A), 2620	all software versions	no	no	no	no
	2810	all software versions	no	no	no
2824, 2848 (serial # < SG505xxxx)	i.07.31 - i.08.80	no	yes	no	yes
	i.08.81 - i.08.97	no	yes	no	no
	i.08.98 and later	no	yes	no	yes
2824, 2848 (serial # >= SG505xxxx)	i.07.31 - i.08.50	no	yes	no	yes
	i.08.51 - i.08.102	no	yes	no	no
	i.08.103 and later	no	yes	no	yes
2900, 2910al, 2915-8G-PoE (J9562A)	all software versions	no	no	no	no
3400cl	all software versions	no	yes	no	no
3500, 3500yl, 3800	all software versions	no	no	no	no
4100gl	all software versions	no	yes	no	yes
4200vl	all software versions	no	no	no	no
5300xl	E.05.04 - E.10.04	no	yes	no	yes
	E.10.05 - E.10.35	no	yes	no	no
	E.10.36 and later	no	yes	no	yes
5400zl	all software versions	no	no	no	no
6108	all software versions	no	yes	no	yes
6120, 6200yl, 6600	all software versions	no	no	no	no
8100fl	all software versions	no	no	no	no
8200zl	all software versions	no	no	no	no
9300m, 9408sl	all software versions	no	yes	no	yes

