Windows®. Life without Walls™. Fujitsu recommends Windows 7.



### **DATASHEET**

## FUJITSU LIFEBOOK AH530 NOTEBOOK

#### YOUR ESSENTIAL PARTNER

#### **LIFEBOOK AH530**

The LIFEBOOK AH530 notebook is slim stylish design notebook with a high definition 39.6cm (15.6-inch) glossy LCD in 16:9 widescreen format. With HDMI you can also enjoy media on your TV. Integrated WLAN and Bluetooth® provide you with the high connectivity. The flat spill-resistant keyboard with num pad provides extra reliability and usability.

#### HIGH PERFORMANCE

Experience the smart family of Intel® Core™ processors that deliver performance that adapts to your needs, making laptops faster and more responsive.

■ New Intel® Core™ processors and latest Intel® mobile platform

#### **HIGH CONNECTIVITY**

Anytime, anywhere with high connectivity for work and private.

■ Integrated WLAN and Bluetooth®, 1.3 megapixel webcam, and digital microphone

#### **HIGH USABILITY AND SECURITY**

Experience the ease of use and protect your most valuable data like confidential figures, pictures, videos and more.

■ Special flat cap spill-resistant keyboard with full num pad and kensington lock















### **COMPONENTS**

PROCESSOR	Intel® Core™ i7-620M processor (2.66 GHz, 4 MB)	
	Intel® Core™ i5-560M processor (2.66 GHz, 3 MB)	
	Intel® Core™ i5-520M processor (2.4 GHz, 3 MB)	
	Intel® Core™ i5-460M processor (2.53 GHz, 3 MB)	
	Intel® Core™ i5-450M processor (2.40 GHz, 3 MB) *	
	Intel® Core™ i3-370M processor (2.40 GHz, 3 MB) *	
	Intel® Core™ i3-350M processor (2.26 GHz, 3 MB) *	
	Intel® Pentium® processor P6100 (2.00 GHz, 3 MB)	
	Intel® Pentium® processor P6000 (1.86 GHz, 3 MB)	
	Intel® Celeron® processor P4600 (2.00 GHz, 2 MB)	
	Intel® Celeron® processor P4500 (1.86 GHz, 2 MB)	
PROCESSOR NOTES	*Processor only for retail, SMB, education and government	
OPERATING SYSTEM		
Operating system optional preinstalled		
	Genuine Windows® 7 Home Premium	
	Genuine Windows® 7 Home Basic Genuine Windows® 7 Starter (EM) 32-bit	
Operating system compatible	Genuine Windows® XP Professional	
Operating system notes	All Windows® 7 versions are Office 2007 ready.	All Windows® 7 versions are Office 2007 ready.
operating system notes	Dependent on configuration Windows 7® versions are:	All Williams 7 versions are office 2007 ready.
	Microsoft Office 2007 ready	
	Microsoft Office 2010 preloaded. Purchase a Product Key to	
	activate a full Microsoft Office 2010 suite.	
MEMORY MODULES	1 GB (module(s) 1 GB) DDR3, 1066 MHz, PC3-8500, DIMM	
	2 GB ( module(s) 2 GB) DDR3, 1066 MHz, PC3-8500, DIMM	
Supported capacity RAM (max.)	8 GB	
Memory slots total	2	
Memory slot type	SO DIMM (DDR3, 1066 MHz)	
HARD DISK DRIVES (INTERNAL)	SATA, 5400 rpm, 500 GB, 2.5-inch	
,	SATA, 5400 rpm, 320 GB, 2.5-inch	
	SATA, 5400 rpm, 250 GB, 2.5-inch	
	SATA, 5400 rpm, 160 GB, 2.5-inch	
Hard disk notes	One Gigabyte equals one billion bytes, when referring to hard	I disk drive canacity
	Accessible capacity may vary, also depending on used softw	
WIRELESS TECHNOLOGIES		
	V2.1	
Bluetooth		
	IEEE 802.11b/g/n	
Integrated WLAN	<u> </u>	
Integrated WLAN	IEEE 802.11b/g/n DVD Super Multi	
Integrated WLAN OPTICAL DRIVE OPTIONS	<u> </u>	LIFEBOOK AH530 Crimson Red Glossy
Integrated WLAN OPTICAL DRIVE OPTIONS Base unit	DVD Super Multi	LIFEBOOK AH530 Crimson Red Glossy
Integrated WLAN OPTICAL DRIVE OPTIONS  Base unit GENERAL SYSTEM INFORMATION	DVD Super Multi	LIFEBOOK AH530 Crimson Red Glossy
Integrated WLAN OPTICAL DRIVE OPTIONS  Base unit GENERAL SYSTEM INFORMATION Chipset	DVD Super Multi  LIFEBOOK AH530 Glossy	LIFEBOOK AH530 Crimson Red Glossy  Black/crimson red
Integrated WLAN OPTICAL DRIVE OPTIONS  Base unit GENERAL SYSTEM INFORMATION Chipset Color	DVD Super Multi  LIFEBOOK AH530 Glossy  Intel® HM55	
Integrated WLAN  OPTICAL DRIVE OPTIONS  Base unit  GENERAL SYSTEM INFORMATION  Chipset  Color  Material	DVD Super Multi  LIFEBOOK AH530 Glossy  Intel® HM55  Black	Black/crimson red
Integrated WLAN OPTICAL DRIVE OPTIONS  Base unit GENERAL SYSTEM INFORMATION Chipset Color Material DISPLAY	DVD Super Multi  LIFEBOOK AH530 Glossy  Intel® HM55  Black Glossy	Black/crimson red Glossy
Bluetooth Integrated WLAN  OPTICAL DRIVE OPTIONS  Base unit  GENERAL SYSTEM INFORMATION Chipset  Color Material  DISPLAY Display Aspect ratio	DVD Super Multi  LIFEBOOK AH530 Glossy  Intel® HM55  Black	Black/crimson red Glossy

GRAPHICS	
Max. resolution external display	1920 x 1200 pixel
Graphics brand name	Intel® HD Graphics
Graphics features	DirectX® 10 support
Shared video memory	up to 1695 MB
INTERFACES	
Memory card slots	1 x 4in1 Card Reader (SD /SDHC / MS / MS Pro)
ExpressCard slots	1 (34/54 mm)
USB 2.0 total	3
VGA	1
HDMI	1
Ethernet (RJ-45)	1
DC-in	1
Audio: line-in / microphone	1
Audio: line-out / headphone	1
Internal microphones	1
Kensington Lock support	2
WIRED COMMUNICATION	
LAN	10/100/1000 MBit/s
KEYBOARD AND POINTING DEVICES	
RETBOARD AND TORTING DEVICES	Spill-resistant keyboard with number block
	Number of keyboard keys: 106, Keyboard pitch: 19.8 mm, Keyboard stroke: 1.8 mm
	Touchpad
	Status LED
MULTIMEDIA	
Audio type	On board
Audio features	Support of high-definition audio, 2x built-in speakers (stereo), Built-in digital microphone, Sound volume control via function key (down: Fn+F8; up: Fn+F9)
Audio features  Camera	
	key (down: Fn+F8; up: Fn+F9)
Camera	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel
Camera POWER SUPPLY	key (down: Fn+F8; up: Fn+F9)
Camera  POWER SUPPLY  AC adapter  Rated voltage range	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)
Camera POWER SUPPLY AC adapter	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz  Li-lon battery 6-cell, 4400 mAh, 48 Wh
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz  Li-lon battery 6-cell, 4400 mAh, 48 Wh  up to 6 h  Battery life may vary depending on product model, configuration, applications, power management settings and features
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz  Li-lon battery 6-cell, 4400 mAh, 48 Wh  up to 6 h  Battery life may vary depending on product model, configuration, applications, power management settings and features
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (S0,	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz  Li-lon battery 6-cell, 4400 mAh, 48 Wh  up to 6 h  Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (S0, running appl., CD in use)  Power consumption: Idle (S0, running	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz  Li-lon battery 6-cell, 4400 mAh, 48 Wh  up to 6 h  Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (SO, running appl., CD in use)  Power consumption: Idle (SO, running OS, Idle mode)  Power consumption: Standby (S3,	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A) 100 - 240 V (AC Input) 50 - 60 Hz Li-lon battery 6-cell, 4400 mAh, 48 Wh up to 6 h Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (S0, running appl., CD in use)  Power consumption: Idle (S0, running OS, Idle mode)  Power consumption: Standby (S3, energy saving mode, WOL enabled)  Power consumption: Minimum (ACPI	key (down: Fn+F8; up: Fn+F9)  Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A)  100 - 240 V (AC Input)  50 - 60 Hz  Li-lon battery 6-cell, 4400 mAh, 48 Wh  up to 6 h  Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W  10.8 W  0.92 W
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (SO, running appl., CD in use)  Power consumption: Idle (SO, running OS, Idle mode)  Power consumption: Standby (S3, energy saving mode, WOL enabled)  Power consumption: Minimum (ACPI status S5, soft off, WOL enabled)	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A) 100 - 240 V (AC Input) 50 - 60 Hz Li-lon battery 6-cell, 4400 mAh, 48 Wh up to 6 h Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W  10.8 W  0.92 W  0.42 W
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (SO, running appl., CD in use)  Power consumption: Idle (SO, running OS, Idle mode)  Power consumption: Standby (S3, energy saving mode, WOL enabled)  Power consumption: Minimum (ACPI status S5, soft off, WOL enabled)  Power consumption note	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A) 100 - 240 V (AC Input) 50 - 60 Hz Li-lon battery 6-cell, 4400 mAh, 48 Wh up to 6 h Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W 10.8 W 0.92 W 0.42 W See white paper Energy Consumption http://docs.ts.fujitsu.com/dl.aspx?id=2baa27bc-1616-4c4a-bcf5-b423fb6a3c55
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (SO, running appl., CD in use)  Power consumption: Idle (SO, running OS, Idle mode)  Power consumption: Standby (S3, energy saving mode, WOL enabled)  Power consumption: Minimum (ACPI status S5, soft off, WOL enabled)  Power consumption note  Link to Energy White Paper	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A) 100 - 240 V (AC Input) 50 - 60 Hz Li-lon battery 6-cell, 4400 mAh, 48 Wh up to 6 h Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W 10.8 W 0.92 W 0.42 W See white paper Energy Consumption http://docs.ts.fujitsu.com/dl.aspx?id=2baa27bc-1616-4c4a-bcf5-b423fb6a3c55
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (SO, running appl., CD in use)  Power consumption: Idle (SO, running OS, Idle mode)  Power consumption: Standby (S3, energy saving mode, WOL enabled)  Power consumption: Minimum (ACPI status S5, soft off, WOL enabled)  Power consumption note  Link to Energy White Paper  DIMENSIONS / WEIGHT / ENVIRONMEN	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A) 100 - 240 V (AC Input) 50 - 60 Hz Li-lon battery 6-cell, 4400 mAh, 48 Wh up to 6 h Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W  10.8 W  0.92 W  0.42 W  See white paper Energy Consumption http://docs.ts.fujitsu.com/dl.aspx?id=2baa27bc-1616-4c4a-bcf5-b423fb6a3c55
Camera  POWER SUPPLY  AC adapter  Rated voltage range  Rated frequency range  1st battery  Runtime 1st battery  Battery notes  Related Processors for power consumption  Power consumption: Maximum (S0, running appl., CD in use)  Power consumption: Idle (S0, running OS, Idle mode)  Power consumption: Standby (S3, energy saving mode, WOL enabled)  Power consumption: Minimum (ACPI status S5, soft off, WOL enabled)  Power consumption note  Link to Energy White Paper  DIMENSIONS / WEIGHT / ENVIRONMENT  Dimensions (W x D x H)	key (down: Fn+F8; up: Fn+F9) Built-in webcam, 1.3 megapixel  19 V / 80 W (4.22 A) 100 - 240 V (AC Input) 50 - 60 Hz Li-lon battery 6-cell, 4400 mAh, 48 Wh up to 6 h Battery life may vary depending on product model, configuration, applications, power management settings and features utilized. Battery recharge time depends on usage.  41.0 W  10.8 W  0.92 W  0.42 W  See white paper Energy Consumption http://docs.ts.fujitsu.com/dl.aspx?id=2baa27bc-1616-4c4a-bcf5-b423fb6a3c55  TAL  378 x 252 x 35,7-38.4 mm

ADDITIONAL SOFTWARE	
Additional software (preinstalled)	Adobe Acrobat Reader CyberLink YouCam
	EasyGuide online user documentation
	Nero Essentials S (burning software)
	Norton Internet Security (incl. Firewall) 90 days version
Additional software (included as a CD/DVD)	Drivers & Utilities DVD (DUDVD)
SECURITY	
Physical security	Kensington Lock support
COMPLIANCE	
Europe	CE Marking
	R&TTE (WLAN, Bluetooth®)
Global	ENERGY STAR® 5.0
	RoHS (Restriction of hazardous substances)
	WiFi certified
	EPEAT® in progress
Russia	GOST
Compliance link	https://sp.ts.fujitsu.com/sites/certificates/default.aspx
WARRANTY	
Standard Warranty	1 year / 2 years (depending on country)
Service level MAINTENANCE AND SUPPORT SERVICE	Collect & Return Service / Bring-in Service (depending on county specific requirements) S - THE PERFECT EXTENSION
Recommended Service	3 years Collect & Return Service 5x9, Response Time: Next Business Day
Spare Parts availability	3 years
Service Weblink	http://ts.fujitsu.com/Supportservice

### RECOMMENDED ACCESSORIES

MicroSaver® Combination **Notebook Lock** 



Protect your notebook and the sensitive information on it from theft with the Kensington ComboSaver® Preset Combination Notebook Lock.

Order Code: S26361-F1650-L500

**Backpack A16** 



Lightweight design; padded notebook section; adjustable and padded shoulder Order Code: straps;zipper pocket on the front with lots of accessory compartments inside; S26391-F119-L165 mesh compartments; grip handle.

#### Messenger Sail5x



The Messenger Sail5x combines traditional urban-messenger bag styling with Order Code: a dual-compartment design. Features include well padded interior able to fit most 41cm / 16" widescreen notebook computers, a generous file and book compartment and pleated pockets for cords and adaptors. All slung by an adjustable and breathable padded strap, this stylish bag is perfect for shuttling your notebook between home and office

S26391-F119-L171

# Windows®. Life without Walls™. Fujitsu recommends Windows 7.

#### **Presenter IV Air**



Do you often give presentations? Would you like to communicate pro actively with your audience during your presentations? Step up to the plate and make use of your freedom of movement with the Presenter IV Air Whether you're leafing through informative material, adjusting audio files or using the laser pointer to indicate special features, you have everything reliably

under control with this presenter.

Thanks to the 2D air mouse function you can even do away with the cable mouse and navigate through your files with ease

Order Code: S26381-K440-L100

Page 5 / 6 http://ts.fujitsu.com/mobile

#### **FUJITSU PLATFORM SOLUTIONS**

In addition to Fujitsu LIFEBOOK AH530, Fujitsu provides a range of platform solutions. They combine reliable Fujitsu products with the best in services, know-how and worldwide partnerships.

#### **Dynamic Infrastructures**

With the Fujitsu Dynamic Infrastructures approach, Fujitsu offers a full portfolio of IT products, solutions and services, ranging from clients to datacenter solutions, Managed Infrastructure and Infrastructureas-a-Service. How much you benefit from Fujitsu technologies and services depends on the level of cooperation you choose. This takes IT flexibility and efficiency to the next level.

#### **Computing Products**

www.fujitsu.com/global/services/computing/

#### Software

www.fujitsu.com/software/

#### **MORE INFORMATION**

Learn more about Fujitsu LIFEBOOK AH530, please contact your Fujitsu sales representative or Fujitsu Business partner, or visit our website. http://ts.fujitsu.com/mobile

#### **FUJITSU GREEN POLICY INNOVATION**

Fujitsu Green Policy Innovation is our worldwide project for reducing burdens on the environment. Using our global know-how, we aim to resolve issues of environmental energy efficiency through IT.

Please find further information at http://www.fujitsu.com/global/about/environment/



#### **COPYRIGHTS**

All rights reserved, including intellectual property rights. Technical data subject to modifications and delivery subject to availability. Any liability that the data and illustrations are complete, actual or correct is excluded.

Designations may be trademarks and/or copyrights of the respective manufacturer, the use of which by third parties for their own purposes may infringe the rights of such owner. For further information see http://ts.fujitsu.com/terms of use.html

Copyright © Fujitsu Technology Solutions

#### **DISCLAIMER**

Technical data are subject to modification and delivery subject to availability. Any liability that the data and illustrations are complete, actual or correct is excluded. Designations may be trademarks and/or copyrights of the respective manufacturer, the use of which by third parties for their own purposes may infringe the rights of such owner

#### CONTACT

FUJITSU Technology Solutions Website: http://ts.fujitsu.com 2010-10-04 CE-EN