



MC3x Series Technical Accessory Guide



NOTE: MC3190-Z (RFID) discontinued 9/2019 - see PMB 10135
 MC32 Android configurations discontinued 12/2018 - see PMB 3138
 MC3190 (non-RFID) discontinued 8/2015
 MC3090-Z (RFID) discontinued 10/2011
 MC3000/MC3090 (non-RFID) discontinued 1/2011

NOTE: This document is only for general reference. Solution Builder and related PMBs should be used for product availability, pricing, and final solution selection.

* Zebra does not endorse or specifically recommend any **third-party products, accessories, or hardware**. ZEBRA DISCLAIMS ANY AND ALL LIABILITY, INCLUDING ANY EXPRESS OR IMPLIED WARRANTIES, WHETHER ORAL OR WRITTEN, FOR SUCH THIRD PARTY PRODUCTS, ACCESSORIES, OR HARDWARE. THE CUSTOMER ACKNOWLEDGES THAT NO REPRESENTATION HAS BEEN MADE BY ZEBRA AS TO THE FITNESS OF THE THIRD-PARTY PRODUCTS, ACCESSORIES, OR HARDWARE FOR THE CUSTOMER'S INTENDED PURPOSE.

Cradles and Charging

Cradles






Part Number	Picture	Description	Notes	Required Items
CRD-MC33-2SUCHG-01		MC33 Single Slot Charge/Communication Cradle	<ul style="list-style-type: none"> ▶Provides USB support ▶Supports MC33 terminal and spare battery charging ▶Will charge spare battery for MC33 or MC32. ▶Supports fast-charging of MC33 device and MC33 battery: <ul style="list-style-type: none"> - charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate. - charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate. ▶LED notification of spare battery charging status. ▶Not compatible for charging MC32 devices. ▶Note: Cradles manufactured after June 2018 will have a larger base/foot print to prevent the cradle from tipping over when using with MC33 RFID units. 	<ul style="list-style-type: none"> ▶Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01) ▶AC Line Cord (23844-00-00R). ▶USB Cable (25-124330-01R) for PC connection
CRD3000-1001RR		Single Slot Cradle	<ul style="list-style-type: none"> ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01) ▶AC Line Cord (23844-00-00R). ▶Also requires 25-63852-01R or 25-68596-01R for host communication. ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.





<p>CRD-MC32-100US-01</p>		<p>MC32/MC33 Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> ▶Includes adapter for charging MC32 spare battery ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes PWR-BGA12V50W0WW and CBL-DC-388A1-01R power supply/line cord, ADP-MC32-CUP0-01 MC3200 Battery Adapter Cup, and 23844-00-00 AC Line Cord ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. ▶Energy Star Compliant 	<ul style="list-style-type: none"> ▶25-63852-01R or 25-68596-01R for host communication. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.
<p>CRD3000-100RES</p>		<p>Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes PWR-BGA12V50W0WW, CBL-DC-388A1-01R and 23844-00-00 AC Line Cord ▶Energy Star Compliant ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶25-63852-01R or 25-68596-01R for host communication. ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.
<p>CRD3000-100RR</p>		<p>Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes KT-14000-148R power supply and 23844-00-00 AC Line Cord ▶Discontinued 12/2010, now use CRD3000-100RES ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶25-63852-01R or 25-68596-01R for host communication. ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.




<p>CRD-MC32-100INT-01</p>		<p>MC32/MC33 Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> ▶Includes adapter for charging MC32 spare battery ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes PWR-BGA12V50W0WWW (Power Supply), CBL-DC-388A1-01R (DC Line Cord) and ADP-MC32-CUP0-01 (MC32 Battery Adapter Cup) ▶Kit usually order by International customers ▶Energy Star Compliant ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶23844-00-00R and 25-63852-01R or 25-68596-01R for host communication. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.
<p>CRD3000-101RES</p>		<p>Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes PWR-BGA12V50W0WWW (Power Supply) and CBL-DC-388A1-01R (DC Line Cord) ▶Kit usually order by International customers ▶Energy Star Compliant ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶23844-00-00R and 25-63852-01R or 25-68596-01R for host communication. ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.
<p>CRD3000-101RR</p>		<p>Single Slot Cradle Kit</p>	<ul style="list-style-type: none"> ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes KT-14000-148R power supply ▶Kit usually order by International customers ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. ▶Discontinued 12/2010, now use CRD3000-101RES 	<ul style="list-style-type: none"> ▶23844-00-00R and 25-63852-01R or 25-68596-01R for host communication. ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.




<p>CRD3000-1000RR</p>		<p>Single Slot Cradle</p>	<ul style="list-style-type: none"> ▶Provides Serial/RS232 or USB support ▶Supports terminal and spare battery charging ▶LED notification of spare battery charging status. ▶Includes 50-14000-148R/KT-14000-148R, 25-63852-01R, and 25-68596-01R ▶Serial port not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. ▶Discontinued July 2008 - replaced by other kit configurations to make MC3000 kits similar to other MC devices. 	<ul style="list-style-type: none"> ▶23844-00-00R ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (XXXXXXXXXX) when using with MC33.
<p>PSCMC3100UE (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>Portsmith Single Slot Ethernet Cradle</p>	<ul style="list-style-type: none"> ▶Cradle communicates with the terminal via USB . ▶Connects to the LAN via a 10/100 mbps Ethernet connection. ▶Cradle accommodates terminals equipped with standard or extended batteries. ▶Includes a USB port (mini-A/B) allowing direct connectivity to a host computer or other USB peripherals. ▶Also includes spare battery charging and supports both standard and extended capacity batteries. ▶PSAK3100UE kit includes: PSCMC3100UE cradle, USB cable, Ethernet cable, Power Supply, and AC Cord ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶Portsmith Power Supply #190362-000LF or 190362-002LC ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.
<p>PS6SMC3000UE (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>Single Slot Ethernet Cradle</p> 	<ul style="list-style-type: none"> ▶Discontinued, now use PSCMC3100UE/PSCK-MC3100UE ▶Cradle communicates with the terminal via USB . ▶Connects to the LAN via a 10/100 mbps Ethernet connection. ▶Cradle accommodates terminals equipped with standard or extended batteries. ▶Includes a USB port (mini-A/B) allowing direct connectivity to a host computer or other USB peripherals. ▶Also includes spare battery charging and supports both standard and extended capacity batteries. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶Portsmith Power Supply #190362-000LF or 190362-002LC ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.




<p>PS6SMC3000M (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>Single Slot Modem Cradle</p> 	<ul style="list-style-type: none"> ▶Discontinued ▶Cradle provides a 56kbps analog modem interface ▶Modem connects to any standard analog telephone line ▶Includes a USB port (mini-A/B) allowing direct connectivity to a host computer or other USB peripherals. ▶Cradle accommodates mobile computers equipped with standard or extended life batteries. ▶Includes spare battery charging and supports both standard and extended life batteries. ▶Not compatible with Android versions of MC32. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. ▶Does not support charging of MC33 spare battery. 	<ul style="list-style-type: none"> ▶Portsmouth Power Supply #190362-000LF or 190362-002LC ▶MC32 Battery Adapter (ADP-MC32-CUP0-01) for charging spare MC32 battery. ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) when using with MC33.
<p>MDMC3000 D-W Available from MD Mobildata (3rd party) *</p> <p>http://www.mdmobildata.de</p>		<p>MC30/MC31/MC32 Desktop/Wallmount Charge-Only Cradle</p>	<ul style="list-style-type: none"> ▶Provides charging only ▶Cradle can be individually cascaded for multi-charger-use. ▶Can be also used for wall-mount, also in multi-charger option ▶Not compatible with MC33. 	
<p>CRD-MC33-5SCHG-01</p>		<p>MC33 5-Slot Charge-Only ShareCradle</p>	<ul style="list-style-type: none"> ▶Will charge up to five MC33 units. ▶Does not charge spare batteries. ▶Supports fast-charging of MC33: <ul style="list-style-type: none"> - charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate. - charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate. ▶Can be racked/ mounted in a standard 19inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01) 	<ul style="list-style-type: none"> ▶DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WWW) ▶AC Line Cord (23844-00-00R)
<p>CRD-MC33-4SC4BC-01</p>		<p>MC33 5-Slot Charge-Only ShareCradle with Spare Battery Charger</p>	<ul style="list-style-type: none"> ▶Will charge up to four MC33 terminals and four MC33 or MC32 spare batteries. ▶Supports fast-charging of MC33 devices and MC33 batteries: <ul style="list-style-type: none"> - charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate. - charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate. ▶Can be racked/ mounted in a standard 19inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01) 	<ul style="list-style-type: none"> ▶DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WWW) ▶AC Line Cord (23844-00-00R)




CHS3000-4001CR		4-Slot Charge Only Cradle	<ul style="list-style-type: none"> Charges 4 terminals Does not charge spare batteries. Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. Does not support fast-charging of MC33. 	<ul style="list-style-type: none"> DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WW) AC Line Cord (23844-00-00R) MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-400CES		4-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> Replaces CRD3000-400CR Charges 4 terminals Does not charge spare batteries. Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. Does not support fast-charging of MC33. Includes DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WW), AC Line Cord (23844-00-00R) Energy Star Compliant 	<ul style="list-style-type: none"> MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-400CR		4-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> Charges 4 terminals Does not charge spare batteries. Includes 50-14001-004R/50-14000-241R, 50-16002-042R, 23844-00-00R Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. Does not support fast-charging of MC33. Discontinued 12/2010, now use CRD3000-400CES 	<ul style="list-style-type: none"> MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-401CES		4-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> Replaces CRD3000-401CR Charges 4 terminals Does not charge spare batteries. Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. Does not support fast-charging of MC33. Includes DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WW) Kit usually order by International customers Energy Star Compliant 	<ul style="list-style-type: none"> 23844-00-00R MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-401CR		4-Slot Charge Only Cradle Kit	<ul style="list-style-type: none"> Charges 4 terminals Does not charge spare batteries. Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. Does not support fast-charging of MC33. Includes 50-14001-004R/50-14000-241R, 50-16002-042R Kit usually order by International customers Discontinued 12/2010, now use CRD3000-401CES 	<ul style="list-style-type: none"> 23844-00-00R MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.

CHS3000-4000CR		4-Slot Charge Only Cradle	<ul style="list-style-type: none"> •Charges 4 terminals •Does <u>not</u> charge spare batteries. •Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. •Does not support fast-charging of MC33. •Includes 50-14001-004R/50-14000-241R, 50-16002-042R •Discontinued July 2008 - replaced by other kit configurations to make MC3000 kits similar to other MC devices. 	<ul style="list-style-type: none"> •23844-00-00R •MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD-MC33-5SETH-01		MC33 5-Slot Ethernet/Charging ShareCradle	<ul style="list-style-type: none"> •Allows network speeds up to 1 Gb •Will charge up to five MC33 units. •Supports fast-charging of MC33: <ul style="list-style-type: none"> - charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate. - charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate. •Can be racked/ mounted in a standard 19 inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01) 	<ul style="list-style-type: none"> •DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WWW) •AC Line Cord (23844-00-00R)
CRD-MC33-4SE4BC-01		MC33 5-Slot Ethernet/Charging ShareCradle with Spare Battery Charger	<ul style="list-style-type: none"> •Allows network speeds up to 1 Gb •Will charge up to four MC33 terminals and four MC33 or MC32 spare batteries. •Supports fast-charging of MC33 devices and MC33 batteries: <ul style="list-style-type: none"> - charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate. - charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate. •Can be racked/ mounted in a standard 19 inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01) 	<ul style="list-style-type: none"> •DC Line Cord (CBL-DC-381A1-01) and Power Supply (PWR-BGA12V108W0WWW) •AC Line Cord (23844-00-00R)
CRD3X01-4001ER		4-Slot Ethernet/Charging Cradle	<ul style="list-style-type: none"> •Allows speeds up to 1 Gb •Uses less power than CRD3000-4001ER with IEEE 802.3az, "EEE" (Energy Efficient Ethernet) •Charges 4 terminals •Does <u>not</u> charge spare batteries. •Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. •Ethernet connectivity to host •Ethernet daisy chain support •USB Host connection to MC3X00 •May require additional driver from support website. •No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. 	<ul style="list-style-type: none"> •DC Line Cord (50-16002-029R) and Power Supply (PWRS-14000-241R) OR DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WWW) •AC Line Cord (23844-00-00R) •MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.


CRD3000-4001ER		4-Slot Ethernet/Charging Cradle	<ul style="list-style-type: none"> ▶Discontinued 10/12/2012, now use CRD3X01-4001ER ▶Charges 4 terminals ▶Does not charge spare batteries. ▶Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. ▶Ethernet connectivity to host ▶Ethernet daisy chain support ▶USB Host connection to MC3000 - does not require additional software on device. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. 	<ul style="list-style-type: none"> ▶DC Line Cord (50-16002-029R) and Power Supply (PWRS-14000-241R) OR DC Line Cord (CBL-DC-382A1-01) and Power Supply (PWR-BGA12V108W0WWW) ▶AC Line Cord (23844-00-00R) ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3X01-401EES		4-Slot Ethernet/Charging Cradle Kit	<ul style="list-style-type: none"> ▶Allows speeds up to 1 Gb ▶Charges 4 terminals ▶Does not charge spare batteries. ▶Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. ▶Ethernet connectivity to host ▶Ethernet daisy chain support ▶USB Host connection to MC3000 - does not require additional software on device. ▶Includes DC Line Cord (CBL-DC-382A1-01), Power Supply (PWR-BGA12V108W0WWW) ▶Uses less power than CRD3000-4001ER with IEEE 802.3az, "EEE" (Energy Efficient Ethernet) ▶May require additional driver from support website. ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. 	<ul style="list-style-type: none"> ▶AC Line Cord (23844-00-00R) ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-400EES		4-Slot Ethernet/Charging Cradle Kit	<ul style="list-style-type: none"> ▶Discontinued 10/12/2012, now use CRD3X01-401EES and 23844-00-00R ▶Charges 4 terminals ▶Does not charge spare batteries. ▶Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. ▶Ethernet connectivity to host ▶Ethernet daisy chain support ▶USB Host connection to MC3000 - does not require additional software on device. ▶Includes PWRS-14000-241R, 50-16002-042R, 23844-00-00R ▶Energy Star Compliant ▶No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. 	<ul style="list-style-type: none"> ▶MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.







CRD3000-400ER		4-Slot Ethernet/Charging Cradle Kit	<ul style="list-style-type: none"> •Charges 4 terminals •Does not charge spare batteries. •Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. •Ethernet connectivity to host •Ethernet daisy chain support •USB Host connection to MC3000 - does not require additional software on device. •Includes 50-14001-004R/50-14000-241R, 50-16002-042R, 23844-00-00R •No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. •Discontinued 12/2010, now use CRD3000-400EES 	<ul style="list-style-type: none"> •MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-401EES		4-Slot Ethernet/Charging Cradle Kit	<ul style="list-style-type: none"> •Discontinued 10/12/2012, now use CRD3X01-401EES •Charges 4 terminals •Does not charge spare batteries. •Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. •Ethernet connectivity to host •Ethernet daisy chain support •USB Host connection to MC3000 - does not require additional software on device. •Includes PWRS-14000-241R, 50-16002-042R •Kit usually order by International customers •Energy Star Compliant •No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. 	<ul style="list-style-type: none"> •AC Line Cord (23844-00-00R) •MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
CRD3000-401ER		4-Slot Ethernet/Charging Cradle Kit	<ul style="list-style-type: none"> •Charges 4 terminals •Does not charge spare batteries. •Does not support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. •Ethernet connectivity to host •Ethernet daisy chain support •USB Host connection to MC3000 - does not require additional software on device. •Includes 50-14001-004R/50-14000-241R, 50-16002-042R •Kit usually order by International customers •No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. •Discontinued 12/2010, now use CRD3000-401EES 	<ul style="list-style-type: none"> •AC Line Cord (23844-00-00R) •MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 when using with MC33.








<p>CRD3000-4000ER</p>		<p>4-Slot Ethernet/Charging Cradle</p>	<ul style="list-style-type: none"> •Charges 4 terminals •Does <u>not</u> charge spare batteries. •Does <u>not</u> support MC3090Z/MC3190Z (RFID) units. Device's back housing and antenna interfere with fit into cradle. •Ethernet connectivity to host •Ethernet daisy chain support •USB Host connection to MC3000 - does not require additional software on device. •Includes 50-14001-004R/50-14000-241R, 50-16002-042R •No communications support when using MC33. Will only serve as a Charge-Only cradle when used with MC33. Does not support fast-charging of MC33. •Discontinued July 2008 - replaced by other kit configurations to make MC3000 kits similar to other MC devices. 	<ul style="list-style-type: none"> •AC Line Cord (23844-00-00R) •MC33 Cradle Adapter (ADP-MC33-CRDCUP-01) - QTY 4 - when using with MC33.
<p>ADP-MC33-CRDCUP-01</p>		<p>MC33 Adapter Cup to MC30/MC31/MC32 Legacy Cradles</p>	<ul style="list-style-type: none"> •Allows MC33 to be used with MC30/MC31/MC32 Single Slot and Multi-Slot Cradles •NOTE: Adapter Cup doesn't provide communications support (USB, Serial, Ethernet). Will only provide charging support. •Does NOT support fast-charging of MC33. MC33 used in legacy cradles will be charged at standard rate: <ul style="list-style-type: none"> - charges 1X battery from 0-90% in about 3 hours at standard charging rate. - charges 2X battery from 0-90% in about 5.5 hours at standard charging rate. •Order one Adapter Cup for Single Slot Cradles and four Adapter Cups for Multi-Slot Cradles. 	
<p>BRKT-SCRD-SMRK-01</p>		<p>MC33 5-Slot ShareCradle Mounting Bracket</p>	<ul style="list-style-type: none"> •Allows for rack and wall mounting of one MC33 5-Slot ShareCradle, up to four MC33 Single Slot ShareCradles, or up to four MC32/MC33 4-Slot Battery Chargers. •Bracket can be mounted on standard 19" network rack or on a wall. •Has cable routing slots and removable power supply tray that stores and conceals power supplies. •Adjustable tabs & screw mounts for easy hanging/installation. •Adjustable orientations: <ul style="list-style-type: none"> - 25° High Density (5-Slot Charge Only Cradle) - Horizontal (Single Slot Cradle or 4-Slot Battery Chargers). •See the Bluetooth-Generic Accessories TAG for info on 3rd party Network Racks that can be used for mounting this bracket. 	

KT-136648-01R		Wall Mount Bracket for MC30/MC31/MC32 4-Slot Cradles	<ul style="list-style-type: none"> Allows cradle to be mounted on a wall. Replaces 8710-050006-01R. Updated design allows additional wall clearance when using CRD3000-4000 cradle and gun version of device. 	CRD3000-4000ER or CHS3000-4000CR
8710-050006-01R		Wall Mount Bracket for MC30/MC31/MC32 4-Slot Cradles	<ul style="list-style-type: none"> Discontinued 8/2011, now use KT-136648-01R Allows cradle to be mounted on a wall. 	CRD3000-4000ER or CHS3000-4000CR
KT-132400-01R		19" Rack Mount Bracket for MC30/MC31/MC32 4-Slot Cradles	<ul style="list-style-type: none"> Enables mounting of one 4-Slot Cradle (CRD3000-4000ER or CHS3000-4000CR) to a standard network rack. Cradle must first be mounted to Wall Mount Bracket which then attaches to Rack Mount Bracket. Bracket hides Power Supply and DC Line Cord 	Wall Mount Bracket (KT-136648-01R)


Battery Charging

Part Number	Picture	Description	Notes	Required Items
SAC-MC33-4SCHG-01		MC32/MC33 4-Slot Battery Charger	<ul style="list-style-type: none"> This cradle charges spare batteries only (1X/Standard or 2X/Extended size). Supports charging of both MC33 and MC32 batteries. Supports fast-charging of MC33 batteries: <ul style="list-style-type: none"> charges 1X battery from 0-90% in about 2 hours vs. 3 hours for standard charging rate. charges 2X battery from 0-90% in about 3.5 hours vs. 5.5 hours for standard charging rate. Can be used standalone or up to four chargers can be installed on Multi-Slot Wall/Rack Mount Bracket (BRKT-SCRD-SMRK-01). Not compatible with MC3000 or MC3100 series spare batteries. 	<p><u>To power single 4-slot Charger:</u></p> <ul style="list-style-type: none"> Power Supply (PWR-BGA12V50W0WW) DC Line Cord (CBL-DC-388A1-01) AC Line Cord (23844-00-00R) <p><u>To power two sets of 4-slot Chargers from one power supply:</u></p> <ul style="list-style-type: none"> Power Supply (PWR-BGA12V108W0WW) DC Y-Cable Line Cord (CBL-DC-523A1-01) AC Line Cord (23844-00-00R) <p><u>To power five 4-slot Chargers:</u></p> <p>Use MC33 20-Slot Battery Charger (SAC-MC33-20SCHG-01) instead.</p> <ul style="list-style-type: none"> PWR-BGA12V108W0WW CBL-DC-381A1-01





SAC-MC33-20SCHG-01		MC32/MC33 20-Slot Battery Charger	<ul style="list-style-type: none"> Charges MC33 or MC32 spare batteries (1X/Standard or 2X/Extended size). Uses 5-Slot ShareCradle with five 4-Slot Battery Chargers (SAC-MC33-4SCHG-01) attached. Does NOT support fast-charging of MC33 batteries. All battery types charged at standard rate: <ul style="list-style-type: none"> charges 1X battery from 0-90% in about 3 hours at standard charging rate. charges 2X battery from 0-90% in about 5.5 hours at standard charging rate. Can be racked/mounted in a standard 19 inch rack system via the mounting accessory (BRKT-SCRD-SMRK-01). Not compatible with MC3000 or MC3100 series spare batteries. 	<ul style="list-style-type: none"> Power Supply (PWR-BGA12V108W0WW) DC Line Cord (CBL-DC-381A1-01) AC Line Cord (23844-00-00R)
SAC7X00-4000CR		4-Slot Battery Charger	<ul style="list-style-type: none"> This cradle charges spare batteries only (1X or 2X size). Provides IEEE1725 compliance. Same charger used by MC7X (does not support MC50) The shims are used with the MC7X Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01) AC Line Cord (23844-00-00R) MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SACX000-4000CR		4-Slot Battery Charger	<ul style="list-style-type: none"> Discontinued 8/2011 This cradle charges spare batteries only (1X or 2X size) Same charger used by MC50 and MC3000 The shims are used with the MC70 Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> Power Supply (PWR-BGA12V50W0WW and CBL-DC-388A1-01 OR PWRS-14000-148R) AC Line Cord (23844-00-00R) MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SAC-MC32-400US-01		4-Slot MC32 Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 6/2019, now use SAC-MC33-4SCHG-01 and associated power supply and line cords - see PMB 10073. Charges MC32 batteries Includes SAC7X00-4000CR, ADP-MC32-CUP0-04, PWR-BGA12V50W0WW, CBL-DC-388A1-01R and 23844-00-00R Provides IEEE1725 compliance. Energy Star Compliant Does not support charging of MC33 batteries. 	
SAC7X00-400CES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Includes SAC7X00-4000CR, PWR-BGA12V50W0WW, CBL-DC-388A1-01R and 23844-00-00R Provides IEEE1725 compliance. Energy Star Compliant Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
701-01013-01ES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 8/2011 Includes SACX000-4000CR, PWRS-14000-148R, and 23844-00-00R Energy Star Compliant Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.

SACX000-410CES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 8/2011 Same as SACX000-4000CR, but also includes PWRS-14000-148R and 23844-00-00R Energy Star Compliant Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SACX000-400CR		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 12/2007 - replaced by SACX000-410CR Same as SACX000-4000CR, but also includes 50-14000-148R and 23844-00-00R Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SACX000-410CR		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Same as SACX000-4000CR, but also includes KT-14000-148R and 23844-00-00R Discontinued 12/2010, now use SACX000-410CES Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SAC-MC32-400INT-01		4-Slot MC32 Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 6/2019, now use SAC-MC32-4SCHG-01 and associated power supply and line cords - see PMB 10073. Charges MC32 batteries Includes SAC7X00-4000CR, ADP-MC32-CUP0-04, PWR-BGA12V50W0WWW, CBL-DC-388A1-01R and 23844-00-00R Provides IEEE1725 compliance. Kit usually order by International customers Energy Star Compliant Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R
SAC7X00-401CES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Includes SAC7X00-4000CR, PWR-BGA12V50W0WWW and CBL-DC-388A1-01R Provides IEEE1725 compliance. Kit usually order by International customers Energy Star Compliant Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SACX000-411CES		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 8/2011 Same as SACX000-4000CR, but also includes PWRS-14000-148R Kit usually order by International customers Energy Star Compliant Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
SACX000-401CR		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Discontinued 12/2007 - replaced by SACX000-410CR Same as SACX000-4000CR, but also includes 50-14000-148R Kit usually order by International customers Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.





SACX000-411CR		4-Slot Battery Charger Kit	<ul style="list-style-type: none"> Same as SACX000-4000CR, but also includes KT-14000-148R Kit usually order by International customers Discontinued 12/2010, now use SACX000-411CES Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
ADP-MC32-CUP0-01 (single pack) ADP-MC32-CUP0-04 (four pack)		MC32 Battery Charger Adapter	<ul style="list-style-type: none"> Allows MC32 batteries to be charged in 4-Slot Battery Charger (SAC7X00-4000CR) (order four pack) OR Single Slot Cradle (CRD3000-1001RR) (order single pack) Does not support charging of MC33 batteries. 	4-Slot Battery Charger (SAC7X00-4000CR) OR Single Slot Cradle (CRD3000-1001RR)
21-32665-45AR		UBC Adapter	<ul style="list-style-type: none"> To be discontinued 11/2019, see PMB 10213. This device makes the charging of multiple batteries easy and cost effective. Simply snap the battery into the adapter and slide the adapter into the UBC charging station. The charging station holds up to four adapters. Charges standard and high capacity batteries Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> KT32665-02R OR KT32665-03R OR UBC2000-I500DES MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
UBC2000-I500DES		UBC Charging Station	<ul style="list-style-type: none"> Quad bay charger. Holds four UBC adapter modules. Includes 50-16002-011R power cord and PWRS-14000-242R power supply Energy Star certified Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R 1-4 UBC adapters (21-32665-45AR) MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
UBC2000-I500DR		UBC Charging Station	<ul style="list-style-type: none"> Discontinued 12/2012, now use UBC2000-I500DES Quad bay charger. Holds four UBC adapter modules. Includes 50-16002-011R power cord and 50-14001-008R/50-14000-242R/PWRS-14000-242R power supply Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R 1-4 UBC adapters (21-32665-45AR) MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.
UBC2000-45AR		UBC Charging Station Kit	<ul style="list-style-type: none"> To be discontinued 11/2019, see PMB 10213. Quad bay charger. Holds four UBC adapter modules. Includes UBC2000-I500DES UBC Charging Station and four 21-32665-45AR UBC Adapters Does not support charging of MC33 batteries. 	<ul style="list-style-type: none"> 23844-00-00R MC32 Battery Adapter (ADP-MC32-CUP0-04) for charging MC32 batteries.









KT-32665-01R		Wall Mount Bracket for UBC2000 Battery Charger	►Discontinued 9/2011	
--------------	---	--	----------------------	--

Direct to Device Charging










Part Number	Picture	Description	Notes	Required Items
CBL-MC33-USBCHG-01		MC33 USB Communication/Charging Cable	►Only compatible with MC33.	For charging: ►USB charger... Indoor use: order Country Specific version of USB Power Supply (PWR-WUA5V12W0xx) In Vehicle use: USB Cigarette Lighter Adapter (CHG-AUTO-USB1-01)
VCA3000-01R		MC30/MC31/MC32 Auto Charge/Cigarette Lighter Adapter Cable	►12/24 volt DC input ►Not compatible with MC33.	
25-67873-03R		MC30/MC31/MC32 Auto Charge/Cigarette Lighter Adapter Cable	►Discontinued 10/2016, now use VCA3000-01R - PMB 2890 ►12 volt DC input ►Not compatible with MC33.	
25-70103-03R		MC30/MC31/MC32 Charge Only Cable Cup	►Not compatible with MC33.	►Power Supply (PWR-BUA5V16W0WW), ►DC Line Cord (CBL-DC-383A1-01) ►AC Line Cord (50-16000-182R) for charging









Communication Cables

Part Number	Picture	Description	Notes	Required Items
CBL-MC33-USBCHG-01		MC33 USB Communication/Charging Cable	►Only compatible with MC33.	For charging: ►USB charger... Indoor use: order Country Specific version of USB Power Supply (PWR-WUA5V12W0xx) In Vehicle use: USB Cigarette Lighter Adapter (CHG-AUTO-USB1-01)
25-67868-03R		MC30/MC31/MC32 USB Client Communication/Charging Cable with Cup	►Not compatible with MC33.	►Power Supply (PWR-BUA5V16W0WW), ►DC Line Cord (CBL-DC-383A1-01) ►AC Line Cord (50-16000-182R) for charging
25-67869-03R		MC30/MC31/MC32 USB Host Communication/Charging Cable with Cup	►Allows MC3000 to act as a USB Host device (i.e. connecting to USB printer, etc.) ►Not compatible with MC33. ►Discontinued May 2013	►Power Supply (PWR-BUA5V16W0WW), ►DC Line Cord (CBL-DC-383A1-01) ►AC Line Cord (50-16000-182R) for charging
25-69474-01R		MC30/MC31/MC32 USB Communication Cable for MSR3000	►Not compatible with MC33. ►Discontinued 12/20/13	MSR3000-100R

25-67866-03R		MC30/MC31/MC32 RS232/Serial Communication/Charging Cable with Cup	<ul style="list-style-type: none"> ▶Not compatible with Android versions of MC32. ▶Not compatible with MC33. 	<ul style="list-style-type: none"> ▶Power Supply (PWR-BUA5V16W0WW), ▶DC Line Cord (CBL-DC-383A1-01) ▶AC Line Cord (50-16000-182R) for charging
25-63852-01R		MC30/MC31/MC32 RS232/Serial Single-Slot cradle to ActiveSync PC/Host cable	<ul style="list-style-type: none"> ▶This is a spare cable. The CRD3000-1000 ships with this cable. ▶Not compatible with Android versions of MC32. ▶Not compatible with MC33. 	
25-124330-01R		MC33 USB Single-Slot Cradle to PC/Host cable	<ul style="list-style-type: none"> ▶Used with the MC33 Single Slot Cradle (CRD-MC33-2SUCHG-01) ▶Micro USB connection on cradle end 	
25-68596-01R		USB Single-Slot cradle to ActiveSync PC/Host cable	<ul style="list-style-type: none"> ▶Used with MC30/MC31/MC32 Single Slot Cradles. ▶Mini USB connection on cradle end 	
MDM9000-100R		Modem Module	<ul style="list-style-type: none"> ▶Discontinued 10/2014 ▶Connects to MC3000 via CRD3000-1000R (Single Slot Cradle). 	<ul style="list-style-type: none"> ▶25-63856-01R ▶CRD3000-1000RR <p>OR</p> <ul style="list-style-type: none"> ▶25-70924-01R
25-63856-01R		Modem Cable for Single-Slot Cradle	<ul style="list-style-type: none"> ▶Needed to connect the MDM9000-100R (Modem Module) to the CRD3000-1000RR (Single Slot Cradle). Allows single slot cradle to be used as a modem cradle. ▶Not compatible with Android versions of MC32. 	<ul style="list-style-type: none"> ▶MDM9000-100 ▶CRD3000-1000RR
KT-MC3000SERMODEMR		Modem Kit for Single Slot Cradle	<ul style="list-style-type: none"> ▶Discontinued 10/2014 ▶Includes MDM9000-100R and 25-63856-01R. Allows single slot cradle to be used as a modem cradle ▶Not compatible with Android versions of MC32. 	CRD3000-1000RR
25-70924-01R		MC30/MC31/MC32 Modem Cable Cup Adapter	<ul style="list-style-type: none"> ▶Needed to connect the MDM9000-100R (Modem Module) to the MC3000 without using a cradle. ▶Does not provide for device charging. ▶Discontinued May 2013 ▶Not compatible with Android versions of MC32. ▶Not compatible with MC33. 	MDM9000-100R

<p>KT-70924-01R</p>		<p>MC30/MC31/MC32 Modem Kit</p>	<ul style="list-style-type: none"> Discontinued 9/2011 Includes MDM9000-100R and 25-70924-01R. Does not provide for device charging. Not compatible with Android versions of MC32. Not compatible with MC33. 	
<p>PSAK-UCM (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>Portsmith USB Modem Adapter</p>	<ul style="list-style-type: none"> Discontinued Connects to MC3X00 via Single Slot USB cradle. Acts as USB Peripheral device to MC3X00 (USB host) Requires no separate power supply, operates on power draw directly from the USB connection. Kit includes PSA1U1M adapter and three USB cables for connecting to a variety of devices. Requires software driver from http://www.portsmith.com Not compatible with Android versions of MC32. Not compatible with MC33. 	<p>CRD3000-1000RR and USB Mini A to Type B conversion cable 170573-000 (PortSmith cable included in kit) OR 25-67868-03R and USB A Receptacle to Type-B Plug conversion cable. This will also require MC3x00 Control Panel applet software to force MC3x00 in USB Host mode.</p>
<p>PS6U1M (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>USB Modem Adapter</p> 	<ul style="list-style-type: none"> Discontinued Connects to MC3000 via Single Slot cradle or USB Cable Not compatible with Android versions of MC32. Not compatible with MC33. 	<p>CRD3000-1000RR and 25-68596-01R OR 25-67868-03R</p>
<p>PSAK-UCE (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>Portsmith USB Ethernet Adapter Kit for MC30/MC31/MC32 and MC3300 series</p>	<ul style="list-style-type: none"> Connects to MC3x00 via Single Slot USB cradles. Acts as USB Peripheral device to MC3x00 (USB host) Requires no separate power supply, has grounded wiring from both the USB and Ethernet ports, and operates on very low power draw directly from the USB connection. Molded end caps enable the adapters to be aligned side by side or top to bottom, for efficient use of desktop space and organization of cables. Kit includes PSA1U1E adapter and three USB cables for connecting to a variety of devices. Android devices require no additional drivers. Windows devices may require software driver from http://www.portsmith.com 	<p>For MC3300 Single Slot Charge/Communication Cradle (CRD-MC33-2SUCHG-01) For MC31/MC32 Single Slot Charge/Communication Cradle (CRD3000-1000RR)</p>
<p>PSA5BT1E (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>Portsmith Bluetooth Ethernet Adapter</p>	<ul style="list-style-type: none"> Discontinued Connects Android Bluetooth devices to Ethernet ONLY compatible with Android MC32 units Pair as many devices as desired Supports 5 concurrent Bluetooth connections to one Adapter PSAK-5BT1E KIT Includes: PSA5BT1E Bluetooth Ethernet Adapter, 5V power supply with AC adapter plugs for worldwide use and Ethernet cable 	


<p>PS6U1UPE (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>USB Ethernet Adapter</p> 	<ul style="list-style-type: none"> Discontinued 8/2012, now use PSAK-UCE Connects to MC3000 via Single Slot USB cradle or USB Cable. Acts as USB Peripheral device to MC3000 (USB host) Currently does not support MC31xx CE due to driver changes 	<p>CRD3000-1000RR and USB Mini A to Mini B conversion cable 170373-000 (PortSmith cable) OR 25-67868-03R and USB A receptacle to mini B conversion cable 190087-000 (PortSmith cable).</p>
<p>KT-88330-03R (3 pack) Discontinued 9/2011</p> <p>KT-88330-10R (10 pack) Discontinued 11/2011</p>		<p>ESD USB Adapter</p>	<ul style="list-style-type: none"> Provides ESD protection when connecting device to PC. 	
<p>FAUSB01 (3rd party) *</p> <p>http://www.blackbox.com</p>		<p>USB A Female to USB A Female adapter</p>	<ul style="list-style-type: none"> Allows the MC3000 to act as a USB host to connect to devices like USB flash drives, etc. This adapter works with the MC3000 Cable Cup adapter. 	<p>25-67868-03R OR 25-67869-03R</p>
<p>GXQU-06 (3rd party) *</p> <p>http://www.radioshack.com</p>		<p>JDI GoldX QuickConnect 5-in-1 USB Cable Kit (6 ft.)</p>	<ul style="list-style-type: none"> Allows the MC3000 to act as a USB host to connect to devices like USB flash drives, etc. This cable works with the MC3000 Single Slot cradle Use a mini A connector on one end and an A female connector on the other end. 	<p>CRD3000-1000RR</p>
<p>RDUYS08220007</p>		<p>USB mini-A to USB A Female adapter</p>	<ul style="list-style-type: none"> Allows the MC30xx to act as a USB host to connect to devices like USB flash drives/memory sticks, mice, etc. This adapter works with the MC3000 Single Slot Cradle. 	
<p>190087-000 (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>USB Adapter Cable: type-A receptacle to mini-B plug</p>	<ul style="list-style-type: none"> Allows the MC3000 USB Client Communication/Charging Cable with Cup to be connected to USB client peripherals like PortSmith's USB Ethernet Adapter. Can also be used to connect to other peripherals with a mini USB-B connector. 	
<p>170373-000 (3rd party) *</p> <p>http://www.portsmith.com</p>		<p>USB Cable: mini-A plug to mini-B plug</p>	<ul style="list-style-type: none"> Allows the MC3000 Single Slot Cradle to be connected to USB client peripherals like PortSmith's USB Ethernet Adapter. Can also be used to connect to other peripherals with a mini USB-B connector. 	
<p>P1031365-058</p>		<p>Cable Cup Adapter to QLn or ZQ6 Series Printers</p>	<ul style="list-style-type: none"> 50" coiled cable Not compatible with Android versions of MC32. Not compatible with MC33. 	








P1031365-060		Cable Cup Adapter to QLn or ZQ6 Series Printers	<ul style="list-style-type: none"> •50" coiled cable •Uses non-standard cable pin-out to MC3X00 - DSR will always be high. •Not compatible with Android versions of MC32. •Not compatible with MC33. 	
25-91513-01R		MC30/MC31/MC32 Cable Cup Adapter to QL Series Printers	<ul style="list-style-type: none"> •Not compatible with Android versions of MC32. •Not compatible with MC33. 	
25-91514-01R		MC30/MC31/MC32 Cable Cup Adapter to Road Warrior (RW) Series Printers	<ul style="list-style-type: none"> •Discontinued 9/2011 •Not compatible with Android versions of MC32. •Not compatible with MC33. 	
25-91512-01R		MC30/MC31/MC32 Cable Cup Adapter to O'Neil Printers	<ul style="list-style-type: none"> •Not compatible with Android versions of MC32. •Not compatible with MC33. 	
CBL-8800-100-DEXR		MC30/MC31/MC32 DEX Cable for MSR3000	<ul style="list-style-type: none"> •Not compatible with Android versions of MC32. •Not compatible with MC33. 	MSR3000-100R
CBL-8800-100-ON1R		MC30/MC31/MC32 O'Neil Printer Cable for MSR3000	<ul style="list-style-type: none"> •Not compatible with Android versions of MC32. •Not compatible with MC33. 	MSR3000-100R
CBL-8800-100-PAXR		MC30/MC31/MC32 Paxar Printer Cable for MSR3000	<ul style="list-style-type: none"> •Not compatible with Android versions of MC32. •Not compatible with MC33. 	MSR3000-100R
CBL-8800-100-ZEBR		MC30/MC31/MC32 Zebra QL Series Printer Cable for MSR3000	<ul style="list-style-type: none"> •Connects to QL series Zebra Printers •Not compatible with Android versions of MC32. •Not compatible with MC33. 	MSR3000-100R

Snap-On Accessories

Part Number	Picture	Description	Notes	Required Items
MSR3000-100R		MC30/MC31/MC32 Magnetic Stripe Reader (MSR)	<ul style="list-style-type: none"> Discontinued 5/2014 Compatible with all Straight Shooter, Rotating Head, Brick and Gun configurations (including 1X and 2X batteries). Does not work with MC3000 mechanical keyboard configurations. Reads up to three tracks of information and can be programmed to divide, rearrange, edit and validate fields of entered data. Also provides charging and communication (15 pin) connectors . Unit will NOT fit into cradle when attached to MSR Not compatible with Android versions of MC32. Not compatible with MC33. 	<ul style="list-style-type: none"> Power Supply (PWR-BUA5V16W0WW), DC Line Cord (CBL-DC-383A1-01) AC Line Cord (50-16000-182R) for charging
3PTY-TIS-MC33TGHD		Pistol Grip Trigger Handle for MC33 Straight-Shooter	<ul style="list-style-type: none"> Allows MC33 Straight-Shooter configurations to be used as a gun handle device. Simple compact trigger handle. Trigger handle mechanically presses the left trigger button on the MC33 when the trigger handle is pulled. Slides into position on the MC33 and locks into place using the handstrap tether point on the MC33. MC33 can be recharged in the cradle with the trigger handle on. Does not block access to camera on back of MC33, which allows for a gun handled camera-enabled device. The MC33 should not be held using the trigger handle while taking pictures to avoid getting user's hand in the shot. MC33 battery can be swapped without removing the trigger handle. IP-67 rated, surviving multiple drops on concrete (drop height: 5.9' 1.8 m) and offering a wide operating temperature range (5°F to 122°F/-15°C to +50°C). Trigger mechanism was designed for over 1 million pulls. MC33 Handstrap must be removed to use Trigger Handle. Only compatible with MC33 Straight-Shooter configurations. NOTE: This is a custom product. Please work with your Zebra representative to open a Custom Product Request (CPR) if you would like to order this item. 	

Soft Goods - Cases/Holsters




Part Number	Picture	Description	Notes	Required Items
SG-MC33-RDHLST-01		MC33 Rigid Holster	<ul style="list-style-type: none"> This carrying case secures the device to a belt. Only compatible with MC33, except MC33 RFID units. Not compatible with devices having Rubber Boot installed. 	







8710-050005-01R		MC30/MC31/MC32 Rigid Holster	<ul style="list-style-type: none"> ►This carrying case secures the device to a belt. ►Not compatible with devices having Rubber Boot installed. ►Not compatible with MC33 or RFID devices. 	
SG-MC3X-SHLSTB-01		Fabric Holster for Brick/Straight-Shooter or Rotating Head configurations	<ul style="list-style-type: none"> ►This carrying case secures the MC3x00 to a belt (using belt clip) or can be worn cross-body (using included strap). ►Compatible with all MC3X series Brick/Straight Shooter or Rotating Head units, including MC33. Not compatible with RFID devices though. ►Devices with Rubber Boot installed will fit into Holster. The fit will be tight though. ►Uses modified strap to secure device in holster vs. 11-69293-01R. 	
11-69293-01R		Fabric Holster for Brick/Straight-Shooter configuration	<ul style="list-style-type: none"> ►Discontinued 6/2018, now use SG-MC3X-SHLSTB-01 - PMB 10008 ►This carrying case secures the MC3x00 to a belt. The holster also includes a shoulder strap. ►Compatible with all MC3X series, including MC33. Not compatible with RFID devices though. ►Devices with Rubber Boot installed will fit into Holster. The fit will be tight though. 	
SG-MC3021212-01R		Fabric Holster for Gun configuration	<ul style="list-style-type: none"> ►Includes modification with a softer belt loop and stronger button snap to avoid the button from snapping open when the MC3x00 is inserted into the holster. ►Devices with Rubber Boot (11-72959-04R) will fit into Holster. The fit will be tight though. ►Compatible with all MC3X series, including MC33. Not compatible with RFID devices though. ►MC33 RFID units must be inserted into cradle with bottom of device inserted first. ►Can be mounted on belt or includes tether points to be used with Universal Should Strap (58-40000-007R) 	
11-76201-01R		Fabric Holster for Gun configuration	<ul style="list-style-type: none"> ►Discontinued 4/16/08 - replaced by SG-MC3021212-01R ►Can be mounted on belt or includes tether points to be used with Universal Should Strap (58-40000-007R) 	
T5963DWSP (3rd party) * http://www.ultimacase.com		MC30/MC31/MC32 SoftTouch Case with D-swivel for Straight Shooter or Turret Head configuration 	<ul style="list-style-type: none"> ►Direct access to side triggers, and belt loop with low profile D-swivel for quick and secure attachment to waist belt. ►Raised edges for display protection against short drops. ►See-thru polyurethane protects keypad. ►Cutouts on sides for access to triggers. ►Elastic loop for keeping stylus ►Not compatible with MC33. 	


<p>O4925DWSPOS2 (3rd party) *</p> <p>http://www.ultimacase.com</p>		<p>Replacement Swivel Belt Clips for holsters</p> 		
<p>11-08062-02R</p>		<p>Belt for holster</p>	<ul style="list-style-type: none"> ▶Belt is 2 inches wide ▶Extends to 48 inches ▶Has improved buckle and softer belt material 	
<p>11-08062-01R</p>		<p>Belt for holster</p>	<ul style="list-style-type: none"> ▶Belt is 2 inches wide ▶Extends to 48 inches ▶Discontinued 9/2009, replaced by 11-08062-02R 	
<p>V6198DW (3rd party) *</p> <p>http://www.ultimacase.com</p>		<p>Belt Extender</p>	<ul style="list-style-type: none"> ▶Used to extend the holster belt (11-08062-02R) an additional 10 inches 	
<p>58-40000-007R</p>		<p>Universal Shoulder Strap</p>	<ul style="list-style-type: none"> ▶1.5" wide, 22 to 50" max. length 	
<p>A1236ST (3rd party) *</p> <p>https://www.shilpitradng.com</p>		<p>Universal Shoulder Strap</p>	<ul style="list-style-type: none"> ▶Belt is 1 inch wide ▶Extends to 54 inches ▶Moulded shoulder pad ▶Plastic swivel snap hooks 	
<p>SG-MC33-HDSTPG-01</p>		<p>Replacement MC33 Gun Handstrap</p>	<ul style="list-style-type: none"> ▶This is the same strap that ships with the MC33 Gun units. ▶Only compatible with MC33. 	





<p>SG-MC3123242-01R (single strap)</p>		<p>Replacement MC31/MC32 Gun Handstrap</p>	<ul style="list-style-type: none"> ▶This is the same strap that ships with the MC31/MC32 Gun units. ▶Includes UHF Gen2 tag for asset tracking. ▶Not compatible with MC33. 	
<p>SG-MC32-HDSTG-01 (pack of 3)</p>		<p>Replacement MC31/MC32/MC33 Gun Handstraps</p>	<ul style="list-style-type: none"> ▶This is an alternative lower cost hand strap for MC31/MC32/MC33 Gun units. ▶Lower profile strap does not include UHF RFID tag for asset tracking. 	
<p>SG-MC3123342-01R (pack of 5)</p>		<p>MC31/MC32/MC33 Gun Handstrap</p>	<ul style="list-style-type: none"> ▶This is an alternative strap for the MC31/MC32/MC33 Gun for customers that don't want a full handstrap that connects from the battery door or bottom of device to the gun handle. ▶D ring provides convenient pull point to remove battery cover on MC31 units. 	
<p>SG-MC33-HDSTPB-01</p>		<p>Replacement MC33 Brick or Turret Head Handstrap</p>	<ul style="list-style-type: none"> ▶This is the same strap that ships with the MC3 Brick (straight shooter) or Turret Head units. ▶Includes loop for storing optional stylus. ▶Only compatible with MC33. 	


<p>MC3123244-01R</p>		<p>Replacement MC31/MC32 Brick or Turret Head Handstrap</p>	<ul style="list-style-type: none"> ▶This is the same strap that ships with the MC31/MC32 Brick (straight shooter) or Turret Head units. ▶Includes UHF Gen2 RFID tag for asset tracking. ▶Includes loop for storing optional stylus ▶Not compatible with MC33. 	
<p>SG-MC3123243-01R</p>		<p>Replacement MC31/MC32 Brick or Turret Head Handstrap</p>	<ul style="list-style-type: none"> ▶Discontinued 4/2018, now use SG-MC3123244-01R - see PMB 3105 ▶This is the same strap that ships with the MC31/MC32 Brick (straight shooter) or Turret Head units. ▶Includes UHF Gen2 RFID tag for asset tracking. ▶Includes loop for storing optional stylus ▶Not compatible with MC33. 	

<p>SG-MC33-LNYDB-01</p>		<p>Lanyard for Brick/Straight-Shooter or Turret Head units</p>	<ul style="list-style-type: none"> ▶Allows MC32 or MC33 Brick/Straight-Shooter or Turret Head units to be attached to a retractable lanyard. ▶Lanyard can be worn cross-body using included strap or strap can be removed and lanyard can be attached to belt. ▶Standard handstrap must be removed to allow lanyard to be attached to MC3X unit. ▶When using as belt mounted lanyard, can be used with Belt for Holster (11-08062-02R) ▶NOT compatible with Gun configuration devices. 	
<p>SG-MC33-RBTS-01</p>		<p>Rubber Boot for MC33 Brick/Straight-Shooter units</p>	<ul style="list-style-type: none"> ▶Works with Imager configuration brick/straight-shooter units ▶Only compatible with MC33. ▶Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings. ▶Compatible with fabric holsters. ▶Not compatible with Forklift Holder ▶Boot must be removed before inserting into cradles. 	




11-70899-04R		Rubber Boot for MC30/MC31/MC32 Brick/Straight-Shooter units	<ul style="list-style-type: none"> ►Works with Imager configuration brick/straight-shooter units ►Not compatible with MC33. ►Compatible with fabric holsters. ►Not compatible with Forklift Holder ►Boot must be removed before inserting into cradles. 	
SG-MC33-RBTRD-01		Boot for MC33 Turret Head Scanner	<ul style="list-style-type: none"> ►Works with Turret Head Scanner configuration units. ►Includes Boot for unit. ►Only compatible with MC33. ►Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings. ►Compatible with fabric holsters. ►Not compatible with Forklift Holder ►Boot must be removed before inserting into cradles. 	Typically ordered with Cup for Turret Head Scanner (SG-MC33-RBTRT-01)
SG-MC33-RBTRT-01		Cup for MC33 Turret Head Scanner	<ul style="list-style-type: none"> ►Only compatible with MC33. ►Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings. 	Typically ordered with Boot for Turret Head Scanner (SG-MC33-RBTRD-01)
BOOTSCANTURRETR		Boot for MC30/MC31/MC32 Turret Head Scanner	<ul style="list-style-type: none"> ►Works with Turret Head Scanner configuration units. ►Includes Boot for unit and Boot for Turret Head scanner. ►Not compatible with MC33. ►Compatible with fabric holsters. ►Not compatible with Forklift Holder ►Boot must be removed before inserting into cradles. 	
11-72096-04R		Boot Cup for MC30/MC31/MC32 Turret Head Scanner	<ul style="list-style-type: none"> ►Includes only the turret head boot that is included with BOOTSCANTURRETR. ►Not compatible with MC33. 	
SG-MC33-RBTG-01		Rubber Boot for MC33 Gun	<ul style="list-style-type: none"> ►Works with both Laser and Imager gun units ►Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R). The fit will be tight though. ►Only compatible with MC33, except MC33 RFID units.. ►Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings. ►Compatible with fabric holsters. ►Not compatible with Forklift Holder ►Boot must be removed before inserting into cradles. 	

11-72959-04R		Rubber Boot for MC30/MC31/MC32 Gun	<ul style="list-style-type: none"> ►Works with both Laser and Imager gun units ►Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R). The fit will be tight though. ►Not compatible with MC33. ►Compatible with fabric holsters. ►Not compatible with Forklift Holder ►Boot must be removed before inserting into cradles. 	
SG-MC33-RBTG-02		Rubber Boot for MC33 RFID unit	<ul style="list-style-type: none"> ►Only compatible with MC33 RFID units. ►Includes holder for optional stylus (SG-TC7X-STYLUS-03), which is not included, and tether point for stylus tether. ►Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings. ►Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R) - bottom of MC33 RFID device will insert into holster. The fit will be tight though. ►Not compatible with Forklift Holder ►Boot must be removed before inserting into cradles. 	
SG-MC33-RBTG-03		Half Rubber Boot for MC33 RFID unit	<ul style="list-style-type: none"> ►Only compatible with MC33 RFID units. ►Includes holder for optional stylus (SG-TC7X-STYLUS-03), which is not included, and tether point for stylus tether. ►Does not increase drop spec of device. Designed to protect the device from the everyday nicks and dings. ►Devices with Boot will also fit into Fabric Gun Holster (SG-MC3021212-01R) - bottom of MC33 RFID device will insert into holster. The fit will be tight though. ►Not compatible with Forklift Holder ►Boot covers top half of device allowing easy insertion into cradles. 	
T5977DW (3rd party) * http://www.ultimacase.com		Heated case for MC30/MC31/MC32 Brick	<ul style="list-style-type: none"> ►For use in environments that are colder than the MC30xx's operating specs. ►Ballistic nylon OP Case is designed with Thinsulate padding for minimizing heat loss ►Two pockets are sewn inside the case for storing Heat Packs that keep the unit warm ►Heat Packs have temperature range of 104F to 156F (40C to 69C) and last up to 7 hours ►Top flap with snaps allows quick and easy insertion or removal of the unit ►Elastic hand strap is sewn on back for holding the unit in palm during use ►2 D-rings allow attachment to an optional shoulder strap 	Requires heat packs which are also available on web site.
(3rd party) * http://www.ultimacase.com	Agora Leather website	Additional holsters for MC3000 series		

0000-0543 (3rd party) * http://www.multiplexx.com/		Hip holster with belt for MC3X Brick/Straight-Shooter units	<ul style="list-style-type: none"> ▶Left-hand/right-hand interchangeable ▶The holster and belt provide protection and hands free mobility to sensitive equipment 	
0000-0540 (3rd party) * http://www.multiplexx.com/		MC30/MC31/MC32 Turret Head Configuration Holster, display exposed with shoulder strap	<ul style="list-style-type: none"> ▶Display exposed for touch screen ease. ▶Includes shoulder strap. ▶Not compatible with MC33. 	
(3rd party) * http://logisterra.com/products/symbol/symbol.html	Logisterra website	Additional Holsters for MC3000 series		
Vehicle/Forklift Cradles and Holders				
Powered Cradles and Holders (provides device charging and/or communication)				
Part Number	Picture	Description	Notes	Required Items
various (3rd party) * http://www.proclipusa.com/category/zebra		Vehicle Cradles for MC30/MC31/MC32	<ul style="list-style-type: none"> ▶Holds MC30/MC31/MC32 Gun or Brick units. ▶Front Facing - allows user to access screen and keyboard while cradled. ▶Variable Mount - can be tilted and swiveled. ▶Available in un-powered, cigarette lighter adapter powered, or hard-wired powered configurations. ▶Mount ready via AMPS hole pattern ▶Not compatible with MC33 units 	Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website
MDMC3000 Available from MD Mobildata (3rd party) * http://www.mdmobidata.de		Vehicle/Fork Truck Cradle for MC30/MC31/MC32 Brick or Gun	<ul style="list-style-type: none"> ▶Provides USB, RS232, and Power connectors ▶USB and RS232 Connector on the backside enables connection of external GPRS or GPS Modules as well as a CANBus Connection for engine control. ▶USB-Connector offers a USB-Client or USB-Host Connection ▶Not compatible with MC33. 	

<p>0000-0481 (3rd party) * http://www.multiplex.com/</p>		<p>MC30/MC31/MC32 vehicle cradle</p>	<ul style="list-style-type: none"> ▶Cradle has USB and RS232 ports ▶The connection can be either an RS232 serial or a USB (client) connection. ▶Communication and charging cradle in cars, vans and fork lift trucks and can also be desk or wall mounted. ▶Serial port not compatible with Android versions of MC32. ▶Not compatible with MC33. 	
---	---	--------------------------------------	---	--

Un-Powered Cradles and Holders (passive holders, no charging support)




Part Number	Picture	Description	Notes	Required Items
MNT-MC33-FLCHKT-01		<p>Fork Lift Cradle Kit (un-powered)</p>	<ul style="list-style-type: none"> ▶Bracket holds all MC3X00 configurations, except RFID units, for convenient mounting on fork lift. ▶Installs on a roll bar or square surface of the forklift and allows the device to be used in landscape or portrait mode. ▶Includes RAM 1" diameter ball on back of cradle. ▶Does NOT charge MC3X00. ▶Kit includes Fork Lift Cradle (MNT-MC33-FLCH-01), RAM Mount Arm (MNT-RAM-B201U), and RAM Mount Base (MNT-RAM-B247U25) 	
MNT-MC33-FLCH-01		<p>Fork Lift Cradle (un-powered)</p>	<ul style="list-style-type: none"> ▶Bracket holds all MC3X00 configurations, except RFID units, for convenient mounting on fork lift. ▶Installs on a roll bar or square surface of the forklift and allows the device to be used in landscape or portrait mode. ▶Includes RAM 1" diameter ball on back of cradle. ▶Does NOT charge MC3X00. ▶Not compatible with devices with rubber boot attached. 	<ul style="list-style-type: none"> ▶RAM Mount Arm for Fork Lift Cradle (MNT-RAM-B201U) ▶RAM Mount Base for Fork Lift Cradle (MNT-RAM-B247U25)
MNT-RAM-B201 U		<p>RAM Mount Arm for MC3X00 Fork Lift Cradle</p>	<ul style="list-style-type: none"> ▶Used with Fork Lift Cradle (MNT-MC33-FLCH-01) ▶RAM Double Sock Arm for 1" ball ▶Uses RAM Mount P/N RAM-B-201U 	










MNT-RAM-B247U25		RAM Mount Base for MC3X00 Fork Lift Cradle	<ul style="list-style-type: none"> ▶Used with Fork Lift Cradle (MNT-MC33-FLCH-01) ▶Attaches to square shaped rail/post of forklift. ▶2.5" Max Width Square Rail Base with 1" diameter ball ▶Uses RAM Mount P/N RAM-B-247U-25 	
241468 (3rd party) *		MC33 Holder, Rear Facing Display, Top Hold, No Tilt or Swivel (un-powered)	<ul style="list-style-type: none"> ▶Holds MC33 Gun, Brick, or Turret Head devices ▶Rear Facing - Device screen faces away from user to prevent device usage while driving ▶Fixed Mount - does not tilt or swivel ▶Mount ready via AMPS hole pattern ▶Only compatible with MC33 series, except MC33 RFID units. 	Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website
711056 (3rd party) *		MC33 Holder, Rear Facing Display, Top Hold, with Tilt Swivel (un-powered)	<ul style="list-style-type: none"> ▶Holds MC33 Gun configurations only ▶Rear Facing - Device screen faces away from user to prevent device usage while driving ▶Variable Mount - can be tilted and swiveled and mounted vertically or horizontally. ▶Mount ready via AMPS hole pattern ▶Only compatible with MC33 GUN units, except MC33 RFID units. 	Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website
241467 (3rd party) *		MC33 Holder, Front Facing Display, Top Hold, No Tilt or Swivel (un-powered)	<ul style="list-style-type: none"> ▶Holds MC33 Gun, Brick, or Turret Head devices ▶Front Facing - allows user to access screen and keyboard while cradled. ▶Fixed Mount - does not tilt or swivel ▶Mount ready via AMPS hole pattern ▶Only compatible with MC33 units,, except MC33 RFID units. 	Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website




<p>711040 (3rd party) *</p> <p>http://www.proclipusa.com/category/zebra</p>		<p>MC33 Holder, Front Facing Display, Top Hold, with Tilt Swivel (un-powered)</p>	<ul style="list-style-type: none"> ▶Holds MC33 Gun, Brick, or Turret Head devices ▶Front Facing - allows user to access screen and keyboard while cradled. ▶Variable Mount - can be tilted and swiveled. ▶Mount ready via AMPS hole pattern ▶Only compatible with MC33 units, except MC33 RFID units. 	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>
<p>various (3rd party) *</p> <p>http://www.proclipusa.com/category/zebra</p>		<p>Vehicle Cradles for MC30/MC31/MC32</p>	<ul style="list-style-type: none"> ▶Holds MC30/MC31/MC32 Gun or Brick units. ▶Front Facing - allows user to access screen and keyboard while cradled. ▶Variable Mount - can be tilted and swiveled. ▶Available in un-powered, cigarette lighter adapter powered, or hard-wired powered configurations. ▶Mount ready via AMPS hole pattern ▶Not compatible with MC33 units 	<p>Mount on vehicle using ProClip Pedestal or Forklift Mount - see ProClip website</p>
<p>7160-0854 (3rd party) *</p> <p>https://www.gamberjohnson.com</p>		<p>Gamber-Johnson Barcode Scanner/Mobile Computer Mount</p>	<ul style="list-style-type: none"> ▶Attaches to the overhead guard leg on forklift trucks. It is designed to fit rectangular pillars between 1.5" to 2.5" wide with easy installation ▶Heavy gauge steel construction for long-term durability in a rugged environment. ▶Black powdercoat finish for maximum corrosion resistance. ▶Designed to securely fit most handheld barcode scanners and mobile computers. ▶Works with wireless and wired devices. 	




7160-1306 (3rd party) *		Gamber-Johnson Scanner Pocket Mount with Small Back Plate	<ul style="list-style-type: none"> Scanner mount is designed to support scanner or handheld computer in a rugged environment by holding it securely to the overhead guard leg of fork lift vehicle. Adjustable in width, and offers 3 mounting orientations from the overhead guard leg or one of Gamber-Johnson's extension bars. Designed to hold most handheld computers and scanners. Adjustable to fit 3.5" to 4.5" width and set at 2.5" tall Designed to be orientated inside, outside, or inline with the overhead guard leg. Attaches to rectangular overhead guard legs that are 1.5 in to 2.5 in (3.81 cm to 6.35 cm) wide. 	
https://www.gamberjohnson.com				
AA1036DW (3rd party) *		MC3XXX-G (Gun) Forklift Holster	 <ul style="list-style-type: none"> Includes cable ties for mounting holster to forklift Does not provide device charging 	
http://www.ultimacase.com				






Misc





Part Number	Picture	Description	Notes	Required Items
SG-TC7X-STYLUS-03 (pack of 3)		MC33 Stylus Kit with Tether	<ul style="list-style-type: none"> Only compatible with MC33 Includes fine-pitch, capacitive Stylus (SG-TC7X-STYLUS1-03) and coiled tether (KT-TC7X-TETHR1-03) Conductive Carbon-filled plastic material w/ 5mm tip. Length of stylus is 3.5". Rigid plastic stylus is optimized for enterprise durability. Clip & tether point to reduce loss. Tether to Handstrap When not being used stylus can be stored in loop on Handstrap or in the optional Holster 	
SG-TC7X-STYEX1-3 (pack of 3)		MC33 Extended Length Stylus	<ul style="list-style-type: none"> Discontinued 2/2019 - see PMB 10057 Only compatible with MC33 Conductive Carbon-filled plastic material w/ 5mm tip Rigid plastic stylus is optimized for enterprise durability. Clip & tether point to reduce loss. When not being used stylus can be stored in optional Holster Use with optional Tether (SG-ET5X-SLTETR-01) 	
KT-MC9X3X-STLSG-05 (pack of 5) KT-MC9X3X-STLSG-10 (pack of 10) KT-MC9X3X-STLSG-50 (pack of 50)		Spare Stylus for MC30/MC31/MC32 Gun	<ul style="list-style-type: none"> This is the standard stylus that ships with the unit Not compatible with MC33. 	

<p>KT-68144-10R (pack of 10) KT-68144-50R (pack of 50)</p>		<p>Spare Stylus for MC30/MC31/MC32 Gun</p>	<ul style="list-style-type: none"> ►Discontinued 12/2017, now use KT-MC9X3X-STLSG-10 or MC9X3X-STLSG-50 - PMB 3057 ►This is the standard stylus that ships with the unit ►Not compatible with MC33. 	
<p>KT-81680-03R (pack of 3) KT-81680-50R (pack of 50)</p>		<p>Tethered Stylus for MC30/MC31/MC32 Gun</p>	<ul style="list-style-type: none"> ►Discontinued 12/2017, now use KT-MC9X3X-STLSG-05 or MC9X3X-STLSG-50 - PMB 3057 ►Includes KT-68144-xx stylus and KT-73440-xx Tethers ►Not compatible with MC33. 	
<p>11-43912-03R (pack of 3) 11-43912-50R (pack of 50)</p>		<p>Spare Tethered Stylus for MC30/MC31/MC32 Brick</p>	<p>This is the standard stylus that ships with the unit. Includes 11-42794-XX Stylus and 11-42722-XX Tethers</p> <ul style="list-style-type: none"> ►Not compatible with MC33. 	
<p>11-42794-03R (pack of 3) 11-42794-50R (pack of 50) - Discontinued 12/2013</p>		<p>Tetherable Stylus for MC30/MC31/MC32 Brick</p>	<ul style="list-style-type: none"> ►Not compatible with MC33. 	
<p>KT-TC7X-TETHR1-03 (pack of 3)</p>		<p>Replacement Coiled Tether for Stylus</p>	<ul style="list-style-type: none"> ►This tether is included with Stylus Kit with Tether (SG-TC7X-STYLUS-03) 	
<p>SG-ET5X-SLTETR-01 (single)</p>		<p>Replacement Coiled Tether for Stylus</p>	<ul style="list-style-type: none"> ►This tether is typically used with the ET5X series' stylus but can be used with MC33 Stylus. 	
<p>KT-73440-01R</p>		<p>Non-Elastic Tethers (pack of 3)</p>	<ul style="list-style-type: none"> ►Typically used with MC30/MC31/MC32 Stylus 	
<p>11-42722-03R (pack of 3) 11-42722-50R (pack of 50)</p>		<p>Elastic Tethers</p>	<ul style="list-style-type: none"> ►Typically used with MC30/MC31/MC32 Stylus 	
<p>KT-97258-01R</p>		<p>MC30xx Replacement Handstrap Buttons (pack of 250)</p>	<ul style="list-style-type: none"> ►Discontinued 12/2015 - PMB 2723 	




11-128366-01R		MC31xx/MC32xx Brick Audio Jack Cover	<ul style="list-style-type: none"> Discontinued 11/2011 pack of 5 covers 	
MISC-MC33-SCRN-01 (pack of 5)		MC33 Tempered Glass Screen Protector (pack of 5)	<ul style="list-style-type: none"> Tempered glass Includes alcohol wipes, cleaning cloth, and tools needed for screen protector installation. 	
KT-144829-03R		MC30/MC31/MC32 Screen Protector (pack of 3)	<ul style="list-style-type: none"> Discontinued 1/2014 For use with applications with high touch screen usage, Symbol recommends the use of a screen protector to minimize wear and tear. Screen protectors enhance the usability and durability of touch screen displays. Benefits include: <ul style="list-style-type: none"> Protection from scratches and gouges Durable writing and touch surface with tactile feel Abrasion and chemical resistance Glare reduction Keeping the device's screen looking like new 	
KT-82057-03R		MC30/MC31/MC32 Screen Protector (pack of 3)	<ul style="list-style-type: none"> Discontinued 12/2013, now use KT-144829-03R For use with applications with high touch screen usage, Symbol recommends the use of a screen protector to minimize wear and tear. Screen protectors enhance the usability and durability of touch screen displays. Benefits include: <ul style="list-style-type: none"> Protection from scratches and gouges Durable writing and touch surface with tactile feel Abrasion and chemical resistance Glare reduction Keeping the device's screen looking like new 	
Additional Screen Protectors (3rd party) * http://www.nushield.com		Additional Screen Protectors	<ul style="list-style-type: none"> NuShield AG™ - works well indoors under bright lights to minimize glare. NuShield AM™ - antimicrobial film is an antiglare film designed for hospitals, public kiosks, restaurants and POS terminals where transmission of disease is a primary concern. NuShield DayVue™ - antireflective film is the best choice for displays that are being used outdoors. 	
Headset/Audio Accessories				
Part Number	Picture	Description	Notes	Required Items







<p>HS2100-OTH</p>		<p>HS2100 Rugged Wired Headset (Over the Head headband)</p>	<ul style="list-style-type: none"> ▶Built to handle the everyday inevitable drops ▶Dustproof, sprayproof and waterproof ▶Ready for the freezer and outdoor subzero temperatures ▶Feather-light for extraordinary comfort ▶Noise cancellation for a superior voice experience in the noisiest environments ▶Detachable swivel boom minimizes costs. ▶Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations. ▶User-replaceable pads and windscreens maximize comfort and hygiene. ▶Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p><u>For MC31/MC32/MC33:</u> Quick Disconnect Headset cable (CBL-HS2100-QDC1-02) AND MC31/MC32 to Quick Disconnect Adapter Cable (25-124411-02R)</p> <p><u>For MC3000:</u> Quick Disconnect Headset cable (CBL-HS2100-QDC1-01) AND MC3000 to Quick Disconnect Adapter Cable (25-124387-02R)</p>
<p>HS2100-BTN-L</p>		<p>HS2100 Rugged Wired Headset (Behind the Neck Left headband)</p>	<ul style="list-style-type: none"> ▶Built to handle the everyday inevitable drops ▶Dustproof, sprayproof and waterproof ▶Ready for the freezer and outdoor subzero temperatures ▶Feather-light for extraordinary comfort ▶Noise cancellation for a superior voice experience in the noisiest environments ▶Detachable swivel boom minimizes costs. ▶Swivelling boom mutes microphone allowing uses to prevent voice pick applications from recognizing non-voice pick conversations. ▶User-replaceable pads and windscreens maximize comfort and hygiene. ▶Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p><u>For MC31/MC32/MC33:</u> Quick Disconnect Headset cable (CBL-HS2100-QDC1-01) AND MC31/MC32 to Quick Disconnect Adapter Cable (25-124411-02R)</p> <p><u>For MC3000:</u> Quick Disconnect Headset cable (CBL-HS2100-QDC1-02) AND MC3000 to Quick Disconnect Adapter Cable (25-124387-02R)</p>
<p>VR12 (3rd party) *</p> <p>http://www.blueparrott.com</p>		<p>BlueParrott VR12 Wired Noise Cancelling Headset</p>	<ul style="list-style-type: none"> ▶Audio accuracy for voice picking and other speech recognition applications. ▶High quality durability stands up to all-day, every-day use. ▶Lightweight design is easy and comfortable to wear all day. ▶Compatible with most major wearable computers and devices used in voice-picking environments. ▶G type (GN Netcom) Quick Disconnect. ▶Convertible design gives choice of over-the-head and behind-the-neck wearing styles. ▶Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p>For MC30XX series: Headset Adapter Cable (25-124387-02R)</p> <p>For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-02R)</p>

RCH51		RCH51 Rugged Cabled Headset	<ul style="list-style-type: none"> Discontinued 12/2018, now use HS2100 series - PMB 2981 Improved to withstand chemicals in certain hair gels Noise cancelling microphone filters ambient noise inches away Extremely rugged strain relief features ensure cable bend tolerance, even at -30C IP67 sealing throughout the headset protects sensitive components from moisture and dust High-strength plastics survive 6' drop at -30C & 500 tumbles Weight: 4 oz. See RCH50/RCH51 Accessories Document for additional accessories. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p>For MC30XX series: Headset Adapter Cable (25-124387-02R)</p> <p>For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-02R)</p>
RCH50		RCH50 Rugged Cabled Headset	<ul style="list-style-type: none"> Discontinued 10/2011, now use RCH51 Noise cancelling microphone filters ambient noise inches away Extremely rugged strain relief features ensure cable bend tolerance, even at -30C IP67 sealing throughout the headset protects sensitive components from moisture and dust High-strength plastics survive 6' drop at -30C & 500 tumbles Weight: 4 oz. See RCH50 Accessories Document for additional accessories. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p>For MC30XX series: Headset Adapter Cable (25-124387-01R)</p> <p>For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-01R)</p>
50-11300-050R		Noise Cancelling Headset	<ul style="list-style-type: none"> Discontinued 8/2011, now use RCH50 Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p>For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-01R)</p>
3PTY-VXI-VR12 (Zebra orderable SKU) http://www.vxicorp.com		BlueParrot VR12 Wired Noise Cancelling Headset 	<ul style="list-style-type: none"> Discontinued 10/2018, now use HS2100 series - PMB 10005 Audio accuracy for voice picking and other speech recognition applications. High quality durability stands up to all-day, every-day use. Lightweight design is easy and comfortable to wear all day. Compatible with most major wearable computers and devices used in voice-picking environments. G type (GN Netcom) Quick Disconnect. Convertible design gives choice of over-the-head and behind-the-neck wearing styles. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	<p>For MC30XX series: Headset Adapter Cable (25-124387-02R)</p> <p>For MC31/MC32/MC33 series: Headset Adapter Cable (25-124411-02R)</p>

<p>See HS2100-HS3100 Accessories Document</p>		<p>HS3100 Rugged Bluetooth Headset</p>	<ul style="list-style-type: none"> ▶HD Voice, also known as Wide Band Audio, brings incredible audio clarity ▶Built to handle the everyday inevitable drops ▶Dustproof, sprayproof and waterproof ▶Ready for the freezer and outdoor subzero temperatures ▶Feather-light for extraordinary comfort ▶Noise cancellation for a superior voice experience in the noisiest environments ▶Swap batteries on the fly — without losing the Bluetooth connection ▶Split-second tap-to-pair simplicity using NFC. ▶Detachable swivel boom minimizes costs. ▶Swivelling boom mutes microphone allowing users to prevent voice pick applications from recognizing non-voice pick conversations. ▶User-replaceable pads and windscreens maximize comfort and hygiene ▶15 hours of battery power ▶Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units. 	<p>See HS2100/HS3100 Accessories Document for headset accessories</p>
<p>various Bluetooth models B550-XT B350-XT C400-XT C300-XT (3rd party) * http://www.blueparrott.com</p>		<p>BlueParrott Bluetooth Headsets</p>	<ul style="list-style-type: none"> ▶Various Bluetooth models available with options that include: <ul style="list-style-type: none"> - Blocking out 96% of background noise - Over 24 hours of talk time - NFC Tap to Pair capable - Bluetooth wireless range capable up to 300 ft. - Convertible wearing options: over the head, behind the neck. <p>See BlueParrot site for model specific options.</p>	
<p>3PTY-VXI-B350XT (Zebra orderable SKU) http://www.vxicorp.com</p>		<p>BlueParrott Bluetooth Headset for voice directed applications</p> 	<ul style="list-style-type: none"> ▶Discontinued 10/2018, now use HS3100 series - PMB 10005 ▶Used to enable Voice Directed Picking (VDP) or Speech Applications in warehouse environments when the use of a wireless headset is desired ▶Not intended to support peer-to-peer communications (PTT) or VoIP calls. ▶Provides 24 hours talk time. ▶Works with StoneStreet Bluetooth stack. Will not function with Microsoft BT stack or voice applications that depend on the Microsoft BT stack. ▶Allows the use of other BT devices (i.e. RS507 scanner or mobile printer) ▶Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units. ▶Zebra Compatible certification for VDP application use with MC32. 	<p>▶MC32 CE7 devices may require Bluetooth Wideband Speech CAB file from support site to enable StoneStreet BT stack wideband (16 KHz) audio support.</p>





<p>3PTY-VXI-B250XTP (Zebra orderable SKU)</p> <p>http://www.vxicorp.com</p>		<p>BlueParrott Bluetooth Headset for voice directed applications</p> 	<ul style="list-style-type: none"> Discontinued 10/2018, now use HS3100 series - PMB 10005 Used to enable Voice Directed Picking (VDP) or Speech Applications in warehouse environments when the use of a wireless headset is desired Not intended to support peer-to-peer communications (PTT) or VoIP calls. Provides 20 hours talk time. Works with StoneStreet Bluetooth stack. Will not function with Microsoft BT stack or voice applications that depend on the Microsoft BT stack. Allows the use of other BT devices (i.e. RS507 scanner or mobile printer) Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units. 	<ul style="list-style-type: none"> MC32 CE7 devices may require Bluetooth Wideband Speech CAB file from support site to enable StoneStreet BT stack wideband (16 KHz) audio support.
<p>3PTY-VXI-EXPWAYII (Zebra orderable SKU)</p> <p>http://www.vxicorp.com</p>		<p>BlueParrott Bluetooth Headset for voice directed applications</p> 	<ul style="list-style-type: none"> Discontinued 10/2018, now use HS3100 series - PMB 10005 Used to enable Voice Directed Picking (VDP) or Speech Applications in warehouse environments when the use of a wireless headset is desired Not intended to support peer-to-peer communications (PTT) or VoIP calls. Provides 8 hours talk time. Works with StoneStreet Bluetooth stack. Will not function with Microsoft BT stack or voice applications that depend on the Microsoft BT stack. Allows the use of other BT devices (i.e. RS507 scanner or mobile printer) Compatible with MC33 or MC32 WEC7 units only. Not compatible with MC32 Android Jellybean units. Zebra Compatible certification for VDP application use with MC92, VC70, WT41 and MC32. 	<ul style="list-style-type: none"> MC32 CE7 devices may require Bluetooth Wideband Speech CAB file from support site to enable StoneStreet BT stack wideband (16 KHz) audio support.
<p>APTT1 (3rd party) *</p> <p>https://www.aina-wireless.com/</p>		<p>Aina Push-To-Talk (PTT) Bluetooth Voice Responder Remote Speaker/Mic (RSM)</p>	<ul style="list-style-type: none"> Bluetooth speaker-microphone designed to work with different walkie talkie style Push-to-Talk applications, including Zebra PTT Pro (check with Zebra PTT Pro engineering team for current device/OS support). Includes clip for attaching device to clothing for lapel speaker/mic usage. Features several buttons which the application developers can assign to different functions. Users can remotely control functions such as push-to-talk, phone calls, channel switching and emergency alerts. Device is ruggedized, MIL-STD 810G and IP67. Long lasting battery designed for 24 hour approx battery life. Can be recharged via micro-USB port. Includes 3.5mm headset jack allowing headphones to be connected for keeping conversations more private. Can be easily paired to mobile computer using NFC tap-to-pair. 	









<p>H3-B-1 (3rd party) *</p> <p>https://www.dellking.com</p>		<p>Wandfu H3 Push-To-Talk (PTT) Bluetooth Remote Speaker/Mic (RSM)</p>	<ul style="list-style-type: none"> ▶Bluetooth speaker-microphone designed to work with different walkie talkie style Push-to-Talk applications, including Zebra PTT Pro (check with Zebra PTT Pro engineering team for current device/OS support). ▶Includes clip for attaching device to clothing for lapel speaker/mic usage. ▶Includes 3.5mm headset jack allowing headphones to be connected for keeping conversations more private. 	
<p>BTR-155 (3rd party) *</p> <p>K551011 (Zebra orderable SKU) ▶Discontinued 3/2019, now order from Savox</p> <p>https://www.savoxaccessories.com</p>		<p>Savox BTR-155 Bluetooth Remote Speaker/Mic (RSM)</p>	<ul style="list-style-type: none"> ▶Bluetooth speaker-microphone designed to work with different walkie talkie style Push-to-Talk applications, including Zebra PTT Pro (check with Zebra PTT Pro engineering team for current device/OS support). ▶Includes clip for attaching device to clothing for lapel speaker/mic usage. ▶Rugged wireless speaker microphone, IP55. ▶Allows cable-free movement ▶Familiar speaker microphone functions; PTT and volume buttons ▶Includes 2.5mm headset jack allowing headphones to be connected for keeping conversations more private. ▶LED status indication ▶High speaker volume ▶Includes: <ul style="list-style-type: none"> - Savox RSM - Modular Wired earpiece - Wall Charger - USB Cable - Quick Start Guide - Carrying Strap 	
<p>BTH-101 (3rd party) *</p> <p>https://www.savoxaccessories.com</p>		<p>Savox Push-To-Talk (PTT) Bluetooth Headset</p>	<ul style="list-style-type: none"> ▶Bluetooth headset designed to work with different walkie talkie style Push-to-Talk applications, including Zebra PTT Pro (check with Zebra PTT Pro engineering team for current device/OS support). ▶Also operates as standard Bluetooth headset for taking phone calls. ▶Device is lightweight and ruggedized, IP55. 	












CBL-HS2100-QDC1-02		HS2100 Quick Disconnect Cable	<ul style="list-style-type: none"> For use when connecting HS2100 to devices using standard Quick Disconnect jack. Cable length is approximately 33" (84 cm). Has improved quick disconnect connector and strain relief vs. CBL-HS2100-QDC1-01. 	
CBL-HS2100-QDC1-01		HS2100 Quick Disconnect Cable	<ul style="list-style-type: none"> Discontinued 5/2019, now use CBL-HS2100-QDC1-02 For use when connecting HS2100 to devices using standard Quick Disconnect jack. 	
25-124386-01R		MC31/MC32/MC33 Headset Adapter Cable, RCH50/BlueParrot connector	<ul style="list-style-type: none"> Discontinued 5/2012 Cable has right angle connector and locking screw into the MC31/32/33's audio jack. Connects RCH50, BlueParrot, Voxware, and Eartec headsets. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	
25-124389-01R		MC31/MC32/MC33 Headset Adapter Cable, bare wire	<ul style="list-style-type: none"> Cable has right angle connector and locking screw into the MC31/32/33's audio jack. Bare wire end connector allows other manufacturers to build their own proprietary connectors on the opposite end for connections to other headsets. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	
25-124411-03R		MC31/MC32/MC33 Headset Adapter Cable, HS2100 / RCH50/ BlueParrot connector	<ul style="list-style-type: none"> Cable has right angle connector and locking screw into the MC31/32/33's audio jack. Connects HS2100, RCH50, BlueParrot, Voxware, and Eartec headsets Updated cable minimizes cross talk and intermittency issues. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	
25-124411-02R		MC31/MC32/MC33 Headset Adapter Cable, HS2100 / RCH50/ BlueParrot connector	<ul style="list-style-type: none"> Discontinued 4/2018, now use 25-124411-03R - see PMB 3105 Cable has right angle connector and locking screw into MC31XX audio jack. Connects HS2100, RCH50, BlueParrot, Voxware, and Eartec headsets Updated cable minimizes cross talk and intermittency issues. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	
25-124411-01R		MC31/MC32/MC33 Headset Adapter Cable, HS2100 / RCH50/ BlueParrot connector	<ul style="list-style-type: none"> Discontinued 9/2013, now use 25-124411-02R Cable has right angle connector and locking screw into MC31XX audio jack. Connects HS2100, RCH50, BlueParrot, Voxware, and Eartec headsets. Not compatible with MC31/MC3300 RFID units or MC3300X units which do not have a headset jack. 	





25-124387-02R		MC30 HS2100/ RCH50/ RCH51 Headset Adapter Cable	<ul style="list-style-type: none"> Connects HS2100/RCH50/RCH51 headset to devices with standard 3-pole 2.5mm barrel jack connector. Updated cable minimizes cross talk and intermittency issues. 	
25-124387-01R		MC30 HS2100/ RCH50/ RCH51 Headset Adapter Cable	<ul style="list-style-type: none"> Discontinued 9/2013, now use 25-124387-02R Connects HS2100/RCH50/RCH51 headset to devices with standard 3-pole 2.5mm barrel jack connector. 	
11-128366-01R		MC31xx/MC32xx Brick Audio Jack Cover	<ul style="list-style-type: none"> Discontinued 11/2011 pack of 5 covers 	
11-128366-02R		MC31xx/MC32xx Turret Head unit Audio Jack Cover	<ul style="list-style-type: none"> Discontinued 11/2011 pack of 5 covers 	
11-128366-03R		MC31xx/MC32xx Gun Audio Jack Cover	<ul style="list-style-type: none"> Discontinued 11/2011 pack of 5 covers 	

Power Cords/Power Supplies



Part Number	Picture	Description	Notes	Required Items
CBL-DC-388A1-01		DC Power Cord	<ul style="list-style-type: none"> Used along with Power Supply PWR-BGA12V50W0WW to power Single Slot Cradle and SACX000 4-Slot Battery Charger. Cable length is 1.8 meters 	
PWR-BGA12V50W0WW		Power Supply	<ul style="list-style-type: none"> Used to power Single Slot Cradles, MC32/MC33 4-Slot Battery Charger, and SACX000 4-Slot Battery Charger. 100-240 VAC, 12V, 4.16A, 50W Provides US DOE Level VI compliance for power efficiency. Replaces PWRS-14000-148R 	DC Line Cord (CBL-DC-388A1-01) and AC Line Cord (23844-00-00R)
KIT-PWR-12V50W		Power Supply Kit	<ul style="list-style-type: none"> Includes Power Supply (PWR-BGA12V50W0WW) and DC Line Cord (CBL-DC-388A1-01) 	AC Line Cord (23844-00-00R)
PWRS-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Discontinued 1/2017, now use PWR-BGA12V50W0WW and CBL-DC-388A1-01 - see PMB 2923 and PMB 2851. Replaces KT-14000-148R Used to power Single Slot Cradles, MC32/MC33 4-Slot Battery Charger, and SACX000 4-Slot Battery Charger. 100-240 VAC, 12VDC, 3.33A Energy Star Compliant 	23844-00-00R



50-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Discontinued 12/2007 - replaced by KT-14000-148R Used to power Single Slot Cradles, MC32/MC33 4-Slot Battery Charger, and SACX000 4-Slot Battery Charger. 	23844-00-00R
KT-14000-148R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Replaces 50-14000-148R Used to power Single Slot Cradles, MC32/MC33 4-Slot Battery Charger, and SACX000 4-Slot Battery Charger. Discontinued 12/2010 - now use PWRS-14000-148R 	23844-00-00R
CBL-DC-383A1-01		DC Line Cord	<ul style="list-style-type: none"> Used to power Snap-On USB/Charge Cable with Power Supply PWR-BUA5V16W0WW Cable length is 6 ft. 	
PWR-BUA5V16W0WW		Power Supply	<ul style="list-style-type: none"> Used with Communication/Charge Cable Cups 100-240VAC, 5.4V, 3A, 16W Meets US DOE Level VI efficiency standard Replaces PWRS-14000-249R 	DC Line Cord (CBL-DC-383A1-01) and AC Line Cord (50-16000-182R)
PWRS-14000-249R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Discontinued 10/2016 in NALA and 1/2017 in EMEA/APAC - replaced by PWR-BUA5V16W0WW and CBL-DC-383A1-01 - PMB 2887. Replaces 50-14000-249R Used with Communication/Charge Cable Cups 100-240VAC, 5.4 VDC, 3A Energy Star Compliant 	50-16000-182R
50-14000-147R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Discontinued 12/2007 - replaced by 50-14000-249R Used with Communication/Charge Cable Cups 	50-16000-182R
50-14000-249R		Power Supply with integrated DC Cord	<ul style="list-style-type: none"> Replaces 50-14000-147R Used with Communication/Charge Cable Cups Discontinued 12/2010 - now use PWRS-14000-249R 	50-16000-182R
CBL-DC-381A1-01		DC Power Cord	<ul style="list-style-type: none"> Used with Power Supply PWR-BGA12V108W0WW to power MC33 5-Slot Multi-Slot ShareCradles and MC32/MC33 20-Slot Spare Battery Charger. This cable does not include the black extension release latch which is not required when used on Multi-Slot ShareCradles. 	

CBL-DC-382A1-01		DC Power Cord	<ul style="list-style-type: none"> ►Used with Power Supply PWR-BGA12V108W0WW to power 4-Slot MC30/MC31/MC32 Legacy Cradles. 	
50-16002-029R		DC Power Cord	<ul style="list-style-type: none"> ►Used with Power Supply PWRS-14000-241R to power 4-Slot MC30/MC31/MC32 Legacy Cradles. ►Discontinued 2/2017, now use CBL-DC-382A1-01 - PMB 2851 and 2933 	
50-16002-042R		DC Power Cord	<ul style="list-style-type: none"> ►Used with Power Supply PWRS-14000-241R to power 4-Slot MC30/MC31/MC32 Legacy Cradles. ►Recommend using 50-16002-029R instead. ►Discontinued 2/2017, now use CBL-DC-382A1-01 - PMB 2851 and 2933 	
CBL-DC-523A1-01		2-Way DC Y Power Cord	<ul style="list-style-type: none"> ►Used to power two 4-Slot Battery Chargers with one Power Supply (PWR-BGA12V108W0WW) 	
25-85993-01R		2-Way DC Y Power Cord	<ul style="list-style-type: none"> ►Used to power two 4-Slot Battery Chargers with one Power Supply (PWRS-14000-241R) ►Discontinued 2/2017, now use CBL-DC-523A1-01 - PMB 2851 and 2933 	
PWR-BGA12V108W0WW		Power Supply	<ul style="list-style-type: none"> ►Used to power 4-Slot Cradles, 5-Slot Cradles, and 20-Slot MC33 Spare Battery Charger. ►100-240 VAC, 12V, 9A, 108W ►Provides US DOE Level VI compliance for power efficiency. ►Replaces PWRS-14000-241R 	CBL-DC-381A1-01 and 23844-00-00R
PWRS-14000-241R		Power Supply	<ul style="list-style-type: none"> ►Replaces 50-14000-241R ►Used to power 4-Slot Cradles, 5-Slot Cradles, and 20-Slot MC33 Spare Battery Charger. ►100-240VAC, 12VDC, 9A ►Energy Star Compliant ►Discontinued 2/2017, now use PWR-BGA12V108W0WW - PMB 2851 and 2933 	50-16002-029R and 23844-00-00R
50-14001-004R		Power Supply	<ul style="list-style-type: none"> ►Discontinued 12/2007 - replaced by 50-14000-241R ►Used to power 4-Slot Cradles, 5-Slot Cradles, and 20-Slot MC33 Spare Battery Charger. 	50-16002-029R and 23844-00-00R
50-14000-241R		Power Supply	<ul style="list-style-type: none"> ►Replaces 50-14001-004R ►Used to power 4-Slot Cradles, 5-Slot Cradles, and 20-Slot MC33 Spare Battery Charger. ►Discontinued 12/2010 - now use PWRS-14000-241R 	50-16002-029R and 23844-00-00R
23844-00-00R		AC Line Cord		
50-16000-182R		AC Line Cord	Used with 50-14000-147R/50-14000-249R/PWRS-14000-249R/PWR-BUA5V16W0WW	

<p>PWR-WUA5V12W0US (US plug style) PWR-WUA5V12W0GB (UK plug style) PWR-WUA5V12W0EU (EU plug style) PWR-WUA5V12W0AU (Australia plug style) PWR-WUA5V12W0CN (China plug style) PWR-WUA5V12W0IN (India plug style) PWR-WUA5V12W0KR (Korea plug style) PWR-WUA5V12W0BR (Brazil plug style)</p>		<p>USB Power Supply</p>	<ul style="list-style-type: none"> ►Used with MC33 Charge/Communication Cable (CBL-MC33-USBCHG-01) to charge device. ►Provides higher current (2.5A) for faster charging ►100-240 VAC, 5 V, 2.5 A 	
<p>CHG-AUTO-USB1-01 CHG-AUTO-USB1-BR (for Brazil)</p>		<p>USB Cigarette Lighter Adapter</p>	<ul style="list-style-type: none"> ►Can be used to charge MC33 from USB snap-on cable. ►Includes two USB A ports providing higher current (2.5A) for faster charging 	
<p>KT-32665-02R</p>		<p>UBC Adapter Power Supply</p>	<ul style="list-style-type: none"> ►Used to power a single UBC Adapter (21-32665-xxR) when not using the UBC Charging Station. ►Includes Power Supply (50-14001-013R), DC Cable (50-16002-004R), and 4 rubber bumper feet to attach to bottom of UBC adapter. ►Discontinued May 2013 	<p>23844-00-00R</p>
<p>KT-32665-03R</p>		<p>UBC Adapter Power Supply (International)</p>	<ul style="list-style-type: none"> ►Discontinued 11/2011 ►Used to power a single UBC Adapter (21-32665-xxR) when not using the UBC Charging Station. ►Includes Power Supply (50-14001-006R), DC Cable (50-16002-004R), and 4 rubber bumper feet to attach to bottom of UBC adapter. 	<p>23844-00-00R</p>

Batteries

Part Number	Picture	Description	Notes	Required Items
<p>BTRY-MC33-27MA-01 (single) BTRY-MC33-27MA-10 (10 pack) BTRY-MC33-27MA-IN (for use in India)</p>		<p>MC33 Spare Standard Capacity Battery with PowerPrecision Plus (2740 mAh)</p> 	<ul style="list-style-type: none"> ►Designed, manufactured & tested to meet rigorous controls & standards ►Premium-grade cells with higher capacity & longer life cycle ►Designed to help prevent overcharging & electrical shock ►Strong & robust housing for optimal performance & durability ►Information available: <ul style="list-style-type: none"> - Advanced state of Charge (shows the remaining battery power based on two factors: present charge and present real-time usage patterns of the device. - Advanced State of Health (highly accurate end-of-life prediction) - Dynamic usage patterns are constantly calculated, factoring in criteria such as the applications that are in use and scanning frequency). ►Only compatible with MC33, except MC33 RFID units. 	

<p>BTRY-MC33-52MA-01 (single) BTRY-MC33-52MA-10 (10 pack)</p> <p>BTRY-MC33-52MA-IN (for use in India)</p>		<p>MC33 Spare High Capacity Battery with PowerPrecision Plus (5200 mAh)</p> 	<ul style="list-style-type: none"> ►Designed, manufactured & tested to meet rigorous controls & standards ►Premium-grade cells with higher capacity & longer life cycle ►Designed to help prevent overcharging & electrical shock ►Strong & robust housing for optimal performance & durability ►Information available: <ul style="list-style-type: none"> - Advanced state of Charge (shows the remaining battery power based on two factors: present charge and present real-time usage patterns of the device). - Advanced State of Health (highly accurate end-of-life prediction) - Dynamic usage patterns are constantly calculated, factoring in criteria such as the applications that are in use and scanning frequency). ►Only compatible with MC33, including MC33 RFID units. 	
<p>BTRY-MC33-70MA-01 (single) BTRY-MC33-70MA-10 (10 pack)</p>		<p>MC3300R (RFID) Spare Extended Capacity Battery with PowerPrecision Plus (7000 mAh)</p> 	<ul style="list-style-type: none"> ►Designed, manufactured & tested to meet rigorous controls & standards ►Premium-grade cells with higher capacity & longer life cycle ►Designed to help prevent overcharging & electrical shock ►Strong & robust housing for optimal performance & durability ►Information available: <ul style="list-style-type: none"> - Advanced state of Charge (shows the remaining battery power based on two factors: present charge and present real-time usage patterns of the device). - Advanced State of Health (highly accurate end-of-life prediction) - Dynamic usage patterns are constantly calculated, factoring in criteria such as the applications that are in use and scanning frequency). ►Only intended to be used with MC3300R (RFID) devices. ►Increases run time of MC3300R an additional 1.5 hours vs. 5200 mAh battery. 	
<p>BTRY-MC31-PPSTD-01</p>		<p>MC3100 Spare 1X Battery with PowerPrecision (2740 mAh)</p> 	<ul style="list-style-type: none"> ►Supports PowerPrecision battery management application ►Compatible with MC3100 units ►Works on Straight Shooter and Rotating Head configuration units only. 	
<p>BTRY-MC3XKAB0E BTRY-MC3XKAB0E-10 (10 pack) BTRY-MC3XKAB0E-50 (50 pack)</p>		<p>MC3000/MC3100 Spare 1X Battery (2740 mAh)</p>	<ul style="list-style-type: none"> ►Compatible with MC3000 or MC3100 units ►Works on Straight Shooter and Rotating Head configuration units only. 	

<p>BTRY-MC30KAB0E</p> <p>BTRY-MC30KAB0E-10 (10 pack)</p> <p>BTRY-MC30KAB0E-50 (50 pack)</p>		<p>MC3000/MC3100 Spare 1X Battery (2740 mAh)</p>	<ul style="list-style-type: none"> Discontinued May 2010, now use BTRY-MC3XKAB0E Compatible with MC3000 or MC3100 units Works on Straight Shooter and Rotating Head configuration units only. 	
<p>BTRY-MC32-01-01</p> <p>BTRY-MC32-01-10 (10 pack)</p>		<p>MC3200 Spare 1X Battery with PowerPrecision (2740 mAh)</p> 	<ul style="list-style-type: none"> Works with all MC32XX configurations only Supports PowerPrecision battery management application Also compatible with MC33, except MC33 RFID units. 	
<p>BTRY-MC31-PPEXT-01</p>		<p>MC3100 Spare 2X High Capacity Battery with PowerPrecision (4800 mAh)</p> 	<ul style="list-style-type: none"> Supports PowerPrecision battery management application Works with all MC31XX configurations only Does not use pull tab 	
<p>BTRY-MC31KAB02</p> <p>BTRY-MC31KAB02-10 (10 pack)</p>		<p>MC3100 Spare 2X High Capacity Battery (4800 mAh)</p>	<ul style="list-style-type: none"> Works with all MC31XX configurations only Does not use pull tab 	
<p>BTRY-MC30KAB02-03</p> <p>BTRY-MC30KAB03-10 (10 pack)</p> <p>BTRY-MC30KAB03-50 (50 pack)</p>		<p>MC3000/MC3100 Spare 2X High Capacity Battery (4800 mAh)</p>	<ul style="list-style-type: none"> Works with all MC30xx/MC31xx configurations except MC31xx Gun, although it is recommended to use BTRY-MC31KAB02 with MC31XX configurations. Used with MC3190-Z (RFID) unit Battery has pull tab for easy removal from device. Purchase Battery Door KT-82600-01R for MC30XX straight shooter and rotating head configurations or Battery Door Kit KT-93480-01R for MC30XX Gun configurations. Discontinued 11/2017 - PMB 3049 	
<p>BTRY-MC32-52MA-01</p> <p>BTRY-MC32-52MA-10 (10 pack)</p>		<p>MC3200 Spare 2X High Capacity Battery with PowerPrecision (5200 mAh)</p> 	<ul style="list-style-type: none"> Works with MC32xx configurations only Supports PowerPrecision battery management application Also compatible with MC33, including RFID units. 	
<p>BTRY-MC32-02-01</p> <p>BTRY-MC32-02-10 (10 pack)</p>		<p>MC3200 Spare 2X High Capacity Battery with PowerPrecision (4800 mAh)</p> 	<ul style="list-style-type: none"> Discontinued 8/2016, now use BTRY-MC32-52MA-01/BTRY-MC32-52MA-10 - PMB 2840 Works with MC32xx configurations only Supports PowerPrecision battery management application Also compatible with MC33, including RFID units. 	
<p>BTRY-MC30KAB02-02</p> <p>BTRY-MC30KAB02-10 (10 pack)</p> <p>BTRY-MC30KAB02-50 (50 pack)</p>		<p>MC3000/MC3100 Spare 2X High Capacity Battery (4400 mAh)</p>	<ul style="list-style-type: none"> Discontinued May 2010, now use BTRY-MC30KAB02-03 Works with all MC30xx/MC31xx configurations except MC31xx Gun Battery has pull tab for easy removal from device. Purchase Battery Door KT-82600-01R for MC30XX straight shooter and rotating head configurations or Battery Door Kit KT-93480-01R for MC30XX Gun configurations. 	

BTRY-MC30KAB02		MC3000 Spare 2X High Capacity Battery (4400 mAH)	<ul style="list-style-type: none"> Discontinued 3/18/08 - replaced by BTRY-MC30KAB02-02 Works with ALL MC3090G Gun Configurations and with MC30x0 Brick IMAGER Configurations Battery has pull tab for easy removal from device. 	
KT-82599-01R		MC30XX 1X Battery Door, Strap, and Stylus	<ul style="list-style-type: none"> Discontinued 10/2011 Works on MC30XX Straight Shooter and Rotating Head configuration units only. 	
KT-82600-01R		MC30XX 2X Battery Door, Strap, and Stylus	<ul style="list-style-type: none"> Discontinued 10/2011 Works on MC30XX Straight Shooter and Rotating Head configuration units. 	
KT-93480-01R		High Capacity Battery Door Kit for MC30xx-G (Gun)	<ul style="list-style-type: none"> Discontinued 10/2011 Works on MC30XX Gun configuration only Includes 2x battery door and handstrap. 	
KT-128372-01R		MC31xx Brick or Turret Head 1X Battery Door Kit	Discontinued 11/2011	
KT-128373-01R		MC31xx Brick or Turret Head 2X Battery Door	Only includes 2x battery door (no handstrap or stylus)	
KT-128374-01R		MC31xx Gun 2X Battery Door	Only includes 2x battery door (no handstrap or stylus)	