



RF360  
Europe GmbH

## SDST (SAW DEVICE SELECTION TABLE)

### SAW RF filter and resonator

Automotive Electronics

Automotive Applications: Remote Keyless Entry Systems  
Tire Pressure Monitoring Systems  
Automotive Telematics Applications  
GPS in Automotive Applications  
Digital Radio Applications

Non Automotive Applications: Garage Door Openers  
Wireless Switches & Smart Home Applications  
Smart Grid Applications  
Wireless Audio Applications  
Security and Alarm Systems  
Wireless Access & Tagging Systems  
Medical Applications

Content:	1. Narrowband Filters for ISM	3
	2. Wideband Filters for ISM	4
	3. Filter for GNSS	6
	4. Filter for Telematics Communication (se/se)	8
	5. Diplexers, band-stop filters and extractors for GNSS, digital radio and metering	10
	6. Bandpass filters for Digital Radio	11
	7. Resonators for ISM	12

RF360 products mentioned within this document are products of RF360 Europe GmbH and other subsidiaries of RF360 Holdings Singapore Pte. Ltd. (collectively, the "RF360 Subsidiaries").

RF360 Europe GmbH, Anzinger Str. 13, Munchen, Germany  
© 2019-2020 RF360 Europe GmbH and/or its affiliated companies. All rights reserved.

These materials, including the information contained herein, may be used only for informational purposes by the customer. The RF360 Subsidiaries assume no responsibility for errors or omissions in these materials or the information contained herein. The RF360 Subsidiaries reserve the right to make changes to the product(s) or information contained herein without notice. The materials and information are provided on an AS IS basis, and the RF360 Subsidiaries assume no liability and make no warranty or representation, either expressed or implied, with respect to the materials, or any output or results based on the use, application, or evaluation of such materials, including, without limitation, with respect to the non-infringement of trademarks, patents, copyrights or any other intellectual property rights or other rights of third parties.

No use of this documentation or any information contained herein grants any license, whether express, implied, by estoppel or otherwise, to any intellectual property rights, including, without limitation, to any patents owned by QUALCOMM Incorporated or any of its subsidiaries.

Not to be used, copied, reproduced, or modified in whole or in part, nor its contents revealed in any manner to others without the express written permission of RF360 Europe GmbH.

Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries. Other product and brand names may be trademarks or registered trademarks of their respective owners.

This technical data may be subject to U.S. and international export, re-export, or transfer ("export") laws. Diversion contrary to U.S. and international law is strictly prohibited.

**Narrowband Filter for ISM (high temperature stability)**

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
169.5	B39171 <b>B3942</b> U310		0.20	1.9	5*5		<a href="#">B3942</a>
313.15			0.20	2.6			
314.00	B39311 <b>B3534</b> A410		0.20	2.7	3.8*3.8	Triplexer	<a href="#">B3534</a>
314.925			0.39	2.7			
313.15	B39311 <b>B3535</b> A410		0.20	2.3	3.8*3.8	Diplexer	<a href="#">B3535</a>
314.00			0.20	2.3			
313.15	B39311 <b>B3538</b> H110		0.18	2.6	3*3	Diplexer	<a href="#">B3538</a>
314.00			0.18	2.3			
313.85	B39314 <b>B3931</b> H110		0.76	2.3	3*3	Wide passband	<a href="#">B3931</a>
313.85	B39311 <b>B3768</b> Z810		0.36	1.9	3.8*3.8		<a href="#">B3768</a>
313.15	B39311 <b>B3955</b> H110	obsolete	0.18	2.2	3*3	Comb filter	
314.00			0.18	2.2			
313.85	B39321 <b>B3787</b> A410		0.76	2.6	3.8*3.8	Comb filter	<a href="#">B3787</a>
315.00			0.36	2.7			
313.85	B39321 <b>B3958</b> H110	obsolete	0.76	2.6	3*3	Comb filter	
315.00			0.36	2.7			
314.45	B39311 <b>B3950</b> H110		1.10	2.2	3*3		<a href="#">B3950</a>
314.45	B39311 <b>B3784</b> Z810		1.10	1.9	3.8*3.8		<a href="#">B3784</a>
314.90	B39311 <b>B3739</b> H110		0.36	2.3	3*3		<a href="#">B3739</a>
315.00	B39321 <b>B3741</b> H110		0.36	2.1	3*3		<a href="#">B3741</a>
315.00	B39321 <b>B3761</b> Z810		0.36	1.9	3.8*3.8		<a href="#">B3761</a>
315.00	B39321 <b>B3781</b> Z810		0.55	1.7	3.8*3.8		<a href="#">B3781</a>
315.00	B39321 <b>B3783</b> Z810		1.10	1.9	3.8*3.8		<a href="#">B3783</a>
400.00	B39401 <b>B3742</b> H110		0.25	2.3	3*3		<a href="#">B3742</a>
426.08	B39431 <b>B3770</b> Z810		0.15	2.0	3.8*3.8		<a href="#">B3770</a>
433.20			0.18	2.8			
433.92	B39431 <b>B3532</b> A410		0.26	2.9	3.8*3.8	Triplexer	<a href="#">B3532</a>
434.64			0.18	2.9			
433.20	B39431 <b>B3537</b> H110		0.18	2.3	3*3	Diplexer	<a href="#">B3537</a>
434.64			0.18	2.3			
433.20	B39431 <b>B3533</b> A410		0.18	2.3	3.8*3.8	Diplexer	<a href="#">B3533</a>
434.64			0.18	2.4			
433.42	B39431 <b>B3735</b> H110		0.36	2.1	3*3		<a href="#">B3735</a>
433.42	B39431 <b>B3791</b> Z810		0.24	3.8	3.8*3.8	external coupling coil; high ultimate rejection	<a href="#">B3791</a>
433.58	B39431 <b>B3536</b> A410		0.30	2.5	3.8*3.8	Diplexer	<a href="#">B3536</a>
434.30			0.30	2.6			
433.60	B39431 <b>B3953</b> H110		0.6	2.1	3*3		<a href="#">B3953</a>
433.92	in dev.	new	0.36	0.6-1.2	2.5*2.0		
433.92	B3301	new	0.34	1.9	3*3	2-5 pinning	<a href="#">B3301</a>
433.92	B39431 <b>B3732</b> H110		0.36	2.4	3*3	high selectivity at fc-2 MHz	<a href="#">B3732</a>
433.92	B39431 <b>B3743</b> H110		0.34	1.9	3*3	low insertion attenuation	<a href="#">B3743</a>
433.92	B39431 <b>B3760</b> Z810		0.36	1.9	3.8*3.8		<a href="#">B3760</a>
433.92	B39431 <b>B3774</b> Z810		0.36	2.4	3.8*3.8	high selectivity at fc-2 MHz	<a href="#">B3774</a>
433.92	B39431 <b>B3790</b> Z810		0.12	3.6	3.8*3.8	external coupling coil; high ultimate rejection	<a href="#">B3790</a>
433.92	B39431 <b>B3780</b> Z810		0.55	2.0	3.8*3.8		<a href="#">B3780</a>
433.92	B39431 <b>B3782</b> Z810		1.10	2.2	3.8*3.8	high usable bandwidth	<a href="#">B3782</a>
433.92	B39431 <b>B3951</b> H110		1.10	2.2	3*3		<a href="#">B3951</a>
433.92	B39431 <b>B3933</b> H110		0.12	3.1	3*3	high nearby rejection	<a href="#">B3933</a>
433.92	B39431 <b>B3935</b> H110		1.06	2.2	3*3	high usable bandwidth	<a href="#">B3935</a>
433.92	B39431 <b>B3936</b> H110		0.55	2.2	3*3		<a href="#">B3936</a>
434.17	B39431 <b>B3932</b> H110		0.78	2.4	3*3		<a href="#">B3932</a>
434.42	B39431 <b>B3733</b> H110		0.36	2.1	3*3	high selectivity at fc-2 MHz	<a href="#">B3733</a>
434.42	B39431 <b>B3748</b> H110		0.36	1.9	3*3		<a href="#">B3748</a>
868.30	B39871 <b>B3734</b> H110		0.30	3.2	3*3	high RFID rejection	<a href="#">B3734</a>
868.30	B39871 <b>B3744</b> H110		0.60	3.0	3*3		<a href="#">B3744</a>
868.60	B39871 <b>B3746</b> H110		1.20	2.6	3*3		<a href="#">B3746</a>
868.95	B39871 <b>B3941</b> H110		0.50	3.2	3*3		<a href="#">B3941</a>
869.30	B39871 <b>B3749</b> H110		1.40	2.7	3*3		<a href="#">B3749</a>
902.875	B39901 <b>B3934</b> H110		1.55	2.4	3*3		<a href="#">B3934</a>
916.50	B39921 <b>B3300</b> H110		1.20	2.7	3*3		<a href="#">B3300</a>
921.42	B39921 <b>B3949</b> H110		0.30	3.4	3*3	Z-Wave	<a href="#">B3949</a>
924.15	B39921 <b>B3419</b> U410		7.10	2.0	3*3	low IL; low amplitude ripple	<a href="#">B3419</a>
928.35	B39931 <b>B3758</b> H110		0.50	3.6	3*3		<a href="#">B3758</a>

## Wideband Filter for ISM

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
313.60	B39311B3403H110		3.3	1.5	3*3	50Ω; pinning 1-4	<a href="#">B3403</a>
313.85	B39311B3713U410		0.60	1.7	3*3	50Ω	<a href="#">B3713</a>
313.85	B39311B3729H110		1.0	1.5	3*3	50Ω; pinning 1-4	<a href="#">B3729</a>
314.35	B39311B3714U410		0.60	1.9	3*3	50Ω	<a href="#">B3714</a>
314.45	B39182B2607P810	new	1.3	1.1	1.8*1.4	Filter with focus on harmonics suppression and very low IL	<a href="#">B2607</a>
315.00	B39321B3719H110		1.0	1.4	3*3	50Ω; pinning 1-4	<a href="#">B3719</a>
315.00	B39321B3722U410		1.0	1.5	3*3	50Ω	<a href="#">B3722</a>
315.00	B39321B3905U510		1.0	1.3	3*3	50Ω se/200Ω bal	<a href="#">B3905</a>
345.00	B39351B3408U410		0.8	2.5	3*3	50Ω	<a href="#">B3408</a>
428.00	B39431B3411U410		16.0	2.0	3*3	50Ω	<a href="#">B3411</a>
433.92	B39182B2608P810	new	1.3	1.1	1.8*1.4	Filter with focus on harmonics suppression and very low IL	<a href="#">B2608</a>
433.92	B39431B3710U410		1.7	2.0	3*3	50Ω	<a href="#">B3710</a>
433.92	B39431B3721U410		1.6	2.6	3*3	50Ω; high selectivity	<a href="#">B3721</a>
433.92	B39431B3727H110		1.7	2.8	3*3	50 Ω, pinning 1-4, high nearby rejection	<a href="#">B3727</a>
433.92	B39431B3900U410		0.4	1.2	3*3	50Ω	<a href="#">B3900</a>
433.92	B39431B3925U410		0.4	1.7	3*3	50Ω; high nearby rejection	<a href="#">B3925</a>
433.92	B39431B3402H110		0.3	1.7	3*3	50Ω; pinning 1-4	<a href="#">B3402</a>
447.70	B39451B3907U410		1.6	3.0	3*3	50Ω	<a href="#">B3907</a>
454.50	B39451B3422U410		2.0	2.8	3*3	50Ω	<a href="#">B3422</a>
480.00	B39481B3427U410	special	20.0	1.7	3*3	Rx co-design with Tx B3426 for duplexing	<a href="#">B3427</a>
505.00	B39511B3426U410	special	10.0	1.7	3*3	Tx co-design with Rx B3427 for duplexing	<a href="#">B3426</a>
480 / 505	in dev.	new	20 / 10	2.0 / 2.0	2.5*2.0	Duplexer	<a href="#">B3445</a>
760.00	B39761B3445U510	special	8.3	2.3	3*3	50Ω; High out-of-band attenuation; Temperature compensation	<a href="#">B3445</a>
760.00	B39761B3928U510		8.3	3.0	3*3	50Ω se/100Ω bal	<a href="#">B3928</a>
845.00	B39851B3438U410		12.0	1.4	3*3	high power for smart metering	<a href="#">B3438</a>
866.50	B39871B4377P810		7.0	2.3	1.4*1.1	improved LSB attenuation; small size	<a href="#">B4377</a>
866.50	B39871B3420U410	obsolete	7.0	1.8	3*3	high power durability	
866.50	B39871B3717U410		7.0	2.2	3*3	50Ω	<a href="#">B3717</a>
866.80	B39871B3441U410	special	2.4	3.4	3*3	50Ω; high nearby rejection Temperature compensation	<a href="#">B3441</a>
869.00	in dev.	special new	2.0	2.7	3*3	very high attenuation up to 70dB Temperature compensation, no AEC-Q200	
869.00	B39871B2600P810		14.0	1.6	1.4*1.1	Low-loss RF filter for smart metering	<a href="#">B2600</a>
869.00	B39871B3430U410		10.0	2.0	3*3	Low-loss RF filter for smart metering	<a href="#">B3430</a>
869.00	B39871B4365P810	special	2.0	2.5	1.4*1.1	no AEC-Q200; Temperature compensation	<a href="#">B4365</a>
869.00	B39871B3440U410	special	2.0	2.6	3*3	50Ω improved LTE suppr. Temperature compensation	<a href="#">B3440</a>
869.00	B39871B3725U410		2.0	2.5	3*3	50Ω; high nearby rejection	<a href="#">B3725</a>
869.00	B39871B3903U510		2.0	1.4	3*3	50Ω se/200Ω bal	<a href="#">B3903</a>
869.00	B39871B4316P810		2.0	2.0	1.4*1.1	50Ω; small size	<a href="#">B4316</a>
869.00	in dev.	new	2.0	1.9	1.4*1.1	no AEC-Q200, for indoor application	
869.00	in dev.	new	2.0	2.7	1.4*1.1	50Ω; small size	
872.00	B39871B3443U410	special	8.0	3.0	3*3	50Ω; extended passband Temp. Comp.	<a href="#">B3443</a>
908.50	B39911B3429U410		13.0	2.0	3*3	steep right skirt Rx co-design with B3433 for duplexing	<a href="#">B3429</a>
915.00	B39921B3434U410	new	10.0	2.2	3*3	steep right skirt	<a href="#">B3434</a>
915.00	B39921B3726U410		10.0	2.6	3*3	50Ω	<a href="#">B3726</a>
915.00	B39921B3435U410		12.0	1.6	3*3	low IL; se/bal	<a href="#">B3435</a>
915.00	B39921B4379U810		26.0	1.9	1.1*0.9	small size	<a href="#">B4379</a>
915.00	B39921B4301F210		26.0	1.5	1.4*1.1	50Ω; small size	<a href="#">B4301</a>
915.00	B39921B4344P810		26.0	2.8	1.4*1.1	50Ω; small size	<a href="#">B4344</a>
915.00	B39921B2672P810		26.0	1.1	1.4*1.1	no AEC-Q200, for indoor application	<a href="#">B2672</a>
915.00	B39921B3728U410		26.0	2.2	3*3	50Ω	<a href="#">B3728</a>
915.00	B39921B4317P810		26.0	1.7	1.4*1.1	50Ω se/200Ω bal	<a href="#">B4317</a>
915.00	B2625	new	26.0	1.7	1.4*1.1	50Ω	<a href="#">B2625</a>
915.00	B39921B2671P810	new	26.0	1.5	1.1*0.9	no AEC-Q200, for indoor application	<a href="#">B2671</a>
915.70	B39921B3432U410		5.8	0.6	3*3	50Ω; low IL 0.9dB max	<a href="#">B3432</a>
916.00	B39921B3718U410		3.5	2.4	3*3	50Ω	<a href="#">B2625</a>
921.50	B39921B2615P810	new	13.0	1.4	1.4*1.1	50Ω	<a href="#">B2615</a>

**Wideband Filter for ISM**

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
922.50	B39921 <b>B2619</b> P810	new	5.0	1.4	1.4*1.1	50Ω	<a href="#">B2619</a>
922.50	B39921 <b>B3407</b> U410		5.0	1.5	3*3	50Ω	<a href="#">B3407</a>
924.50	B39921 <b>B2616</b> P810	new	5.0	2.1	1.4*1.1	50Ω	<a href="#">B2616</a>
925.00	B39931 <b>B3446</b> U410	special	4.0	2.0	3*3	50Ω; Temperature compensation	<a href="#">B3446</a>
925.00	B39931 <b>B3919</b> U410		3.2	1.4	3*3	50Ω	<a href="#">B3919</a>
925.15	B39931 <b>B4336</b> P810		5.9	1.7	1.4*1.1	50Ω	<a href="#">B4336</a>
925.20	B39931 <b>B3926</b> U410		5.8	1.4	3*3	50Ω	<a href="#">B3926</a>
925.50	B39931 <b>B3433</b> U410	special	5.0	2.2	3*3	50Ω; Tx co-design with B3429 for Duplexing	<a href="#">B3433</a>
925.80	B39931 <b>B3916</b> U410		4.6	0.6	3*3	50Ω; low IL 0.9dB max	<a href="#">B3916</a>
925.80	B39931 <b>B3921</b> U410		4.6	1.6	3*3	50Ω; high selectivity	<a href="#">B3921</a>
2441.75	B39242 <b>B4347</b> P810		83.5	1.7	1.4*1.1	50Ω; Wifi filter with high suppression at SDARS	<a href="#">B4347</a>
2441.75	B39242 <b>B3918</b> U410		83.5	1.9	3*3	50Ω; Wifi filter with high suppression at SDARS	<a href="#">B3918</a>
2441.75	B39242 <b>B4360</b> P810		83.5	2.1	1.1*0.9	50Ω	<a href="#">B4360</a>
2442.00	B39242 <b>B4346</b> P810	special	79.0	1.9	1.4*1.1	50Ω BAW	<a href="#">Sales</a>
2442.00	B39242 <b>B2614</b> P810	new special	79.0	1.2-1.5	1.1*0.9	50Ω BAW	<a href="#">Sales</a>
2448.50	B39242 <b>B3912</b> U410		97.0	1.7	3*3	50Ω	<a href="#">B3912</a>

## Filter for GNSS

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
1166,22	1249,136	1207,5	B39122B2627P810	new	82.92	1.9-2.6	1.1*0.9	GNSS L5+E5+G3+L2+G2	<a href="#">Sales</a>
1166,45	1186,45	1176.45	B39122B3452U410		20	1.3	3*3	GNSS E5a (QZSS L5)	<a href="#">Sales</a>
1196	1250	1223	B39122B3596U410		54	2.0	3*3	GNSS E5b+G3+L2+G2; High selectivity; Low GDR; Dashboard	<a href="#">Sales</a>
1197	1249	1223	in dev.	new	52	1.0-1.3	1.1*0.9	GNSS E5b+G3+L2+G2; Low GDR; Low IA	<a href="#">Sales</a>
1197	1249	1223	B39122B2620P810	new	52	1.1-1.5	1.4*1.1	GNSS E5b+G3+L2+G2; Low GDR; High Att.	<a href="#">Sales</a>
1215	1254	1234,5	B39122B3439U410	new	39	1.5	3*3	GNSS L2+G2	<a href="#">Sales</a>
1273,75	1283,75	1278.75	B39132B3428U410		10	1.5	3*3	GNSS E6 (QZSS L6)	<a href="#">Sales</a>
1525	1559	1542.00	B39152B3421U410		34	1.4	3*3	GNSS L	<a href="#">B3421</a>
1525	1605,9	1565.50	in dev.	new	80.9	1.2-1.5	1.4*1.1	GNSS L+L1+E1+G1+B1; Low GDR; Low IA	
1525	1606	1565.50	B39232B3424U410		81	2.0	3*3	GNSS L+L1+E1+G1+B1 Low GDR; Dashboard	<a href="#">Sales</a>
1559	1582,5	1606	B2631	new	7	1.1	1.4*1.1	GNSS L1+E1+G1+B1 low GDR; Low IA	<a href="#">B3412</a>
1559	1616	1588.00	B39162B3412U410		57	1.8	3*3	GPS/Galileo/Glonass/BeiDou	<a href="#">B3412</a>
1559	1616	1587.50	B39162B3413U410		57	2.0	3*3	GPS/Galileo/Glonass/BeiDou improved ESD robustness	<a href="#">B3413</a>
1559	1606	1582.50	B39162B3415U410		47	2.0	3*3	GPS/Galileo/Glonass/BeiDou High att. at 1450 to 1525 MHz	<a href="#">B3415</a>
1559	1605,7	1582.35	B39163B3431B710		46.7	1.3-1.6	2.5*2	GPS/Galileo/Glonass/BeiDou	<a href="#">B3431</a>
1559,05	1605,89	1582.47	B39162B2617P810		46.8	0.8-1.4	1.4*1.1	GPS/Galileo/Glonass/BeiDou 50Ωse/100Ωbal; Low GDR	<a href="#">B2617</a>
1559,05	1605,89	1582.47	B39162B2618P810		46.8	1.4	1.1*0.9	GPS/Galileo/Glonass/BeiDou Out of Band selec.; post LNA	<a href="#">B2618</a>
1559,05	1605,89	1582.47	B39162B2611P810		46.8	0.9	1.1*0.9	GPS/Galileo/Glonass/BeiDou small size; low IL; pre LNA	<a href="#">B2611</a>
1559,05	1605,66	1582.40	B39162B4327P810		46.61	1.4	1.4*1.1	GPS/Galileo/Glonass/BeiDou	<a href="#">B4327</a>
1559,05	1605,89	1582.47	B39162B4348P810		46.8	0.8	1.4*1.1	GPS/Galileo/Glonass/BeiDou; Top =105C	<a href="#">B4348</a>
1559,05	1605,66	1582.40	B39162B4353P810		46.61	1.0-1.5	1.4*1.1	GPS/Galileo/Glonass/BeiDou; Top =125C	<a href="#">B4353</a>
1560	1606	1583.00	B39162B3423U410		46	2.0	3*3	GNSS L1+E1+G1+B1 High selectivity; Low GDR; Dashboard	<a href="#">B3423</a>
1560	1616	1588.00	B39162B3913U410		56	2.0	3*3	GPS/Galileo/Glonass/BeiDou	<a href="#">B3913</a>
1565	1606	1585.50	B39162B3519U410		41	1.9	3*3	GPS/Galileo/Glonass	<a href="#">B3519</a>
1565,42	1605,89	1585.60	B39162B3414U510		40.47	2.1	3*3	GPS/Galileo/Glonass 50Ωse/100Ωbal; High att. at 1625 MHz	<a href="#">B3414</a>
1571,42	1605,89	1588.65	B39162B3401B710		34.47	1.6	2*2.5	GPS/Galileo/Glonass	<a href="#">B3401</a>
1572,42	1578,42	1575.42	B39162B3524B710		6.0	1.4	2.5*2	GPS/Galileo; 50Ωse/50Ωse	<a href="#">B3524</a>
1572,42	1578,42	1575.42	B39162B3525U510	obsolete	6.0	2.8	3*3	GPS/Galileo 50Ωse/100Ωbal; high selectivity; post LNA	
1572,42	1578,42	1575.42	B39162B3923U410		6.0	1.3	3*3	GPS/Galileo; low IA; pre LNA	<a href="#">B3923</a>
1573,42	1605,89	1588.655	B39162B4310P810		34.47	1.5	1.4*1.1	GPS/Galileo/Glonass; Low IA; pre LNA	<a href="#">B4310</a>
1573,42	1605,89	1588.655	B39162B4313P810		34.47	1.6	1.4*1.1	GPS/Galileo/Glonass 50Ωse/100Ωbal; high selectivity; post LNA	<a href="#">B4313</a>
1573,92	1576,92	1575.42	B39162B4300F210		3.0	1.2	1.4*1.1	GPS/Galileo; low IA	<a href="#">B4300</a>
1574,397	1576,443	1575.42	B39162B3400U410		2.0	2.3	3*3	GPS/Galileo; High nearby rejection	<a href="#">B3400</a>
1574,42	1576,42	1575.42	B39162B3528U510		2.0	1.2	3*3	GPS/Galileo; 50Ωse/100Ωbal; low IA	<a href="#">B3528</a>
1574,42	1576,42	1575.42	B39162B4308P810		2.0	1.3	1.4*1.1	GPS/Galileo; 50Ωse/100Ωbal; low IA	<a href="#">B4308</a>

**Filter for GNSS****Diplexer / Comb filter**

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
1164	1218	1191	B39162B3504U410	new	54	2.0	3*3	GNSS L1+E1+G1+B1 / L5+E5+G3 comb filter	<a href="#">Sales</a>
1559	1606	1582.5			47	2.7			
1164	1250	1207	in dev.	new	86	2.4	3*3	GNSS L1+E1+G1+B1 / L5+E5+G3+L2 comb filter; High Attenuation; Low GDR	<a href="#">Sales</a>
1559	1606	1582.5			47	2.8			
1166.22	1186.68	1176.45	in dev.	new	20.46	1.6	3*3	GNSS L1+E1+G1+B1 / L5+E5a comb Filter; Low GDR	<a href="#">Sales</a>
1559	1607	1583			48	1.9			
1196	1250	1223	B3436	new	54	2.0	3*3	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb Filter; Low GDR	<a href="#">Sales</a>
1559	1606	1582.5			47	2.7			
1196	1249	1222.5	B39162B2621P810	new	53	2.7	1.5*1.1	GNSS L+L1+E1+G1+B1 / E5b+G3+L2+G2 comb filter; Low GDR	<a href="#">Sales</a>
1525	1606	1565.5			81	3.1			
1197	1249	1223	in dev.	new	52	1.6-2.2	1.5*1.1	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 diplexer; Low GDR; high Attenuation	<a href="#">Sales</a>
1559	1606	1582.5			47	1.4-2.2			
1570	1580	1575	B39162B3518H910		10	3.8	3*2.5	GPS/Glonass diplexer	<a href="#">Sales</a>
1597	1607	1602			10	3.6			

**Extractor / Band Stop filter**

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
1574.42	1605.89	see DS	B39162B4322P810		see DS	1.6 - 1.8	2*1.6	GPS/Glonass extractor	<a href="#">Sales</a>
1574.42	1605.89	see DS	B39162B3405H910		see DS	1.9 - 3.4	3*2.5	GPS/Glonass bal / Non-GPS/Glonass se	<a href="#">Sales</a>
1559.05	1605.89	see DS	B39162B3478H910	new	see DS	1.6 - 2.6	3*2.5	GPS/Glonass/Beidou extractor	<a href="#">Sales</a>
1565.42	1605.89	see DS	B39162B4340P810	new	see DS	1.6 - 2.4	2*1.6	GPS/Glonass/Beidou extractor	<a href="#">Sales</a>
1559.05	1605.89	see DS	B39162B4368P810	new	see DS	1.8 - 2.2	2*1.6	GPS/Glonass/Beidou extractor	<a href="#">Sales</a>
1572.42	1578.42	1575.42	B39162B3470H910	new	6	0.65 - 1.9	3*2.5	GPS band stop filter	<a href="#">Sales</a>

**Filter and Duplexer for Telematics Communication (se/se; 50Ω/50Ω)**

Band	Function	Center Frequency MHz	Type	Remark	Package size mm*mm	Feature	DS link
1	Duplexer	1950/2140	B39212 <b>B4425</b> P810		2.0*1.6	Improved isolation	<a href="#">B4425</a>
	(D)Rx filter	2140	B39212 <b>B4358</b> P810		1.4*1.1		<a href="#">B4358</a>
	(D)Rx filter	2140	B39212 <b>B4359</b> P810		1.4*1.1	High isolation next to skirt on Tx side	<a href="#">B4359</a>
2	Tx filter	1950	B39202 <b>B4309</b> P810		1.4*1.1		<a href="#">B4309</a>
	Duplexer	1880/1960	B39202 <b>B4431</b> P810		1.8*1.4		<a href="#">B4431</a>
	(D)Rx filter	1960	B39202 <b>B4366</b> P810		1.4*1.1		<a href="#">B4366</a>
3	Tx filter	1880	B39192 <b>B4315</b> P810		1.4*1.1		<a href="#">B4315</a>
	Duplexer	1747.5/1842.5	B39182 <b>B4421</b> P810		1.8*1.4		<a href="#">B4421</a>
	(D)Rx filter	1842.5	B39182 <b>B4361</b> P810	special	1.4*1.1	Temperature compensation	<a href="#">B4361</a>
4	Tx filter	1747.5	B39172 <b>B4331</b> P810		1.4*1.1		<a href="#">B4331</a>
	Duplexer	1732.5/2132.5	B39212 <b>B4424</b> P810		2.0*1.6		<a href="#">B4424</a>
	(D)Rx filter	2140	B39212 <b>B4358</b> P810		1.4*1.1		<a href="#">B4358</a>
5	Tx filter	1732.5	B39172 <b>B4307</b> F210		1.4*1.1		<a href="#">B4307</a>
	Duplexer	836.5/881.5	B39881 <b>B4422</b> P810		2.0*1.6		<a href="#">B4422</a>
	(D)Rx filter	881.5	B39881 <b>B4362</b> P810		1.4*1.1		<a href="#">B4362</a>
5/26	Tx filter	836.5	B39841 <b>B4311</b> P810		1.4*1.1		<a href="#">B4311</a>
	(D)Rx filter	876.5	B39781 <b>B2601</b> P810		1.1*0.9	small size	<a href="#">B2601</a>
	Duplexer	2535/2655	B39272 <b>B4418</b> P810		2.0*1.6		<a href="#">B4418</a>
7	(D)Rx filter	2655	B39272 <b>B2602</b> P810		1.1*0.9	small size	<a href="#">B2602</a>
	(D)Rx filter	2655	B39272 <b>B4357</b> P810		1.4*1.1		<a href="#">B4357</a>
	Tx filter	2535	B39252 <b>B4332</b> P810		1.4*1.1		<a href="#">B4332</a>
8	Duplexer	897.5/942.5	B39941 <b>B4432</b> P810		2.0*1.6		<a href="#">B4432</a>
	(D)Rx filter	942.5	B39941 <b>B2606</b> P810		1.1*0.9	small size	<a href="#">B2606</a>
	(D)Rx filter	942.5	B39941 <b>B4356</b> P810	special	1.4*1.1	B20 co-design, Temperature compensation	<a href="#">B4356</a>
11	(D)Rx filter	942.5	B39941 <b>B4363</b> P810		1.4*1.1		<a href="#">B4363</a>
	Tx filter	897.5	B39901 <b>B4330</b> P810		1.4*1.1		<a href="#">B4330</a>
	Duplexer	1438/1486	in dev.	new	2.0*1.6		
11/21	(D)Rx filter	1493.4	in dev.	new	1.1*0.9		
	Duplexer	707/742	B39741 <b>B4414</b> P810		2.0*1.6	including B13 Rx	<a href="#">B4414</a>
	Duplexer	707.5/737.5	B39741 <b>B4423</b> P810		2.0*1.6		<a href="#">B4423</a>
12/17	(D)Rx filter	737	B39731 <b>B2609</b> P810		1.1*0.9	small size	<a href="#">B2609</a>
	(D)Rx filter	737	B39741 <b>B4339</b> P810		1.4*1.1		<a href="#">B4339</a>
	Tx filter	707	B39711 <b>B4337</b> P810		1.4*1.1		<a href="#">B4337</a>
13	Duplexer	782/751	B39871 <b>B4420</b> P810		2.0*1.6		<a href="#">B4420</a>
	(D)Rx filter	751	B39751 <b>B4354</b> P810		1.4*1.1		<a href="#">B4354</a>
	(D)Rx filter	751	B39751 <b>B2613</b> P810		1.1*0.9		<a href="#">B2613</a>
12/13/17	Tx filter	782	B39781 <b>B4378</b> P810		2.0*1.6	High power durability (29dBm)	<a href="#">B4378</a>
	Tx filter	782	B39781 <b>B4319</b> P810		1.4*1.1		<a href="#">B4319</a>
	(D)Rx filter	742.5	B39741 <b>B2605</b> P810		1.4*1.1		<a href="#">B2605</a>
13/14	Tx filter	787.5	B39791 <b>B4341</b> P810		1.4*1.1		<a href="#">B4341</a>
	Duplexer	793	in dev.	new	1.8*1.4		
	(D)Rx filter	763	B39761 <b>B2626</b> P810	new	1.1*0.9		<a href="#">B2626</a>
14	Duplexer	847/806	B39851 <b>B4428</b> P810		2.0*1.6		<a href="#">B4428</a>
	(D)Rx filter	806	in dev.	new	1.1*1.4		
	(D)Rx filter	806	B39811 <b>B4355</b> P810	special	1.4*1.1	B8 co-design, Temperature compensation	<a href="#">B4355</a>
20	(D)Rx filter	806	B39811 <b>B4369</b> P810		1.4*1.1		<a href="#">B4369</a>
	Tx filter	847	B39851 <b>B4320</b> P810		1.4*1.1		<a href="#">B4320</a>
	Duplexer	1455.4/1503.4	B39152 <b>B4429</b> P810		2.0*1.6		<a href="#">B4429</a>
21	(D)Rx filter	1503.4	B39152 <b>B4374</b> P810		1.4*1.1		<a href="#">B4374</a>
	Duplexer	831.5/876.5	B39871 <b>B4430</b> P810		2.0*1.6		<a href="#">B4430</a>
26	(D)Rx filter	876.5	B39871 <b>B4376</b> P810		1.4*1.1		<a href="#">B4376</a>
	Duplexer lower	718/773	B39771 <b>B4426</b> P810		2.0*1.6		<a href="#">B4426</a>
28	Duplexer upper	733/788	B39791 <b>B4427</b> P810		2.0*1.6		<a href="#">B4427</a>
	(D)Rx filter	780.5	B39781 <b>B4373</b> P810	special	1.4*1.1	Temperature compensation	<a href="#">B4373</a>
29	(D)Rx filter	722.5	B39721 <b>B2603</b> P810		1.1*0.9	small size	<a href="#">B2603</a>
	(D)Rx filter	722.5	B39721 <b>B4370</b> P810		1.4*1.1		<a href="#">B4370</a>
30	(D)Rx filter	2355	B39242 <b>B2604</b> P810	new	1.1*0.9	small size	<a href="#">B2604</a>
	(D)Rx filter	2355	B39242 <b>B4371</b> P810		1.4*1.1		<a href="#">B4371</a>
32	(D)Rx filter	1474	B39152 <b>B4375</b> P810		1.4*1.1		<a href="#">B4375</a>



**Filter and Duplexer for Telematics Communication (se/se; 50Ω/50Ω)**

Band	Function	Center Frequency MHz	Type	Remark	Package size mm*mm	Feature	DS link
33/39+34	(D)Rx filter	1900 2017.5	B39202 <b>B4384</b> P810		1.5*1.1	2in1	<a href="#">B4384</a>
34	Rx filter	2017.5	in dev.		1.1*0.9		
38	Tx filter	2595	B39262 <b>B4343</b> P810		1.4*1.1	post-PA	<a href="#">B4343</a>
40	(D)Rx filter	2350	B39242 <b>B4352</b> P810		1.4*1.1		<a href="#">B4352</a>
	Tx filter	2350	B39242 <b>B4351</b> P810		2.0*1.6	50 Ω se IN / 50 Ω se OUT	<a href="#">B4351</a>
41	Rx	2593	B39262 <b>B4349</b> P810		2.0*1.6		<a href="#">B4349</a>
71	Duplexer	634.5/680.5	in dev.	new	2.0*1.6		
	(D)Rx filter	634.5	in dev.	new	1.4*1.1		

**Duplexer se/se for High Rx - Tx out-of-band isolation**

Band	Function	Center Frequency MHz	Type	Remark	Package size mm*mm	Feature	DS link
2	Duplexer	1880/1960	B39202 <b>B4412</b> P810		2.0*1.6		<a href="#">B4412</a>
3	Duplexer	1747.5/1842.5	B39182 <b>B4411</b> P810		2.0*1.6		<a href="#">B4411</a>
5	Duplexer	836.5/881.5	B39881 <b>B4416</b> P810		2.0*1.6		<a href="#">B4416</a>
7	Duplexer	2535/2655	B39272 <b>B4418</b> P810		2.0*1.6		<a href="#">B4418</a>
8	Duplexer	2535/2655	B39941 <b>B4410</b> P810		2.0*1.6		<a href="#">B4410</a>
12/17	Duplexer	707/737	B39741 <b>B4413</b> P810		2.0*1.6		<a href="#">B4413</a>
	Duplexer	707/742	B39741 <b>B4414</b> P810		2.0*1.6	including B13 Rx	<a href="#">B4414</a>
20	Duplexer	847/806	B39851 <b>B4409</b> P810		2.0*1.6		<a href="#">B4409</a>

**Di/Triplexer for Telematics application**

Band	Function	Center Frequency MHz	Type	Remark	Package size mm*mm	Feature	DS link
1+3+11/21	Rx filter	2140+1842.5+ 1493.4	B4389	new	1.8*1.4	Triplexer	<a href="#">Sales</a>
1+3+32	Rx filter	2140+1842.5+ 1474	in dev.	new	1.8*1.4	Triplexer	<a href="#">Sales</a>
2+4	Diplexer	1960 + 2132.5	B39212 <b>B4385</b> P810		1.5*1.1	optimized for carrier aggregation	<a href="#">Sales</a>
2/25+4/66	Diplexer	1962.5 + 2155	B39222 <b>B4387</b> P810	new	1.5*1.1	optimized for carrier aggregation	<a href="#">Sales</a>

**Diplexer, band-stop filter and extractor for GNSS, digital radio and metering**

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
725.50	B39731 <b>B3473</b> H910				3*2.5	DVB-T band-stop filter; LTE 700 Tx and Rx suppression	<a href="#">Sales</a>
725.50	B39731 <b>B3477</b> B510				3*3	LTE 700 Notch	<a href="#">Sales</a>
733.00	in dev.				3*2.5	Band-stop filter ISDB-T LTE 700Tx, band 18 and 19 suppression	
736.00	B39741 <b>B3481</b> B510	new			3*3	Band-stop filter for digital TV, band 8, 20, 28 suppression	<a href="#">Sales</a>
753.00	B39751 <b>B3480</b> B510	new			3*3	Band-stop filter for digital TV, band 8, 20, 28 suppression	<a href="#">Sales</a>
861.00	B39731 <b>B3479</b> B510				3*3	Band-stop filter ISDB-T; LTE 700Tx, band 18 and 19 suppression	<a href="#">Sales</a>
868.50	B39871 <b>B3448</b> U510				3*3	Telestart-Extractor; Temperature compensation	<a href="#">Sales</a>
924.30	B39921 <b>B3474</b> H910				3*2.5	Notch filter for 920 MHz Japan AMI band	<a href="#">Sales</a>
1575.00 2326.25	B39232 <b>B3526</b> U510		2.048 12.5	1.8 1.6	3*3	GPS/SDARS Diplexer	<a href="#">Sales</a>
1575.00 2332.50	B39232 <b>B3920</b> U510		6 25	1.2 1.4	3*3	GPS/SDARS Diplexer	<a href="#">Sales</a>
1592.21 2332.50	B39232 <b>B3927</b> U510		37.58 25	1.5 1.6	3*3	GPS/Glonass/SDARS Diplexer	<a href="#">Sales</a>
2332.50	B39232 <b>B3471</b> H910				3*2.5	SDARS band-stop filter	<a href="#">Sales</a>
2332.50	in dev.	new			1.5*1.1	SDARS band-stop filter	<a href="#">Sales</a>
2402.50	B39242 <b>B2610</b> P810	new special			1.5*1.1	Band-stop filter for SDARS and Wifi	<a href="#">Sales</a>
2436.00	B39242 <b>B2612</b> P810	new special	83.5		1.5*1.1	WLAN notch, 125C, Temperature compensation	<a href="#">Sales</a>

**Bandpass filter for Digital Radio**

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Standard	Feature	DS link
1472	B39152B1664U410		40	1.6	3.0*3.0	DMB (DAB), WorldSpace	50Ωse/50Ωse	<a href="#">B1664</a>
1472	B39152B1647U510		40	3.0	3*3	DMB (DAB), WorldSpace	50Ωse/100Ωbal	<a href="#">B1647</a>
1472	B39152B4325P810		40	1.5	1.4*1.1	DMB (DAB), WorldSpace	50Ωse/50Ωse	<a href="#">B4325</a>
1472	B39152B4326P810		40	2.2	1.4*1.1	DMB (DAB), WorldSpace	50Ωse/100Ωbal	<a href="#">B4326</a>
2332.50	B39232B3425U510		25	2.4	3*3	Sirius/XM Satellite Radio	50Ωse/100Ωbal	<a href="#">Sales</a>
2332.50	B39232B1669U410		25	2.4	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse	<a href="#">Sales</a>
2332.50	B39232B3404U410		25	0.6	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse; very low IL	<a href="#">Sales</a>
2332.50	B39232B3595U410		25	1.5	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse	<a href="#">Sales</a>
2332.50	B39232B3442U410	special	25	3.0	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse Temperature compensation	<a href="#">Sales</a>
2332.50	B39232B3416U410		25	0.47	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse; low IA	<a href="#">Sales</a>
2332.50	B39232B2622P810	new	25	0.33	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse	<a href="#">Sales</a>

**Resonator for ISM**

Center Frequency MHz	Type	Remark	Frequency Tolerance kHz	Frequency Tolerance ppm	Insertion Attenuation dB	Package size mm*mm	DS link
314.90	B39311R <b>994</b> H110		±25	±79	1.5	3.0*3.0	<a href="#">R 994</a>
315.00	B39321R <b>901</b> H110		±75	±238	1.5	3.0*3.0	<a href="#">R 901</a>
315.00	B39321R <b>1901</b> A310		±50	±159	1.4	3.0*3.0	<a href="#">R1901</a>
315.00	B39321R <b>1921</b> A310		±25	±79	1.5	3.0*3.0	<a href="#">R1921</a>
315.02	B39321R <b>993</b> H110		±25	±79	1.5	3.0*3.0	<a href="#">R 993</a>
315.04	B39321R <b>963</b> H110		±50	±159	1.4	3.0*3.0	<a href="#">R 963</a>
315.50	B39321R <b>903</b> H110		±75	±238	1.5	3.0*3.0	<a href="#">R 903</a>
319.508	B39321R <b>1952</b> A310		±75	±50	1.5	3.0*3.0	<a href="#">R1952</a>
433.92	in dev.	new	±75	±173	1.4	2.5*2.0	
433.92	B39431R <b>920</b> H110		±75	±173	1.4	3.0*3.0	<a href="#">R 920</a>
433.92	B39431R <b>1920</b> A310		±25	±58	1.4	3.0*3.0	<a href="#">R1920</a>
433.94	B39431R <b>992</b> H110		±25	±58	1.5	3.0*3.0	<a href="#">R 992</a>
434.42	B39431R <b>969</b> H110		±50	±115	1.3	3.0*3.0	<a href="#">R 969</a>
868.35	B39871R <b>1950</b> A310		±150	±173	1.2	3.0*3.0	<a href="#">R1950</a>
915.00	B39921R <b>2906</b> H110		±250	±273	7.2	3.0*3.0	<a href="#">R2906</a>
1176.00	B39122R <b>959</b> H110	obsolete	±300	±255	1.3	3.0*3.0	