

A55M-DGS

AMD A55 FCH (Hudson-D2)

ASRock
www.asrock.com



Product Brief

- Solid Capacitor for CPU Power
- Support for Socket FM1 100W processors
- Supports Dual Channel DDR3 2400+(OC)
- Supports AMD Dual Graphics
- 5.1 CH HD Audio (Realtek ALC662 Audio Codec), Supports THX TruStudio™
- Supports PCIE Gigabit LAN
- Supports XFast RAM, XFast LAN, XFast USB Technology
- Supports AMD Steady Video™ : New video post processing capability for automatic jitter reduction on home/online video
- Free Bundle : CyberLink MediaEspresso 6.5 Trial ; ASRock MAGIX Multimedia Suite

Detail Specification

Platform	- Micro ATX Form Factor: 8.8-in x 6.8-in, 22.4 cm x 17.3 cm - Solid Capacitor for CPU power
CPU	- Support for Socket FM1 100W processors - Supports AMD's Cool 'n' Quiet Technology - UMI-Link GEN2
Chipset	- AMD A55 FCH (Hudson-D2)
Memory	- Dual Channel DDR3 memory technology - 2 x DDR3 DIMM slots - Supports DDR3 2400+(OC)/1866/1600/1333/1066/800 non-ECC, un-buffered memory - Max. capacity of system memory: 16GB
Expansion Slot	- 1 x PCI Express 2.0 x16 slot - 1 x PCI slot - Supports AMD Dual Graphics
Graphics	- AMD Radeon HD 65XX/64XX graphics in Llano APU - DirectX 11, Pixel Shader 5.0 - Max. shared memory 512MB - Dual VGA Output: support DVI-D and D-Sub ports by independent display controllers - Supports DVI with max. resolution up to 1920x1200 @ 60Hz - Supports D-Sub with max. resolution up to 1920x1600 @ 60Hz - Supports AMD Steady Video™: New video post processing capability for automatic jitter reduction on home/online video - Supports HDCP function with DVI port - Supports Full HD 1080p Blu-ray (BD) / HD-DVD playback with DVI port
Audio	- 5.1 CH HD Audio (Realtek ALC662 Audio Codec) - Supports THX TruStudio™
LAN	- PCIE x1 Gigabit LAN 10/100/1000 Mb/s - Realtek RTL8111E - Supports Wake-On-LAN - Supports LAN Cable Detection - Supports Energy Efficient Ethernet 802.3az - Supports PXE
Rear Panel I/O	I/O Panel - 1 x PS/2 Mouse Port - 1 x PS/2 Keyboard Port - 1 x D-Sub Port - 1 x DVI-D Port - 4 x Ready-to-Use USB 2.0 Ports - 1 x RJ-45 LAN Port with LED (ACT/LINK LED and SPEED LED) - HD Audio Jack: Line in / Front Speaker / Microphone
Connector	- 4 x SATA2 3.0 Gb/s connectors, support RAID (RAID 0, RAID 1 and RAID 10), NCQ, AHCI and "Hot Plug" functions - 1 x IR header - 1 x CIR header - 1 x Print port header - 1 x COM port header - 1 x CPU Fan connector (4-pin) - 1 x Chassis Fan connector (4-pin) - 1 x Power Fan connector (3-pin) - 24 pin ATX power connector - 4 pin 12V power connector - Front panel audio connector - 2 x USB 2.0 headers (support 4 USB 2.0 ports)
BIOS Feature	- 32Mb AMI UEFI Legal BIOS with GUI support - Supports "Plug and Play" - ACPI 1.1 Compliance Wake Up Events - Supports jumperfree - SMBIOS 2.3.1 Support - CPU, DRAM, VDDP, SB Voltage Multi-adjustment
Support CD	- Drivers, Utilities, AntiVirus Software (Trial Version), AMD Live! Explorer, CyberLink MediaEspresso 6.5 Trial, ASRock MAGIX Multimedia Suite - OEM
Unique Feature	- ASRock Extreme Tuning Utility (AXTU) - ASRock Instant Boot - ASRock Instant Flash - ASRock APP Charger - ASRock SmartView - ASRock XFast USB - ASRock XFast LAN - ASRock XFast RAM - Hybrid Booster: - ASRock U-COP
Hardware Monitor	- CPU Temperature Sensing - Chassis Temperature Sensing - CPU/Chassis/Power Fan Tachometer - CPU Quiet Fan - CPU/Chassis Fan Multi-Speed Control - Voltage Monitoring: +12V, +5V, +3.3V, Vcore
OS	- Microsoft® Windows® 7 / 7 64-bit / Vista™ / Vista™ 64-bit / XP / XP 64-bit compliant
Certifications	- FCC, CE, WHQL - ErP/EuP Ready (ErP/EuP ready power supply is required)
Accessories	- Quick Installation Guide, Support CD, I/O Shield - 2 x SATA data cables

A55M-DGS

AMD A55 FCH (Hudson-D2)

ASRock
www.asrock.com



XFast RAM
Fully Optimize Memory Usage

XFast LAN
Faster Internet Access


XFast USB
Boosts up your USB speed



5X Faster for Photoshop Execution


XFast RAM will create a virtual disk from the system memory to boost the performance. For Photoshop, it can even perform 5X faster than before.

* The performance boost percentage may vary with a different configuration.



Lower Latency In Game

5X Faster
XFast LAN can lower latency in the game after setting online game priority higher.



USB Performance Comparison

5X Faster

The Most Powerful APU Graphics Ever

Configuration		
Model	ASRock A55M-DGS	Other A55 Motherboard
Chipset	Hudson D2	Hudson D2
CPU	AMD A8-3850 2.9 GHz	AMD A8-3850 2.9 GHz
RAM	Kingston DDRIII 2250 2GB*2	Kingston DDRIII 2250 2GB*2
VGA Card	ATI HD 6600	ATI HD 6600
HDD	Western Digital WD6402AAEX	Western Digital WD6402AAEX

Onboard APU Graphics Performance




50.82%
Surpassed Performance

3DMark Vantage (Performance)


ASRock A55M-DGS



Other A55 Motherboard



Dual Graphics Performance




20.90%
Surpassed Performance

3DMark Vantage (Performance)

ASRock A55M-DGS



Other A55 Motherboard



A55M-DGS

AMD A55 FCH (Hudson-D2)

ASRock
www.asrock.com

DDR3 2400+ Support


The World's Fastest A55 Motherboard With DDR3 2400+ Support



	Read	Write	Copy	Latency
Memory	11471 MB/s	11386 MB/s	13350 MB/s	42.2 ns
L1 Cache	106764 MB/s	52447 MB/s	19457 MB/s	0.9 ns
L2 Cache	26634 MB/s	23177 MB/s	23726 MB/s	3.1 ns
L3 Cache				

CPU Type: Dual-Core AMD A5-3530 (1 core, Socket FM1)
CPU Clock: 3300.0 MHz
CPU FSB: 125.0 MHz (original: 100 MHz) (multiplier: 25x)
CPU Multiplier: 25x
CPU Stepping: 00

Memory Bus: 1300.0 MHz
Memory Type: Dual Channel DDR3-2400
Channel: AMD Radeon 2, AMD 012
Motherboard: A55 FCH



ASRock A55M-DGS MB


DDR3 2400+

Other A55 MB
DDR3 1866



AMD Dual Graphics

The AMD Dual Graphics technology combines APU and GPU computing power to optimize user's visual experience.



AMD Steady Video™ THX TruStudio

New Video Post Processing Capability : automatic jitter reduction on home/online video.



Delivering the fullest audio experience for games, music and movies.



Cyberlink MediaEspresso 6.5 Trial

The fastest video media conversion software



MAGIX Multimedia Suite

The ultimate solutions to enhance your media experience. From music management, music creation, video editing to photo management. Simply do more with your media than you ever thought possible.



SmartView

The smart start page for IE that combines your most visited web sites, history, Facebook friends and real-time newsfeed.



App Charger

The best Apple charge companion

