



# SAP R/3 PM Training Maintenance Processing

## Summary

- Notification
- Work Order
- Completion Confirmation



Chapter...


Notification

## SAP R/3 PM Notification

- Notification are requests for maintenance activities
- Notification are created automatically by maintenance plans or manually by the capture of failure or maintenance request
- Notifications documented the description of failures and maintenance activities
- Normally you have 1:1 relation between notification and work orders
- After the maintenance activities the relevant actions and cause codes are documented
- Notifications are the basis for the technical reporting and the generation of key performance indicators (KPI)

# SAP R/3 PM Notification

## SAP Easy Access




### Transaction IW51 Create

The notification type describe different maintenance requests. Each notification type can be contain different information fields.

Exemplary notification types:

Error Report	Z0
Maintenance Request	Z1
Malfunction Report	Z2
Activity Report	Z3
Prev. Maintenance report	Z4

### Create PM Notification: Initial Screen



# SAP R/3 PM Notification

## Create PM Notification: Maintenance Request

The screenshot shows the SAP R/3 PM Notification creation interface. Red arrows point to the following fields:

- Notification ID:** %00000000001 Z1
- Functional loc. (Reference object):** [Empty field]
- Planner group (Responsibilities):** [Empty field]
- Object part (Item):** [Empty field]

Other visible fields include:

- Status: OSNO
- Order: [Empty field]
- Required Start: 03.06.2010 08:03:49
- Required End: [Empty field] 00:00:00
- Priority: [Empty field]
- Main WorkCtr: [Empty field]
- Reported by: [Empty field]
- Notif. date: 03.06.2010 08:03:49
- Object part, Damage, Cause code, Cause text: [Empty fields]

At the bottom, it shows "Entry 1 frm 0".

Edit first the description and select the relevant technical object (FL or EQ).  
Press ENTER  
All stored information will be complete.

Then you can edit

- Object Part
- Damage
- Cause code

These information you can select from catalogs.

At the register Additional Data you can stored a detailed description of the failure.

# SAP R/3 PM Notification

Responsibilities	
Planner group	<input type="text"/> / <input type="text"/>
Main WorkCtr	<input type="text"/> / <input type="text"/>
Reported by	<input type="text"/>

Item	
Object part	<input type="text"/> <input type="text"/>
Damage	<input type="text"/> <input type="text"/>
Text	<input type="text"/>
Cause code	<input type="text"/> <input type="text"/>
Cause text	<input type="text"/>

Catalog Selection	
Object part	Object parts
ZALLG	general types of object parts
▶ 0010	not available, please use text
▶ 0020	axle
▶ 0030	engine
▶ 0040	break
▶ 0050	cage

Catalog selection

Select one relevant item with double click.

You have catalogs for:

- Object Part
- Damage
- Cause Code
- Activities

Save your entries.

Responsibilities	
Planner group	<input type="text"/> / <input type="text"/>
Main WorkCtr	<input type="text"/> / <input type="text"/>
Reported by	<input type="text"/>


Item	
Object part	<input type="text"/> <input type="text"/>
Damage	<input type="text"/> <input type="text"/>
Text	<input type="text"/>
Cause code	<input type="text"/> <input type="text"/>
Cause text	<input type="text"/>

Catalog Selection	
Damage	Overview of damage
ZALLG	general reasons for damages
▶ 0010	not available, please use text
▶ 0020	crack
▶ 0030	deformation
▶ 0040	leakage
▶ 0050	fouling

# SAP R/3 PM Change Notification

## SAP Easy Access




Transaction IW22 - Change

If it is necessary than you can change the notification.

If you know the notification number than you can use this transaction.

The most used transaction will be list editing.


## Change PM Notification: Initial Screen





# SAP R/3 PM Change Notification

## SAP Easy Access



Transaction IW28 - Change

The list editing are used for the creation of the notification list.  
Select the technical object and the selection period.

## Change Notifications: Selection of Notifications

The screenshot shows the 'Change Notifications: Selection of Notifications' dialog box. The 'Notification status' section has 'Outstanding' and 'In process' checked. The 'Notification selection' section has 'Functional location' and 'Notification date' circled in red. The 'Notification date' field shows '05.03.2010' to '03.06.2010'. The 'Cls.' button is visible at the bottom right.

Field	Value	Operator	Value
Notification		to	
Notification type		to	
Functional location		to	
Equipment		to	
Material		to	
Serial number		to	
Addit. device data		to	
Order		to	
Notification date	05.03.2010	to	03.06.2010
Partners			

# SAP R/3 PM

## Change Notification

### Change Notifications: List of Notifications

S	Notif.date	Notification	Order	Description	Typ	Functional loc.	Description of functional location	Equipment	Description of technical object
	17.02.2010	10000092	700020	Test Rückmeldung unb. ungeplant	Z2	200-10-10-10-1	Stanzanlage 1.1	100006	Stanzautomat 1.1
	17.02.2010	10000093		Zu Auftrag 7000202 - Status EROF	Z0	200-10-10-10-1	Stanzanlage 1.1		
	18.02.2010	10000096		xchdtgjzktul	Z2	200-10-10-10-1	Stanzanlage 1.1	100006	Stanzautomat 1.1
	19.02.2010	10000100		Zu Auftrag 7000202 - Status EROF	Z0	200-10-10-10-1	Stanzanlage 1.1		
	29.04.2010	10000124	700029	Schleifmaschine gewechselt	Z2	200-45-10-20	Technologie Schleifen		
	06.05.2010	10000127		Störung Klappe 1	Z2	20-10-005-020-	Schmelztiegel		
	10.05.2010	10000128		Störung Ofenlinie	M2	20-10-005-010	Vorlegierungssofen (LGO)		
	11.05.2010	10000130		Störung Klappe 1	Z2	20-10-005-060-	Rührwerksklappe		
	11.05.2010	10000132		Lagerbock Ventilator 2 Streichen	Z1	20-10-005-060-	Rührwerk		
	18.05.2010	10000135	700030		Z2	2000-10-10-010	SMT 1		
	27.05.2010	10000136	700030	Störung Klappe 1	Z0	20-10-005-010-	Rührwerksklappe		
	27.05.2010	10000137	700030	Ofenklappe defekt	Z1	20-10-005-010-	Ofenzustellung		

From the list you can select the relevant notification with double click on the notification number.

#### REMARK:



If the selected parameter relevant for only one notification, than the system display the notification and not the notification list.

# SAP R/3 PM

## Release or complete Notification

### Change Notifications: List of Notifications

S	Notif.date	Notification	Order	Description	Typ	Functional loc.	Description of functional location	Equipment	Description of technical object
	17.02.2010	10000092	700020	Test Rückmeldung unb. ungeplant	Z2	200-10-10-10-1	Stanzanlage 1.1	100006	Stanzautomat 1.1
	17.02.2010	10000093		Zu Auftrag 7000202 - Status EROF	Z0	200-10-10-10-1	Stanzanlage 1.1		
	18.02.2010	10000096		xchdtgjzktul	Z2	200-10-10-10-1	Stanzanlage 1.1	100006	Stanzautomat 1.1
	19.02.2010	10000100		Zu Auftrag 7000202 - Status EROF	Z0	200-10-10-10-1	Stanzanlage 1.1		
	29.04.2010	10000124	700029	Schleifmaschine gewechselt	Z2	200-45-10-20	Technologie Schleifen		
	06.05.2010	10000127		Störung Klappe 1	Z2	20-10-005-020	Schmelztiegel		
	10.05.2010	10000128		Störung Ofenlinie	M2	20-10-005-010	Vorlegierungssofen (LGO)		
	11.05.2010	10000130		Störung Klappe 1	Z2	20-10-005-060	Rührwerksklappe		
	11.05.2010	10000132		Lagerbock Ventilator 2 Streichen	Z1	20-10-005-060	Rührwerk		
	18.05.2010	10000135	700030		Z2	2000-10-10-010	SMT 1		
	27.05.2010	10000136	700030	Störung Klappe 1	Z0	20-10-005-010	Rührwerksklappe		
	27.05.2010	10000137	700030	Ofenklappe defekt	Z1	20-10-005-010	Ofenzustellung		

Select one or more notification and then press the button release  or the button complete 

# SAP R/3 PM

## Release or complete Notification

The screenshot displays the SAP R/3 PM interface for a 'Malfunction Report'. The top menu bar includes 'Maintenance notification', 'Edit', 'Goto', 'Extras', 'Environment', 'System', and 'Help'. A dropdown menu is open under 'Functions', with the 'Complete...' option (Shift+F4) highlighted. The main window shows a notification for 'Z2 Male Function' with status 'NOPR ORAS' and order '7000303'. Below this, the 'Change PM Notification: Malfunction Report' window is visible, showing notification details and reference object information.

**Malfunction data**

Malfunct. start	18.05.2010	11:16:46	<input type="checkbox"/> Breakdown
Malfunct. end		00:00:00	<input type="checkbox"/> Breakdown

**Change PM Notification: Malfunction Report**

Notification	10000135	Z2 Male Function
Status	NOPR ORAS	
Order	7000303	

**Reference object**

Functional loc.	2000-10-10-010	SMT 1
Equipment		
Assembly		

Use the menu path for complete the notification

or you can click on the button



# SAP R/3 PM Notification

Tutorial
----------

Create Notification	IW21
Create Notification from the Structural Display	IH01
Change Notification	IW22
Change Notification from List	IW28
Modify Notification List	
Change Notification from the Structural Display	IH01
Close Notification	




Chapter...

Work Order

## **SAP R/3 PM Work Order**

- The maintenance activities in the SAP-system are done with work order and notification. The work order is the cost collector and in the notification the technical history will be saved.
- A work order is not only a cost collector. The work steps needed for a repair can be planned in it manually or with a task list as well.
- In a work order you can plan the repair dates and times as well as responsible persons (own or external), needed materials or services (stock or non-stock).
- For every planned service or non-stock material one or more purchase requisitions will be generated.


# SAP R/3 PM Work Order





# SAP R/3 PM Work Order

## SAP Easy Access



The order type control the accounting of work orders.


Preventive Maintenance	Z000
Planned Maintenance	Z001
Unplanned Maintenance	Z002
Investment	Z003
Regular requirements	Z004
Other Service, not maintenance	Z005
Remodeling, construction, improvement	Z006
Construction of spare part	Z007

## Create Order: Initial Screen

The screenshot shows the 'Create Order: Initial Screen' in SAP. The 'Order Type' field is checked, and a red arrow points to it from the text above. The 'Restrictions' tab is active, showing a list of order types. The 'Type' column is highlighted in yellow for Z000.

Type	Name
Z000	preventive maintenance
Z001	planned maintenance
Z002	unplanned maintenance
Z003	investment
Z004	regulatory requirement
Z005	other services, not maintenance
Z006	remodelling, optimisation, improvement
Z007	construction of spare parts

# SAP R/3 PM Work Order



The screenshot shows the SAP R/3 PM 'Structure List' interface. The menu bar includes 'List', 'Edit', 'Goto', 'Extras', 'Environment', 'Settings', 'System', and 'Help'. The 'Goto' menu is open, showing options: 'Create notification', 'Create order' (highlighted), 'Graphic...', and 'Back'. The main area displays a tree view of technical objects for 'Plant MSEI'. The object '2000-10-10-010' is selected and highlighted in yellow. A red arrow points from the 'Goto' menu to this selected object.

Functional loc.	2000	Valid F
Description	Plant MSEI	
2000	Plant MSEI	
2000-10	module mfg	
2000-10-10	Assembly	
2000-10-10-010	SMT 1	
2000-10-10-020	SMT 2	
2000-10-10-030	Cell 2	
2000-10-10-040	Cell 4	
2000-10-20	Incoming	
2000-10-30	Test	
2000-10-40	Fault Isolation	
2000-10-60	MRB and Rework	


Transaction IH01 – Structural Display


Select the technical object from the structure.

Open the menu “Goto” and create order

# SAP R/3 PM Work Order

**Create Order: Initial Screen**

Header data 

Order Type  

Priority

Func. Loc.  SMT 1

Equipment

Assembly

Plng plant

Bus. Area

Reference

Order   Relationship

Select the Order type

The relation to the technical object are automatically selected.

# SAP R/3 PM Work Order

## Create planned maintenance : Central Header

The screenshot shows the SAP R/3 PM Work Order Central Header form. The form is divided into several sections:

- Order Data:** Order (Z001 %000000000001), Sys. Status (CRTD MANC NTUP).
- Person responsible:** PlannerGrp ( / Z100), Mn.wk.ctr ( / ), Notifctn, Costs (EUR), PMActType (EAU single order), SystCond.
- Dates:** Bsc start (03.06.2010), Basic fin. (03.06.2010), Priority, Revision.
- Reference object:** Func. Loc. (2000-10-10-010 SMT 1), Equipment, Assembly.
- First operation:** Operation, WkCtr/Plnt ( / Z100), Ctrl key (ZM01), Acty Type, Work durtn (H), Number, Oprtn dur. (H), Person. no.

Red arrows point to the following fields:

- Order description field (yellow background)
- Mn.wk.ctr field
- Equipment field
- WkCtr/Plnt field

Edit the relevant data

Description

Main Work Center

Work Center

# SAP R/3 PM Work Order

## Create planned maintenance : Operation Overview

OpAc	SOp	Work ctr	Plant	Co...	StTextK	S...	Operation short text	LT	Work	Un	N...	Dur.	Un	CcKey
0010		Z-MECH	Z100	ZM01			Test for Training			2H	1		2H	Calculate work
0020		Z-ELEK	Z100	ZM01						H			H	
0030		Z-ELEK	Z100	ZM01						H			H	
0040		Z-ELEK	Z100	ZM01						H			H	
0050		Z-ELEK	Z100	ZM01						H			H	

Edit the relevant data

Select the work center

If you have more then one maintenance activities with different work centers, than you can plan the steps.


Edit the planned duration for each task.

You can switch between internal and external work with the control key.

Save the work order.

# SAP R/3 PM Change Work Order


## SAP Easy Access



Transaction IW32 – Change

The last created or modified work order are displayed as proposal value.

Press ENTER



# SAP R/3 PM Change Work Order

**Change planned maintenance 7000309: Central Header**

Order: Z001 7000309 | Test for Training

System Status: CRTD NMAT PRC SETC

Person responsible:  
 PlannerGrp: / Z100  
 Mn.wk.ctr: Z-ELEK / Z100 (Group of electrician)  
 Notifctn:   
 Costs:  EUR  
 PMActType: EAU (single order)  
 SystCond.:

Dates:  
 Bsc start: 03.06.2010 | Priority: 2-High  
 Basic fin.: 03.06.2010 | Revision:

Reference object:  
 Func. Loc.: 2000-10-10-010 | SMT 1  
 Equipment:   
 Assembly:

First operation:  
 Operation: Test for Training | CckKey: Calculate work  
 WkCtr/Pint: Z-MECH / Z100 | Ctrl key: ZM01 | Acty Type: Z\_HWS |  PRT  
 Work durtn: 2 H | Number: 1 | Oprtn dur.: 2 H |  Comp.  
 Person. no:

Change or add data


Release the work order with the button



Save the work order

# SAP R/3 PM Order List

## SAP Easy Access



Transaction IW38 – Change / IW39 – Display

Create the order list with following selection parameters:

Order status: outstanding, in progress  
 Functional Location: 2000\*  
 Period: 01.01.2010 - today


## Change PM Orders: Selection of Orders

The screenshot shows the 'Change PM Orders: Selection of Orders' dialog box. The 'Order status' section has 'Outstanding' and 'In process' checked. The 'Order selection' section shows 'Functional location' as '2000\*' and 'Period' as '01.01.2010' to '03.06.2010'. Other fields include 'Order', 'Order Type', 'Equipment', 'Material', 'Serial number', 'Addit. device data', 'Notification', 'Main work center', 'Plant for WorkCenter', 'Partners', and 'Currency'.



# SAP R/3 PM Order List

## Change PM Orders: List of Orders



The screenshot shows the SAP R/3 PM Order List interface. At the top, there is a toolbar with various icons for navigation and actions. Below the toolbar is a table with the following columns: S, Order, Type, Bsc start, and Description. The table contains three rows of data.

S	Order	Type	Bsc start	Description
	7000294	Z002	01.06.2010	Repair Oven 2
	7000303	Z001	27.05.2010	test
	7000309	Z001	03.06.2010	Test for Training

Select one work order with double click on the order number.

# SAP R/3 PM Work Order

**Change planned maintenance 7000309: Cost Overview**

Complete (business)

Order Z001 7000309 Test for Training

Sys.Status REL NMAT PRC SETC

HeaderData Operations Components **Costs** Objects Addit. Data Locat

Estimated costs 0,00 EUR

Val.in Object Curr. EUR  
 Val.in CoAreaCurr. EUR

Rep. Plan/Act. Rep. Budget/Commit.

Overview Costs Quantities Key figures

Group/Dscrip...	Est. costs	Plan costs	Act. costs	C...
Costs	0,00	90,00	0,00	E...
Z10	0,00	90,00	0,00	E...

At the cost overview you can see the planned costs.

If you want change the settlement rule then press the button



Save and exit.

# SAP R/3 PM Order List

## Change PM Orders: List of Orders

S	Order	Type	Bsc start	Description
	7000294	Z002	01.06.2010	Repair Oven 2
	7000303	Z001	27.05.2010	test
✓	7000309	Z001	03.06.2010	Test for Training

If you have not released work orders at these list, then can you mark one or more and press the button



# SAP R/3 PM Modify Order List

## Change PM Orders: List of Orders

The screenshot shows the SAP R/3 PM 'Change PM Orders: List of Orders' dialog box. The main dialog has a toolbar with various icons, including a button with a document and a plus sign (indicated by a red arrow). Below the toolbar is a table of orders:

S	Order	Type	Bsc start	Description
	7000294	Z002	01.06.2010	Repair Oven 2
	7000303			
✓	7000309			

The 'Change Layout' sub-dialog is open, showing two panes: 'Displayed Columns' and 'Column Set'. The 'Displayed Columns' pane lists: Column Name, Selected line, Order, Order Type, Basic start date, and Description. The 'Column Set' pane lists: Column Name, Order category, Currency, Entered by, Created on, Last changed by, Change date for order master, Long text exists, Company Code, Plant, Business Area, and Controlling Area. At the bottom of the sub-dialog are icons for OK, Save, and Cancel.

Press the button




Now you can create your own layout for these list.

If you want, then you can save the layout as variant.

# SAP R/3 PM Order List

## SAP Easy Access



Transaction IW38 – Change / IW39 – Display

Create the order list with following selection parameters:

Order status: outstanding, in progress

Functional Location: 2000\*

Period: 01.01.2010 - today


## Change PM Orders: Selection of Orders

The screenshot shows the 'Change PM Orders: Selection of Orders' dialog box. The 'Order status' section has 'Outstanding' and 'In process' checked. The 'Order selection' section has the following parameters:

Field	Value	Operator	Value
Order		to	
Order Type		to	
Functional location	2000*	to	
Equipment		to	
Material		to	
Serial number		to	
Addit. device data		to	
Notification		to	
Main work center		to	
Plant for WorkCenter		to	
Period	01.01.2010	to	03.06.2010
Partners			
Currency			

# SAP R/3 PM Order List

**Change PM Orders: List of Orders**



	S	Order	Type	Bsc start	Description
		7000294	Z002	01.06.2010	Repair Oven 2
		7000303	Z001	27.05.2010	test
		7000309	Z001	03.06.2010	Test for Training

Select one work order with double click on the order number.

# SAP R/3 PM Work Order

**Change planned maintenance 7000309: Central Header**

Complete (business)

Order: Z001 7000309 | Test for Training

System Status: REL NMAT PRC SETC

HeaderData | Operations | Components | Costs | Objects | Addit. Data | Location

**Person responsible**

PlannerGrp: / Z100 | Notifctn: | Costs: 0,00 EUR | PMActType: EAU single order | SystCond.:

Mn.wk.ctr: Z-ELEK / Z100 Group of electrician

**Dates**

Bsc start: 03.06.2010 | Priority: 2-High | Basic fin.: 03.06.2010 | Revision:

**Reference object**

Func. Loc.: 2000-10-10-010 SMT 1 | Equipment: | Assembly:


**First operation**

Operation: Test for Training | CcKey: Calculate work | WkCtr/Plnt: Z-MECH / Z100 | Ctrl key: ZM01 | Acty Type: Z\_HWS | Work durtn: 2 H | Number: 1 | Oprtn dur.: 2 H | Person. no:

For complete (technical) click on the button



# SAP R/3 PM Work Order



For complete (technical) you can also use the menu path.

## REMARK

If it is necessary to change information at the work order after the complete, then you can cancel the complete.



# SAP R/3 PM Work Order

Order Edit Goto Extras Environment System Help

**Create planner**

Order: Z001 %000  
Sys. Status: CRTD MAN

HeaderData

Person responsible  
PlannerGrp: /  
Mn.wk.ctr: Z-E1ek

Dates  
Bsc start: 03.06.2010  
Basic fin.: 03.06.2010

Reference object  
Func. Loc.: 2000-10-10-020 SMT 2  
Equipment:  
Assembly:

First operation  
Operation: CcKey: Calculate work  
WkCtr/Plnt: Z-Mech / Z100 Ctrl key: ZM01 Act Type: PRT  
Work durtn: H Number: Oprtn dur.: H Comp.  
Person. no:

Task list selection menu options:  
 - Direct entry  
 - To reference object  
 - General task lists for assembly  
 - General task lists for object structure  
 - **General task lists** (highlighted)  
 - Display task lists

Create a new work order with transaction IW31 or use the structural display.

You can attached to the work order an task list. Use the menu path.



# SAP R/3 PM Work Order


## Create planned maintenance : Operation Overview

OpAc	SOp	Work ctr	Plant	Co.	StTextK	S	Operation short text	LT	Work	Un	N..	Dur.	Un	CckKey	ActTyp
0010		Z-ELEK	Z100	ZM01			Sichtprüfung		0,5	H	1	0,5	H		Z_HWS
0020		Z-ELEK	Z100	ZM01			Messung Isolationswiderstand			H					Z_HWS
0030		Z-ELEK	Z100	ZM01			Dokumentation			H					Z_HWS
0040		Z-ELEK	Z100	ZM01			Kennzeichnung			H					Z_HWS
0050		Z-ELEK	Z100	ZM01						H			H		
0060		Z-ELEK	Z100	ZM01						H			H		
0070		Z-ELEK	Z100	ZM01						H			H		

The task list are attached and the operation are listed.

# SAP R/3 PM Order List

## SAP Easy Access



For the planning of the work load for the next month, you can create the order list with all work orders for the main work center, for the work center or an complete list.

Select at the screen the parameters

Example:

Overview for the months 01 – 06

Use the monitor to display the priority or the due - date


## Change PM Orders: Selection of Orders

The screenshot shows the 'Change PM Orders: Selection of Orders' screen. The 'Order status' section has 'Outstanding' and 'In process' checked. The 'Order selection' section shows various filters:





Order		to		
Order Type		to		
Functional location	2000*	to		
Equipment		to		
Material		to		
Serial number		to		
Addit. device data		to		
Notification		to		
Main work center		to		
Plant for WorkCenter		to		
Period	01.01.2010	to	30.06.2010	
Partners				
Currency				

# SAP R/3 PM Work Order

## Change PM Orders: List of Orders



The screenshot shows the SAP R/3 PM Work Order List of Orders interface. It features a toolbar with various icons for navigation and actions, including a search icon, a pencil icon, a refresh icon, a list icon, a document icon, a printer icon, a funnel icon, a bar chart icon, a calculator icon, an 'Order' button, a document with checkmark icon, a document with flag icon, a grid icon, an 'Operations' button, and a document with plus icon.

Monit...	S	Order	Type	Bsc start	Description
		7000294	Z002	01.06.2010	Repair Oven 2
		7000303	Z001	27.05.2010	test
		7000309	Z001	03.06.2010	Test for Training
		7000310	Z001	03.06.2010	Test for Training

Modify the list for you own requirements.

# SAP R/3 PM Work Order

## Tutorial

Create Work Order	IW31
Create Work Order from Structural Display	IH01
Change Work Order	IW32
Work Order List (Change Mode)	IW38
Release Work Order	IW32
Complete Work Order	IW32
Create Work Order with Task List	IW32
Create Report with Order List	IW39



Chapter...

Confirmation

# SAP R/3 PM Confirmation

## SAP Easy Access

The screenshot shows the SAP Easy Access navigation tree. The 'Logistics' folder is expanded, and 'Plant Maintenance' is selected. Under 'Plant Maintenance', 'Maintenance Processing' is expanded, and 'Completion Confirmation' is selected. The 'Entry' sub-menu is also expanded, and 'IW42 - Overall Completion Confirmation' is highlighted with a dashed border.

Transaction IW42 - Overall Completion Confirmation

You can edit the working time to the relevant operation.

The screenshot shows the SAP IW42 transaction interface. The title bar reads 'Overall Completion Confirmation'. The 'Order' field contains '7000310' and 'Test for Training'. The 'Oper./Act.' field is empty. The 'Tech.completion' button is visible. The 'Time confirmation' table is displayed below, showing a list of operations with their respective working times and dates.

Confirmation	Op...	Sub...	O	Act. Work	Unit	F	C	N	Work Ctr	Plant	ATy.	A...	Postg date	Pers. No.
1017	0010			0,50	H				Z-ELEK	Z100	Z_HWS		03.06.2010	
1018	0020			1	H				Z-ELEK	Z100	Z_HWS		03.06.2010	
1019	0030			1	H				Z-ELEK	Z100	Z_HWS		03.06.2010	
1020	0040			1	H				Z-ELEK	Z100	Z_HWS		03.06.2010	

The 'Goods movements' section is also visible, showing a 'Goods Movements Overview' table with columns for Material, Description, Quantity, U..., Plant, Stor., Batch, and Val.



# SAP R/3 PM Confirmation

## SAP Easy Access

- ▶ Favorites
- ▼ SAP menu
  - ▶ Office
  - ▶ Cross-Application Components
  - ▼ Logistics
    - ▶ Materials Management
    - ▶ Sales and Distribution
    - ▶ Logistics Execution
    - ▶ Production
    - ▶ Production - Process
    - ▼ Plant Maintenance
      - ▶ Management of Technical Objects
      - ▼ Maintenance Processing
        - ▶ Notification
        - ▶ Order
        - ▶ Compatible Units
        - ▶ Capacity Requirements Planning
        - ▼ Completion Confirmation
          - ▼ Entry
            - ◻ IW41 - Individual Time Confirmation
            - ▼ Collective Time Confirmation
              - ◻ IW44 - Without Selection
              - ◻ **IW48 - With Selection**
              - ◻ IW42 - Overall Completion Confirmation
            - ▶ Time Sheet
            - ◻ IW25 - Activity Report
          - ▶ Display

Transaction IW428- With Selection

Select the functional location.

## Confirmation using operation list: Selection of Order Operation

Compatible Unit ID	<input type="text"/>	to	<input type="text"/>	↔
Construction Measure Number	<input type="text"/>	to	<input type="text"/>	↔
Equipment	<input type="text"/>	to	<input type="text"/>	↔
Functional Location	<input type="text"/>	to	<input type="text"/>	↔

Order operation selection				
Work center	<input type="text"/>	to	<input type="text"/>	↔
Plant	<input type="text"/>	to	<input type="text"/>	↔
Order	<input type="text"/>	to	<input type="text"/>	↔
Order Type	<input type="text"/>	to	<input type="text"/>	↔
Reference date	<input type="text"/>	to	<input type="text"/>	↔
Operation/Activity	<input type="text"/>	to	<input type="text"/>	↔
Operation short text	<input type="text"/>	to	<input type="text"/>	↔
Functional location	2000*	to	<input type="text"/>	↔
Equipment	<input type="text"/>	to	<input type="text"/>	↔

# SAP R/3 PM Confirmation

## PM Order Confirmation: Collective Confirmation

Default Values																						
-->	Confirmation	Order	Op...	Sub...	C...	Sp...	Act. Work	Unit	F	C	N	Work ctr	Plnt	ATy.	A...	Postg date	Pers. No.	Wg...	Rem. Work	Unit	Fore	
Confirmations																						
C	Confirmation	Order	Op...	Sub...	C...	Sp...	Act. Work	Unit	F	C	N	Work Ctr	Plnt	ATy.	A...	Postg date	Pers. No.	Wg...	Rem. Work	Unit	Fore	
✓	991	7000294	0010				2	H				Z-MECH	Z100	Z_HWS		03.06.2010					H	
	1006	7000303	0010																			
	1016	7000309	0010																			
	1017	7000310	0010																			
	1018	7000310	0020																			
	1019	7000310	0030																			
	1020	7000310	0040																			

Edit the relevant data.

# SAP R/3 PM Confirmation

## Tutorial

Individual Time Confirmation	IW41
Overall Completion Confirmation	IW42
Collective Time Confirmation	IW48
Demonstration Optimized Confirmation	

**Thank you**



**P&S Consulting GmbH  
Am Kiekenbusch 10  
47269 Duisburg**

**Frank Ostwald  
Director Sales & Marketing  
Tel.: +49.203.75990.29  
E-mail: [frank.ostwald@ps-consulting.de](mailto:frank.ostwald@ps-consulting.de)  
[www.ps-consulting.de](http://www.ps-consulting.de)**

