

Manual for DO101

This product is a wireless switch that supports inching /self-locking mode. It has already been set on inching mode (turn on 1s and then auto-off) for garage door opener application.

Users can add the device to the APP eWeLink (available on both Android and iOS) in order to remotely control connected home appliances or devices, like garage door.

Supported functions include:

- Remotely turning On/Off
- Timing Schedules
- Device Sharing
- Group Management
- Works with Amazon Echo, Echo Dot, Amazon Tap
- Works with Google Home
- Works with Google Nest

Works With Amazon Alexa

This product works with Amazon Alexa. You can ask Alexa to control the device with the following voice commands.

Please note that only US/UK English and German voice commands are supported now.

Try out these phrases ({deviceName} should be the name of your device):

Alexa, turn on {deviceName} - Alexa, turn off {deviceName} - Alexa, turn {deviceName} off

Alexa, turn {deviceName} on - Alexa, schalte Gerätnamen ein - Alexa, schalte Gerätnamen aus

After downloading the app eWeLink, open the box and check the following diagram. Press and hold the bottom that shows in diagram beside the red light for 7Sec until LED blinks fast (it shows that the device is ready for pairing). Pressing other bottoms will change inching mode! Then follow up the app leads. After installing the app and making sure that the switch works correctly (clicking sound can be heard when turning the switch On/Off). Connect the two wires of this device either to the wall switch terminals of the main unit opener or directly to the wall switch.

power supply

12V
Adapter



Connect these wires either to the wall switch terminals of the main unit opener or directly to the wall switch